Radiative Cooling of Relativistic Electron Beams

Zhirong Huang

Stanford Linear Accelerator Center, Stanford University, Stanford, CA 94309

Work supported by Department of Energy contract DE-AC03-76SF00515.

Abstract

Modern high-energy particle accelerators and synchrotron light sources demand smaller and smaller beam emittances in order to achieve higher luminosity or better brightness. For light particles such as electrons and positrons, radiation damping is a natural and effective way to obtain low emittance beams. However, the quantum aspect of radiation introduces random noise into the damped beams, yielding equilibrium emittances which depend upon the design of a specific machine.

In this dissertation, we attempt to make a complete analysis of the process of radiation damping and quantum excitation in various accelerator systems, such as bending magnets, focusing channels and laser fields. Because radiation is formed over a finite time and emitted in quanta of discrete energies, we invoke the quantum mechanical approach whenever the quasiclassical picture of radiation is insufficient. We show that radiation damping in a focusing system is fundamentally different from that in a bending system. Quantum excitation to the transverse dimensions is absent in a straight, continuous focusing channel, and is exponentially suppressed in a focusing-dominated ring. Thus, the transverse normalized emittances in such systems can in principle be damped to the Compton wavelength of the electron, limited only by the Heisenberg uncertainty principle. In addition, we investigate methods of rapid damping such as radiative laser cooling. We propose a laser-electron storage ring (LESR) where the electron beam in a compact storage ring repetitively interacts with an intense laser pulse stored in an optical resonator. The laser-electron interaction gives rise to rapid cooling of electron beams and can be used to overcome the space charge effects encountered in a medium energy circular machine. Applications to the designs of low emittance damping rings and compact x-ray sources are also explored.

Acknowledgments

I could have doubled the length of this dissertation if I had recounted in detail how each of the following people have helped me throughout my graduate school period and the process of writing this dissertation. Instead, I have to condense my everlasting gratitude into these following paragraphs.

First of all, I am grateful to have Ron Ruth as my thesis advisor, who has provided me with direction, insight, motivation and support to obtain my Ph.D. at Stanford. Ron has been very patient in teaching and helping me whenever I have problems in my research. His precise intuition in physics and excellent leadership have steered a steady course for the completion of my dissertation.

I also feel very lucky to have both Alex Chao and Todd Smith to serve on my reading and defense committee. I have greatly benefited from their critical comments and careful reading of my dissertation. Special thanks to Alex for introducing me to, and guiding me through the field of beam physics. I would very much like to thank Richard Blankenbecler and Kosuke Ishii for serving on my defense committee. Sidney Drell has been very generous to me by offering his keen vision when he was on my reading committee, and by agreeing to withdraw from the committee because of the conflicting schedule.

I have enjoyed working with Pisin Chen, with whom I have the opportunity to learn about advanced accelerator concepts, and to discover the beauty of both physics and life. John Irwin has been very helpful to me, especially by providing me a nice working environment for finishing up my dissertation. I also appreciate the help from Dave Whittum, who volunteered to read through my dissertation and supplied with stimulating discussion. In addition, I would also like to extend my thanks to all the

people in Accelerator Research Departments at SLAC that have helped me through one way or another, and to the United State government which has supported my work here through the Department of Energy, under contract No. DE-AC03-76SF00515.

During these years at Stanford, I have made many friends and I would like to thank them all for making my time here so enjoyable. They are: Robert Chang, Yunzhong Chen, Eddie Lin, Hong Liu, Dennis Palmer, Jun Teng, Chunxi Wang, Xiaowei Zhan, Biao Zhang, and Xiaolei Zhu.

Finally, I would like to thank my entire family members for all their support and encouragement. Most importantly, I thank my wife Yanrong for her unconditional love and support. She and our lovely boy Jonathan have helped complete me as a human being.

Contents

Abstract	iv
Acknowledgments	v
1 Introduction	1
2 Beam Phase Space and Emittance	4
2.1 Canonical Phase Space and the Distribution Function	4
2.2 Liouville's Theorem and the Vlasov Equation	5
2.3 Beam Emittance	7
2.4 RMS Emittance	8
2.5 Beam Cooling and the Stationary Beam State	11
3 Radiation from Relativistic Electrons	13
3.1 Classical Theory of Radiation	15
3.1.1 Fields of a Moving Charged Particle	15
3.1.2 Angular Distribution of Radiated Power	18
3.1.3 Spectral Distribution of Radiated Power	21
3.1.4 Synchrotron Radiation	26
3.1.5 Radiation from Quasiperiodic Motions	30
3.2 Quantum Theory: An Introduction	36
4 Radiation Damping and Quantum Excitation	43
4.1 Electron Storage Rings	44

4.1.1	Introduction	44
4.1.2	Transverse Damping and Excitation	47
4.1.3	Longitudinal Damping and Excitation	54
4.2	Straight, Continuous Focusing Channels	56
4.2.1	Lack of Quantum Excitation and the Transverse Ground State	56
4.2.2	Asymmetric Damping	62
4.2.3	Comparison with Undulators	68
4.2.4	Generalizations and Practical Considerations	69
4.3	Periodic Focusing Channels	71
4.4	Bent Focusing Systems	81
4.4.1	Limitations of the Quasiclassical Approach	81
4.4.2	Suppression of Transverse Excitation	82
4.4.3	Longitudinal Considerations	93
4.4.4	A Focusing-dominated Damping Ring	96
5	Laser-Electron Storage Ring	98
5.1	Radiative Laser Cooling	99
5.2	Beam Dynamics in a LESR	101
5.2.1	Damping and Excitation in a Laser Field	102
5.2.2	Space Charge Effects	108
5.2.3	X-ray Generation	110
5.3	LESR Configurations and Applications	111
5.3.1	A Compact Damping Ring	112
5.3.2	An Intense X-ray Source	114
6	Conclusions and Future Work	116
A	Transverse Dynamics in a Storage Ring	119
A.1	Coordinate System	119
A.2	Transverse Hamiltonian	120
A.3	Dispersion Function	122
A.4	Betatron Oscillation	124

B Index of Symbols	127
Bibliography	134

List of Tables

5.1	Laser-Electron Storage Ring Paramters	113
-----	---	-----

List of Figures

3.1	The schematic drawing of the radiation emitted from a moving electron at the retarded time t'	15
3.2	The polar coordinates used in Section 3.1.2.	19
3.3	Radiation is formed in a characteristic length $l_r \sim \rho/\gamma$	22
3.4	Radiation is formed over the whole oscillation period.	23
3.5	The angles used in Section 3.1.4.	26
3.6	The universal function $S(x)$ for synchrotron radiation.	29
3.7	Geometry for undulator or channeling radiation.	32
4.1	The schematic drawing of the radiation reaction in a straight, continuous focusing channel.	61
4.2	The primed and the unprimed coordinate systems used for channeling motion	63
4.3	Evolution of the normalized transverse action J_x/J_{x0} and the normalized energy E/E_0 with the scaled time $\Gamma_c t$ for (a) $\gamma_0^2 \theta_{p0}^2 = 100$, (b) $\gamma_0^2 \theta_{p0}^2 = 1$ and (c) $\gamma_0^2 \theta_{p0}^2 = 0.1$	67
4.4	The focusing function in an idealized FODO lattice.	80
4.5	Contours of integration for Eqs. (4.179) and (4.180).	90
4.6	Horizontal and vertical quantum excitation rate in units of $\Gamma_b \hbar$, predicted by (a) the quasi-classical model, i.e., the second terms of Eqs. (4.189) and (4.190), and (b) the quantum mechanical perturbation approach, i.e., the second terms of Eqs. (4.187) and (4.188).	94
5.1	The coordinates for laser-electron interaction.	100

5.2	The schematic diagram of a laser-electron storage ring.	102
5.3	The laser-electron interaction region.	104
5.4	The geometry for x-ray generation.	115
A.1	The Frenet-Serret curvilinear coordinate system (x, s, y)	120
A.2	The Courant-Snyder invariant ellipse.	126

Chapter 1

Introduction

A particle beam is characterized by a set of quantifying parameters being either constants of motion or functions varying from point to point along a beam transport line. The parameters may be a single particle property like the betatron function which applies to all particles within a beam, or quantities that are defined only for a collection of particles like the beam emittance. While the betatron function depends upon the focusing structure of the beam transport line and can be altered by design, the emittance is a measure of the beam's phase space volume and is a constant of motion in the absence of nonlinear and dissipative effects. Together, they determine the structure of the beam. For example, the spot size and the angular divergence of a beam at a waist are given by

$$\sigma_{x,y} = \sqrt{\beta_{x,y}\varepsilon_{x,y}}, \quad \sigma'_{x,y} = \sqrt{\frac{\varepsilon_{x,y}}{\beta_{x,y}}}, \quad (1.1)$$

where $\beta_{x,y}$ is the beta function at the waist, and $\varepsilon_{x,y}$ is the beam emittance in the x or the y direction.

To have useful applications, an accelerator must be able to deliver beams of small spot size as well as small angular divergence. From Eq. (1.1), we see right away why low emittance beams (“cold” beams) are always desired. One can start with a relatively cold beam created from good particle sources such as RF guns. Alternatively, one can “cool” the relatively “warm” beam during the beam transit by introducing proper sources of dissipation into the accelerator system. Modern high-energy particle

accelerators and synchrotron light sources demand smaller and smaller beam emittances to achieve higher luminosity or better brightness. Thus, the study of cooling techniques to generate very low emittance particle beams is an increasingly important subject in beam physics research.

For light particles such as electrons and positrons, radiative cooling is a natural and effective way to achieve very low emittance beams. The study of radiative cooling is of major practical importance in the design and construction of cyclic electron accelerators and, especially, electron and positron storage rings. It is well known that the average effects of synchrotron radiation cause the emittances of the beam in all three degrees of freedom to damp towards equilibria, limited only by the fluctuating nature of quantum emissions. Thus, the equilibrium emittances achieved in a storage ring are the balance between radiation damping and quantum excitation. A smaller equilibrium emittance could be obtainable by reducing the rate of quantum excitation or increasing the rate of radiation damping. What is the ultimate emittance obtainable in a storage ring? The standard treatment of quantum excitation is quasiclassical, based on the approximation that the time associated with the emission of radiation quanta is short compared with the periods of the classical modes of oscillation in all three degrees of freedoms. What would happen to the rate of quantum excitation when this approximation is no longer valid? Is there any fast damping mechanism to rapidly cool the electron or positron beams? Understanding and resolving these problems constitute the core of this dissertation.

In this dissertation, we attempt to make a complete analysis of radiation damping and quantum excitation in various accelerator systems, such as bending magnets, focusing channels and laser fields. Due to the quantum nature of radiation, we invoke quantum mechanical approach whenever the quasiclassical picture of radiation is insufficient. New results on radiative cooling in the presence of strong focusing fields and intense laser pulses are obtained. Applications to the designs of low emittance electron beams and bright x-ray sources are also discussed.

The structure of this dissertation is as follows: after this short introductory chapter, Chapter 2 will introduce the fundamental concepts of phase space and beam

emittance. Chapter 3 will describe the theory of radiation—both classical and quantum mechanical. Chapter 4 will investigate in detail the different characteristics of radiation damping and quantum excitation between bending systems and focusing systems. A general treatment will be given based on quantum mechanical perturbation theory when both focusing and bending forces are present. Chapter 5 will be devoted to the discussion of laser-electron storage rings, where we apply radiative laser cooling to damp or stabilize electron beams in order to generate low emittance electrons or intense x-rays. Finally, Chapter 6 will draw conclusions based on the results obtained in this dissertation and lay out possible future work. A review on the transverse dynamics in storage rings and a list of symbols can be found in Appendix A and B.

We want to point out that the International System (MKS) is adopted in almost all the equations of this dissertation, except when they are expressed in practical units. Although the word “electron” is used most often in connection with radiation, all the results derived for the electron apply equally well to the positron¹. In fact, many of these results can also be applied to any relativistic, charged particle with proper substitutions of charge and mass. Finally, the references of this dissertation are organized in alphabetical order in the Bibliography. When referred in the body of the text, we follow the chronological order of the publications. Thus, the reference numbers do not appear sequentially.

¹For electrons, the charge $e = -1.6022 \times 10^{-19}$ C, and for positron, $e = +1.6022 \times 10^{-19}$ C.

Chapter 2

Beam Phase Space and Emittance

Emittance is a property of a distribution of particles in phase space. Its invariance arises from the invariants of the underlying dynamical system. In a conservative Hamiltonian system, the volume of phase space occupied by the beam is called the emittance because it is invariant by the virtue of Liouville's theorem. In a conservative linear system, the statistical definition of the RMS emittance is especially useful and is invariant because it is related to the expectation value of the single particle invariant action. In a damped linear system with random noise, which is the subject of this dissertation, it can be shown that the stationary distribution is a Gaussian in phase space. Thus, the RMS emittance is a good representation of the beam quality in such a system as it gives a measure of standard deviations for a Gaussian beam.

2.1 Canonical Phase Space and the Distribution Function

A beam of N particles is a system of $3N$ degrees of freedom if the internal degrees of freedom (like spin) can be neglected. The $3N$ coordinates q_i are the components of the coordinate vector $\mathbf{r}_j (j = 1, \dots, N)$ of each particle. In the absence of friction forces, the equations of motion can be written in the form of Hamilton:

$$\dot{q}_i = +\frac{\partial H}{\partial p_i}, \quad \dot{p}_i = -\frac{\partial H}{\partial q_i}, \quad i = 1, \dots, 3N \quad (2.1)$$

where the Hamiltonian $H(q_i, p_i, t)$ is a function of the coordinates q_i , the conjugate momenta p_i , and time t . If H does not explicitly depend on the time t , the Hamiltonian H is the total energy of the system that is invariant.

The canonical phase space is then the $6N$ -dimensional space with the conjugate coordinates $q_i, p_i (i = 1, \dots, 3N)$. The state of a beam at a time t is represented by a point with coordinates $q_i(t), p_i(t)$ in the canonical phase space. As t increases, the representative point generates a curve, called a phase trajectory.

When N particles are identical and noninteracting, the same Hamiltonian $H(\mathbf{q}, \mathbf{p}, t)$ is sufficient to describe each individual particle in the 6-dimensional canonical phase space $(\mathbf{q}, \mathbf{p})$. At a time t , the state of the beam is represented by the set of N points $M_j(t)$, where the point M_j corresponds to the particle $j (j = 1, \dots, N)$.

The N particles form a beam only if the N points are clustered in a relatively small volume of the 6-dimensional phase space. When N is large, the beam state can be represented by a phase space distribution density $f(\mathbf{q}, \mathbf{p}, t)$ such that at time t the number dN of representative points in an infinitesimal volume $d\mathbf{q}d\mathbf{p}$ is given by:

$$dN = f(\mathbf{q}(t), \mathbf{p}(t), t) d\mathbf{q}d\mathbf{p}. \quad (2.2)$$

In general, the distribution function $f(\mathbf{q}(t), \mathbf{p}(t), t)$ explicitly depends on the time t as the density does not stay constant at a particular point $M(\mathbf{q}, \mathbf{p})$.

2.2 Liouville's Theorem and the Vlasov Equation

In statistical mechanics, Liouville's theorem [50] applies to an ensemble of many systems, each containing N particles [21]. It describes the conservation of density of the ensemble in the $6N$ -dimensional phase space and applies to systems of either interacting or noninteracting particles.

In the context of beam physics, Liouville's theorem is applicable to a beam of particles when the interaction between particles is negligible, or when a particle interacts more strongly with the collective fields of the other particles than with its nearest neighbors [13]. In either case, the equations of motion for all particles are governed by a single conservative Hamiltonian $H(q_i, p_i, t)$. These particles are represented by

points with slightly different initial conditions in 6-dimensional phase space $(\mathbf{q}, \mathbf{p})$ and follow Hamilton's equations

$$\dot{\mathbf{q}} = +\frac{\partial H}{\partial \mathbf{p}}, \quad \dot{\mathbf{p}} = -\frac{\partial H}{\partial \mathbf{q}}. \quad (2.3)$$

One can view $\dot{\mathbf{q}}$ and $\dot{\mathbf{p}}$ as components of the velocity field $\mathbf{v} = (\dot{\mathbf{q}}, \dot{\mathbf{p}})$ at each instant of time in the phase space. Similar to the condition of incompressible flow in the fluid mechanics, the condition that phase space volume is preserved by the flow is equivalent to the vanishing of the divergence of the velocity field:

$$\nabla \cdot \mathbf{v} = \frac{\partial \dot{\mathbf{q}}}{\partial \mathbf{q}} + \frac{\partial \dot{\mathbf{p}}}{\partial \mathbf{p}} = \frac{\partial^2 H}{\partial \mathbf{p} \partial \mathbf{q}} - \frac{\partial^2 H}{\partial \mathbf{q} \partial \mathbf{p}} = 0, \quad (2.4)$$

which is automatically satisfied as a consequence of Hamilton's equations. Thus, the infinitesimal volume $d\mathbf{q}d\mathbf{p}$ is invariant in a conservative (time dependent or independent) Hamiltonian system. Since two particles having the same initial conditions must have exactly the same trajectory in phase space determined by the Hamilton's equations, it follows that the only way for two trajectories to meet at a given time is for them to coincide for all time. It is then clear that the number of particles within the volume remains constant because a particle initially inside can never get out the boundary which is formed by surrounding particles. From Eq. (2.2), we deduce that the phase space distribution function $f(\mathbf{q}(t), \mathbf{p}(t), t)$ is invariant as one follows the motion of the system. More precisely, the density at the point $M(t)$ is equal to the density at the transformed point $M(t')$ at another time t' :

$$f(\mathbf{q}(t), \mathbf{p}(t), t) = f(\mathbf{q}(t'), \mathbf{p}(t'), t'). \quad (2.5)$$

Or equivalently

$$\frac{df}{dt} = \frac{\partial f}{\partial t} + \frac{\partial f}{\partial \mathbf{q}} \dot{\mathbf{q}} + \frac{\partial f}{\partial \mathbf{p}} \dot{\mathbf{p}} = 0. \quad (2.6)$$

Eq. (2.6) is called the Vlasov equation [13].

With the use of Eq. (2.3), we can put Eq. (2.6) in the form

$$\begin{aligned} 0 = \frac{df}{dt} &= \frac{\partial f}{\partial t} + \frac{\partial f}{\partial \mathbf{q}} \frac{\partial H}{\partial \mathbf{p}} - \frac{\partial f}{\partial \mathbf{p}} \frac{\partial H}{\partial \mathbf{q}} \\ &\equiv \partial_t f + [f, H] \end{aligned} \quad (2.7)$$

where $[f, H]$ is the Poisson bracket. If the system is completely integrable, the transformation to action-angle variables

$$(\mathbf{q}, \mathbf{p}) \rightarrow (\boldsymbol{\phi}, \mathbf{J}) \quad (2.8)$$

can be found, in which the actions $\mathbf{J}$ are all invariant that do not involving time explicitly. Then the stationary distribution ($\partial_t f = 0$) must be a function of these invariant actions $\mathbf{J}$ [37].

2.3 Beam Emittance

Liouville's theorem allows one to characterize a beam of N particles by measuring the phase space volume it occupies. In a conservative Hamiltonian system, this volume is invariant.

Neglecting mutual interactions and coupling between the three coordinates of a particle, one can divide the 6-dimensional phase space into three separate 2-dimensional phase spaces: horizontal (x and p_x), vertical (y and p_y) and longitudinal (s and $\delta = \Delta E/E$). The beam phase space volume is then projected onto each degree of freedom as the beam phase space areas. The horizontal beam emittance ε_x is usually defined considering the $(x, x' = dx/ds)$ phase space, instead of the (x, p_x) canonical phase space because x' represents the angular divergence of the particle.

From Appendix A, a particle in a conservative linear system follows an ellipse in the (x, x') phase space characterized by the Courant-Snyder invariant W . Representative points of particles with the same Courant-Snyder invariant, but with different phases, are on the same ellipse at time t . Different ellipses correspond to different Courant-Snyder invariants. The area (usually divided by π) of the ellipse that encloses all or 95 % of the particles in its interior is then defined as the horizontal emittance ε_x ¹. It is also the product of the two semi-axes of the ellipse. If the ellipse is upright, its axes coincide with the x and x' axes. The two semi-axes are half the beam size Δx and the beam divergence $\Delta x'$ respectively. For a uniformly distributed

¹Sometimes the emittance defined in the (x, x') phase space is called the geometric emittance.

beam enclosed by an envelope ellipse described by the Courant-Snyder invariant W_0 , the horizontal beam emittance is simply given by

$$\varepsilon_x = W_0. \quad (2.9)$$

Similarly, one can define the emittance for the vertical and the longitudinal dimensions.

The emittance defined in the (x, x') phase space is not an invariant when acceleration is involved. To obtain the Liouville invariant phase space area, we should use the conjugate momentum p_x instead of x'

$$p_x = m_p c \beta \gamma x', \quad (2.10)$$

where m_p is the particle mass, γ is the kinetic energy of the particle in units of its rest energy $m_p c^2$, and

$$\beta = \sqrt{1 - \frac{1}{\gamma^2}} \quad (2.11)$$

is the velocity of the particle in units of the speed of light c . Thus, the normalized emittance defined by

$$\varepsilon_x^n = \beta \gamma \varepsilon_x \quad (2.12)$$

is an invariant of the beam in a Hamiltonian system, independent of the acceleration. As $\beta \gamma$ increases proportionally to the particle momentum p_x , the emittance ε decreases as $1/p_x$. This is called “adiabatic damping”. Because the transverse momentum p_x is not changed during the acceleration, while the total momentum p is changed, the transverse angle $x' = p_x/p$ becomes smaller and the geometric emittance becomes smaller.

2.4 RMS Emittance

When the particle distribution is not uniform, the above definition of emittance as the area of the phase space region containing a certain fraction of the total particles

suffers from the arbitrariness of the chosen fraction and the chosen boundary. An unambiguous and widely used definition of the beam emittance is based on the statistical point of view. Let us consider the two-dimensional (x, x') phase space: given an arbitrary but normalized distribution function $\hat{f}(x, x')$ with $\int \hat{f}(x, x') dx dx' = 1$, we define moments of the beam distribution

$$\begin{aligned}\langle x \rangle &= \int x \hat{f}(x, x') dx dx', & \langle x' \rangle &= \int x' \hat{f}(x, x') dx dx', \\ \sigma_x^2 &= \int (x - \langle x \rangle)^2 \hat{f}(x, x') dx dx', & \sigma_{x'}^2 &= \int (x' - \langle x' \rangle)^2 \hat{f}(x, x') dx dx', \\ \sigma_{xx'} &= \int (x - \langle x \rangle)(x' - \langle x' \rangle) \hat{f}(x, x') dx dx',\end{aligned}\tag{2.13}$$

where σ_x and $\sigma_{x'}$ are RMS beam widths. Then the definition of the RMS beam emittance is given by [12]

$$\varepsilon_{\text{rms}} = \sqrt{\sigma_x^2 \sigma_{x'}^2 - \sigma_{xx'}^2}.\tag{2.14}$$

The computational advantage of such a statistical definition of the emittance is self-explanatory. More importantly, the particular form of the RMS emittance is ultimately related to the dynamical invariant of a linear system. From Appendix A, a general linear equation of motion in two-dimensional (x, x') phase space is an ellipse that is characterized by an invariant action J . The canonical transformation from (x, x') to the action-angle variables (J, ϕ) is given by Eq. (A.24):

$$\begin{aligned}x &= \sqrt{\frac{2J\beta_x}{p_0}} \cos \phi, \\ x' &= -\sqrt{\frac{2J}{\beta_x p_0}} \left(\sin \phi - \frac{1}{2} \beta'_x \cos \phi \right),\end{aligned}\tag{2.15}$$

where $\beta_x(s)$ is the betatron function that satisfies Eq.(A.23), and p_0 is the reference particle momentum. From Section 2.2, the stationary distribution is a function of the action J only, and hence we can write

$$\hat{f}(x, x') = \check{f}(J) \quad \text{with} \quad \int \check{f}(J, \phi) dJ d\phi = 1.\tag{2.16}$$

Let us define the expectation value of J to be

$$\langle J \rangle = \int J \check{f}(J, \phi) dJ d\phi, \quad (2.17)$$

then we have

$$\begin{aligned} \langle x \rangle &= \int x \hat{f}(x, x') dx dx' = \int \sqrt{\frac{2J\beta_x}{p_0}} \cos \phi \check{f}(J) dJ d\phi = 0 = \langle x' \rangle, \\ \sigma_x^2 &= \int x^2 \hat{f}(x, x') dx dx' = \int \frac{2J\beta_x}{p_0} \cos^2 \phi \check{f}(J) dJ d\phi = \beta_x \frac{\langle J \rangle}{p_0}, \end{aligned} \quad (2.18)$$

$$\begin{aligned} \sigma_{x'}^2 &= \int (x')^2 \hat{f}(x, x') dx dx' = \int \frac{2J}{\beta_x p_0} \left(\sin \phi - \frac{1}{2} \beta_x' \cos \phi \right)^2 \check{f}(J) dJ d\phi \\ &= \frac{1}{\beta_x} \left(1 + \frac{\beta_x'^2}{4} \right) \frac{\langle J \rangle}{p_0}, \end{aligned} \quad (2.19)$$

$$\begin{aligned} \sigma_{xx'} &= \int xx' \hat{f}(x, x') dx dx' = \int \frac{2J}{p_0} \cos \phi \left(\sin \phi - \frac{1}{2} \beta_x' \cos \phi \right) \check{f}(J) dJ d\phi \\ &= \frac{\beta_x'}{2} \frac{\langle J \rangle}{p_0}, \end{aligned} \quad (2.20)$$

from which we obtain the RMS emittance

$$\varepsilon_{\text{rms}} = \sqrt{\sigma_x^2 \sigma_{x'}^2 - \sigma_{xx'}^2} = \frac{\langle J \rangle}{p_0} = 2\langle W \rangle. \quad (2.21)$$

where W is the Courant-Snyder invariant and is equal to the area of the ellipse in the phase space (x, x') over π . Thus, the RMS emittance defined by Eq.(2.14) is independent of s under linear transformation. For a uniform distribution in J , the RMS emittance is just a quarter of the area (divided by π) of the largest ellipse, which is the definition of the beam emittance in Section 2.3². More importantly, Eq. (2.21) allows us to obtain the RMS emittance for an arbitrary stationary distribution.

From Eqs. (2.18) and (2.19), the RMS beam widths are given by

$$\sigma_x = \sqrt{\varepsilon_{\text{rms}} \beta_x}, \quad \sigma_{x'} = \sqrt{\frac{\varepsilon_{\text{rms}}}{\beta_x}} \left(1 + \frac{\beta_x'^2}{4} \right)^{1/2}. \quad (2.22)$$

When acceleration is involved in the linear system and p_0 is no longer a constant, we can define a normalized RMS emittance as

$$\varepsilon_{\text{rms}}^n = \beta \gamma \varepsilon_{\text{rms}} = \frac{\langle J \rangle}{m_p c}. \quad (2.23)$$

²Sometimes, a factor of 4 is attached to Eq. (2.14) for this reason.

Therefore, the normalized RMS emittance is related to the expectation value of the single particle action over the beam distribution through Eq. (2.23). It is invariant in a linear system because of the invariance of the underlying dynamical system, namely, the invariant action.

Accelerator systems are designed to be linear or nearly-linear, thus the RMS definition of the emittance is particularly useful in characterizing the distribution of particles in phase space. However, since the RMS emittance is not necessarily representative of the phase space area, a curved line in the phase space has a null area but a nonzero RMS emittance. In addition, the RMS emittance is no longer invariant under nonlinear forces and filamentation processes even though the “true” phase space area is still conserved for the Hamiltonian system. Care is also needed when distributions have long tails because RMS emittance may overestimate the spread of the core distribution.

2.5 Beam Cooling and the Stationary Beam State

By cooling, we mean circumvention of Liouville’s theorem, *i.e.*, the reduction of the phase space region occupied by a beam of particles through non-Hamiltonian dissipative forces. Such manipulations of beam phase space usually introduce random noise to the system. This noise tends to diffuse the particles in phase space and prevent any further reduction of the phase space region when the cooling rate balances the diffusion rate. In the development of charged particle accelerators, different techniques have been adapted for different species of particles to take advantage of their unique properties. Stochastic and electron cooling are two standard methods to obtain small emittance proton beams. Laser cooling of ions has provided beams of the lowest temperature. Ionization cooling has been proposed to reduce the transverse emittance of muon beams. For a general review on beam cooling, please see Ref. [66] and the references thereafter. In this dissertation, we are interested in the radiative cooling of electron or positron beams.

In a dissipative system with noise such as an electron storage ring, the distribution function is governed by the Fokker-Planck equation instead of the Vlasov equation.

The discussion of the Fokker-Planck equation is out of scope of this dissertation and can be found, for example, in Ref. [37]. If the system is linear in the absence of dissipation and fluctuation, the stationary distribution in a two-dimensional phase space (J, ϕ) that obeys the Fokker-Planck equation is simply given by [37]

$$\tilde{f}(J) = \frac{1}{2\pi p_0 \varepsilon_{\text{rms}}} \exp\left(\frac{-J}{p_0 \varepsilon_{\text{rms}}}\right), \quad (2.24)$$

where the normalization factor $p_0 \varepsilon_{\text{rms}}$ is determined by Eq. (2.21). Thus, the dissipative, fluctuating system selects a particular exponential function of the action as the stationary distribution. The damping usually occurs in a time scale much longer than any other relevant time, we can then follow the time evolution of the single particle invariant action to observe the damping and the growth of the RMS emittance.

From Eq (A.26), the action in the horizontal phase space (x, x') can be written as

$$J = p_0(\gamma_x x^2 + 2\alpha_x x x' + \beta_x x'^2)/2, \quad (2.25)$$

where $\alpha_x, \beta_x, \gamma_x$ are the Twiss parameters. The Jacobian of the transformation Eq. (2.15) is given by

$$\frac{\partial(x, x')}{\partial(J, \phi)} = \frac{1}{p_0}. \quad (2.26)$$

The stationary distribution Eq. (2.24) is then transformed to a Gaussian distribution in the horizontal phase space (x, x') :

$$\hat{f}(x, x') = \frac{1}{2\pi \varepsilon_{\text{rms}}} \exp\left[-\frac{\gamma_x x^2 + 2\alpha_x x x' + \beta_x x'^2}{2\varepsilon_{\text{rms}}}\right]. \quad (2.27)$$

Therefore, the RMS emittance measures standard deviations of a Gaussian beam in both x and x' by virtue of Eq. (2.22). We will adopt the RMS definition of the emittance from now on and simply call it the emittance.

Chapter 3

Radiation from Relativistic Electrons

It is well known that accelerated charges emit electromagnetic radiation. In classical electrodynamics, the radiation intensity and angular spectral distribution are related directly to the trajectory and the motion of the charged particle. The covariant form of the total power radiated was derived a hundred years ago by Liénard [48]. Extensive calculations of the radiation emitted by relativistic particles, including the angular distribution of radiated power into harmonics in circular motion was published in a book by Schott [61]. However, it was not until the 1940s that the complete classical theory of synchrotron radiation was put together by Schwinger [62, 63] and by Ivanenko and Sokolov [34] in modern form. In 1947, the first synchrotron light was experimentally observed at the GE 70 MeV synchrotron [19]. Nowadays, there are more than a dozen dedicated synchrotron light sources around the globe to take advantage the unique properties of synchrotron and insertion device radiation from relativistic electron and positron beams for scientific and industrial applications.

Prompted by questions of whether and when quantum corrections to the classical theory of electromagnetic radiation became significant, Schwinger [64] calculated the first order correction in the Planck constant $\hbar$ by an operator method and showed that the quantum corrections was extremely small for all existing or contemplated machines. Schwinger notes that Sokolov, Klepilog and Ternov [69] reached the same

conclusion contemporaneously, as obtained by a calculation based on the exact wavefunctions of Dirac equation. In fact, Klepikov [42], and more completely, Sokolov and Matveev [70] obtained the full quantum correction in the ultra-relativistic limit, re-confirmed the first order corrections and the conclusion that quantum effects are negligible in terms of radiation calculations unless the field seen by the particles is the order of Schwinger’s critical field (4.41×10^9 Tesla) [64]. Such a strong field could be reached when a high energy electron beam encounters the collective field created by a colliding positron beam, an intense laser pulse, or a microscopic crystal field. To fully account for the quantum effects in these circumstances, Baier and Katkov [5, 6, 7] extended Schwinger’s operator method and developed a “quasiclassical” theory of radiation. Their method is relatively simple but rather powerful in problems related to strong field phenomena, for example, in beam-beam interaction or so called beamstrahlung [79].

In laboratory accelerators, the magnetic fields (on the order of 1 Tesla), boosted by the relativistic γ factor, are still orders of magnitude smaller than Schwinger’s critical field. The radiation emitted by high energy electrons is an essentially classical phenomenon. Nevertheless, as Sokolov and Ternov [71] noted, well below the critical field, the discrete quantum nature of the radiation may manifest itself in orbit fluctuations through the so-called quantum excitation of the radial betatron oscillation. Sands [58] investigated the effect of radiation fluctuations on synchrotron oscillations and found it to be the limiting factor on the bunch length. Subsequent developments led to the understanding of quantum fluctuation in electron storage rings. Therefore, the quantum theory of radiation plays a very important role in understanding the effects of radiation on the motion of the radiating particles, which is the main topic of this dissertation.

In this chapter, we first review the classical theory of electromagnetic radiation and derive the angular and spectral distribution of radiation from circular and quasiperiodic motions. Although most results in Section 3.1 can be found in standard textbooks or lecture notes on synchrotron radiation such as Ref. [35, 24, 78, 46], we emphasize the important role of radiation formation length in characterizing the radiation spectrum, especially in Section 3.1.5 where we follow Ref. [8] to give a unified treatment

Figure 3.1: The schematic drawing of the radiation emitted from a moving electron at the retarded time t' .

of undulator and channeling radiation. We then introduce the quantum theory of radiation based on the Klein-Gordon equation in Section 3.2, and illustrate both the wavefunction and the operator methods in order to obtain the full quantum correction of radiated power. Theory of radiation, both classical and quantum, will serve as the starting point for the discussion of the following chapters.

3.1 Classical Theory of Radiation

3.1.1 Fields of a Moving Charged Particle

Let $\mathbf{r}(t')$ be the position of the electron at time t' , $\mathbf{x}$ be the position of the observer, and $\mathbf{R}(t') = \mathbf{x} - \mathbf{r}(t')$ (see Fig. 3.1). An electromagnetic signal emitted by the electron at time t' and traveling on a straight path will arrive at the observer at time

$$t = t' + \frac{R(t')}{c}, \quad (3.1)$$

where $R(t') = |\mathbf{x} - \mathbf{r}|$, t' is called the retarded time or the emitter time, and t the observer time. The motion of the electron is specified by $\mathbf{r}(t')$ with

$$\frac{d\mathbf{r}}{dt'} = \beta c = -\frac{d\mathbf{R}}{dt'}. \quad (3.2)$$

The retarded scalar and vector potential (4-potential) due to a moving point charge are given by [35, 46]

$$A_\mu(\mathbf{x}, t) = \frac{1}{4\pi\epsilon_0} \int \int \frac{J_\mu(\mathbf{x}', t')}{R} \delta\left(t' + \frac{R}{c} - t\right) d^3x' dt', \quad (3.3)$$

where $J_\mu(\mathbf{x}', t') = e\beta_\mu\delta(\mathbf{x}' - \mathbf{r}(t'))$ is the current density of the point charge with $\beta_\mu = (\boldsymbol{\beta}/c, 1)$, and $\mathbf{r}(t')$ is the orbiting path of the electron. The delta function in Eq. (3.3) is needed for the retarded potential. The integral of Eq. (3.3) becomes

$$A_\mu(\mathbf{x}, t) = \frac{e}{4\pi\epsilon_0} \int \frac{\beta_\mu(t')}{R(t')} \delta\left(t' + \frac{R(t')}{c} - t\right) dt'. \quad (3.4)$$

Using

$$\int F\delta(f(t'))dt' = \frac{F}{|df/dt|}, \quad (3.5)$$

we obtain the scalar and vector potentials as [35, 46]

$$\Phi(\mathbf{x}, t) = \frac{e}{4\pi\epsilon_0} \frac{1}{(1 - \mathbf{n} \cdot \boldsymbol{\beta})R} \Big|_{\text{ret}}, \quad \mathbf{A}(\mathbf{x}, t) = \frac{e}{4\pi\epsilon_0 c} \frac{\boldsymbol{\beta}}{(1 - \mathbf{n} \cdot \boldsymbol{\beta})R} \Big|_{\text{ret}}, \quad (3.6)$$

where $\mathbf{n} = \mathbf{R}/R = \boldsymbol{\nabla}R$. The potentials of Eq. (3.6) are known as the Liénard-Wiechert potentials.

The electric and magnetic fields are then given by

$$\mathbf{E} = -\boldsymbol{\nabla}\Phi - \frac{\partial \mathbf{A}}{\partial t}, \quad \mathbf{B} = \boldsymbol{\nabla} \times \mathbf{A}, \quad (3.7)$$

Using the identity $\boldsymbol{\nabla} \rightarrow \boldsymbol{\nabla}R \frac{\partial}{\partial R} = \mathbf{n} \frac{\partial}{\partial R}$, we obtain

$$\begin{aligned} \mathbf{E} &= \frac{e}{4\pi\epsilon_0} \int \left[\frac{\mathbf{n}}{R^2} \delta\left(t' + \frac{R}{c} - t'\right) + \frac{\boldsymbol{\beta} - \mathbf{n}}{cR} \delta\left(t' + \frac{R}{c} - t'\right) \right] dt' \\ &= \frac{e}{4\pi\epsilon_0} \left[\frac{\mathbf{n}}{(1 - \mathbf{n} \cdot \boldsymbol{\beta})R^2} + \frac{1}{c(1 - \mathbf{n} \cdot \boldsymbol{\beta})} \frac{d}{dt'} \frac{\mathbf{n} - \boldsymbol{\beta}}{(1 - \mathbf{n} \cdot \boldsymbol{\beta})R} \right]_{\text{ret}}, \end{aligned} \quad (3.8)$$

$$\begin{aligned} \mathbf{B} &= \frac{e}{4\pi\epsilon_0 c} \int (\mathbf{n} \times \boldsymbol{\beta}) \left[-\frac{1}{R^2} \delta\left(t' + \frac{R}{c} - t'\right) \frac{1}{cR} \delta\left(t' + \frac{R}{c} - t'\right) \right] dt' \\ &= \frac{e}{4\pi\epsilon_0 c} \left[\frac{\mathbf{n} \times \boldsymbol{\beta}}{(1 - \mathbf{n} \cdot \boldsymbol{\beta})R^2} + \frac{1}{c(1 - \mathbf{n} \cdot \boldsymbol{\beta})} \frac{d}{dt'} \frac{\mathbf{n} \times \boldsymbol{\beta}}{(1 - \mathbf{n} \cdot \boldsymbol{\beta})R} \right]_{\text{ret}}. \end{aligned} \quad (3.9)$$

The time derivative of the vector $\mathbf{n}$ is given by the ratio of the vector $\mathbf{v}$ to R , *i.e.*,

$$\frac{d\mathbf{n}}{cdt'} = \frac{\mathbf{n} \times (\mathbf{n} \times \boldsymbol{\beta})}{R} = \frac{(\mathbf{n} \cdot \boldsymbol{\beta})\mathbf{n} - \boldsymbol{\beta}}{R}, \quad (3.10)$$

we obtain then

$$\mathbf{E}(\mathbf{x}, t) = \frac{e}{4\pi\epsilon_0} \left[\frac{\mathbf{n} - \boldsymbol{\beta}}{(1 - \mathbf{n} \cdot \boldsymbol{\beta})^2 R^2} + \frac{\mathbf{n}}{c(1 - \mathbf{n} \cdot \boldsymbol{\beta})} \frac{d}{dt'} \frac{1}{(1 - \mathbf{n} \cdot \boldsymbol{\beta})R} - \frac{1}{c(1 - \mathbf{n} \cdot \boldsymbol{\beta})} \frac{d}{dt'} \frac{\boldsymbol{\beta}}{(1 - \mathbf{n} \cdot \boldsymbol{\beta})R} \right]_{\text{ret}}, \quad (3.11)$$

$$\mathbf{B}(\mathbf{x}, t) = \frac{e}{4\pi\epsilon_0 c} \left[\left(\frac{\boldsymbol{\beta}}{(1 - \mathbf{n} \cdot \boldsymbol{\beta})^2 R^2} - \frac{1}{c(1 - \mathbf{n} \cdot \boldsymbol{\beta})} \frac{d}{dt'} \frac{\boldsymbol{\beta}}{(1 - \mathbf{n} \cdot \boldsymbol{\beta})R} \right) \times \mathbf{n} \right]_{\text{ret}} \quad (3.12)$$

The magnetic field is in fact given by

$$\mathbf{B} = \frac{1}{c} \mathbf{n} \times \mathbf{E}. \quad (3.13)$$

Thus, it suffices to calculate only the electric radiation field. Using the following relations

$$\frac{d\boldsymbol{\beta}}{dt'} = \dot{\boldsymbol{\beta}}; \quad \frac{dR}{cdt'} = -\mathbf{n} \cdot \boldsymbol{\beta}, \quad \frac{d[(1 - \mathbf{n} \cdot \boldsymbol{\beta})R]}{cdt'} = \beta^2 - \boldsymbol{\beta} \cdot \mathbf{n} - \frac{R}{c} \mathbf{n} \cdot \dot{\boldsymbol{\beta}}. \quad (3.14)$$

one obtains the electric field as following

$$\mathbf{E}(\mathbf{x}, t) = \frac{e}{4\pi\epsilon_0} \left[\frac{\mathbf{n} - \boldsymbol{\beta}}{\gamma^2(1 - \mathbf{n} \cdot \boldsymbol{\beta})^3 R^2} \right]_{\text{ret}} + \frac{e}{4\pi\epsilon_0 c} \left[\frac{\mathbf{n}}{(1 - \mathbf{n} \cdot \boldsymbol{\beta})^3 R} \times ((\mathbf{n} - \boldsymbol{\beta}) \times \dot{\boldsymbol{\beta}}) \right]_{\text{ret}}. \quad (3.15)$$

Note here that the electric field is composed of two terms. The first term, that is proportional to $1/R^2$, is a static field pointing away from the charge at the time t . This field can be transformed into an electrostatic electric field by performing a Lorentz transformation into a frame in which the charge is at rest. The total radiated energy from this term is zero.

The second term, related to the acceleration of the electron, is the radiation field, which is proportional to $1/R$. Both $\mathbf{E}$ and $\mathbf{B}$ radiation fields are transverse to $\mathbf{n}$ and are proportional to $1/R$. We will therefore retain only the radiation field in all subsequent discussions.

3.1.2 Angular Distribution of Radiated Power

When the velocity of the electron is small, the radiation field becomes

$$\mathbf{E} = \frac{e}{4\pi\epsilon_0 c} \left[\frac{\mathbf{n} \times (\mathbf{n} \times \dot{\boldsymbol{\beta}})}{R} \right]_{\text{ret}}, \quad (3.16)$$

and Poynting's vector (energy flux) is given by

$$\mathbf{S} = \frac{1}{\mu_0} \mathbf{E} \times \mathbf{B} = \frac{1}{\mu_0 c} |\mathbf{E}|^2 \mathbf{n}. \quad (3.17)$$

Thus the power radiated per unit solid angle is given by

$$\frac{dP_\gamma}{d\Omega} = \frac{1}{\mu_0 c} |\mathbf{E}|^2 R^2 = \frac{e^2}{16\pi^2 \epsilon_0 c} |\mathbf{n} \times (\mathbf{n} \times \dot{\boldsymbol{\beta}})|^2 = \frac{e^2}{16\pi^2 \epsilon_0 c} \dot{\beta}^2 \sin^2 \Theta, \quad (3.18)$$

where the angle Θ is the angle between vector $\mathbf{n}$ and $\dot{\boldsymbol{\beta}}$, *i.e.*, $\mathbf{n} \times \dot{\boldsymbol{\beta}} = |\dot{\boldsymbol{\beta}}| \sin \Theta$. Integrating over all angles, the total radiated power is given by Larmor's formula [35]

$$P_\gamma = \frac{1}{4\pi\epsilon_0} \frac{2e^2 \dot{\beta}^2}{3c} = \frac{2r_e m_e c \dot{\beta}^2}{3}, \quad (3.19)$$

where m_e is the electron mass and

$$r_e = \frac{e^2}{4\pi\epsilon_0 m_e c^2} = 2.82 \times 10^{-15} \text{m} \quad (3.20)$$

is the classical electron radius.

For electrons with a relativistic velocity, Poynting's vector becomes

$$\mathbf{S} \cdot \mathbf{n} = \frac{r_e m_e c}{4\pi} \left[\frac{1}{(1 - \mathbf{n} \cdot \boldsymbol{\beta})^6 R^2} |\mathbf{n} \times ((\mathbf{n} - \boldsymbol{\beta}) \times \dot{\boldsymbol{\beta}})|^2 \right]_{\text{ret}}. \quad (3.21)$$

Notice that $\mathbf{S} \cdot \mathbf{n}$ is the energy per unit area per unit time detected at the observer time t of radiation emitted by the charge at the emitter time t' . Thus, the power radiated per unit solid angle in terms of the emitter time t' is given by

$$\frac{dP_\gamma(t')}{d\Omega} = R^2 (\mathbf{S} \cdot \mathbf{n}) \frac{dt}{dt'} = R^2 (\mathbf{S} \cdot \mathbf{n}) (1 - \mathbf{n} \cdot \boldsymbol{\beta}) = \frac{r_e m_e c}{4\pi} \frac{|\mathbf{n} \times ((\mathbf{n} - \boldsymbol{\beta}) \times \dot{\boldsymbol{\beta}})|^2}{(1 - \mathbf{n} \cdot \boldsymbol{\beta})^5}. \quad (3.22)$$

Figure 3.2: The polar coordinates used in Section 3.1.2.

When we work out the vector identities of Eq. (3.22) and express β in terms of the momentum and the (kinetic) energy

$$\mathbf{p} = \gamma m_e c \boldsymbol{\beta}, \quad E = \gamma m_e c^2, \quad (3.23)$$

we obtain the angular distribution of the radiated power [63]

$$\frac{dP_\gamma(t')}{d\Omega} = \frac{r_e}{4\pi\gamma^2 mc} \left[\frac{\dot{\mathbf{p}}^2 - \dot{E}^2/c^2}{(1 - \mathbf{n} \cdot \mathbf{p}c/E)^3} - \frac{1}{\gamma^2} \frac{(\mathbf{n} \cdot \dot{\mathbf{p}} - \dot{E}/c)^2}{(1 - \mathbf{n} \cdot \mathbf{p}c/E)^5} \right]. \quad (3.24)$$

Without losing generality, we choose a coordinate system in which the z axis coincides with the direction of the instantaneous momentum $\mathbf{p}$, and the xz plane is that of the orbital plane ($\mathbf{p}$ and $\dot{\mathbf{p}}$ plane). Using the polar angles θ and ϕ (Fig. 3.2), we have

$$\begin{aligned} \mathbf{n} &= (\sin \theta \cos \phi, \sin \theta \sin \phi, \cos \theta), \\ \boldsymbol{\beta} &= \mathbf{p}c/E = (0, 0, \beta), \\ \dot{\mathbf{p}} &= (\dot{p}_\perp, 0, \dot{p}_\parallel), \\ \frac{\dot{E}}{c} &= \boldsymbol{\beta} \cdot \dot{\mathbf{p}} = \beta \dot{p}_\parallel \end{aligned} \quad (3.25)$$

Equation (3.24) then becomes

$$\begin{aligned} \frac{dP_\gamma(t')}{d\Omega} = \frac{r_e}{4\pi\gamma^2 m_e c} & \left\{ \dot{p}_\parallel^2 \left[\frac{(1-\beta^2)^2}{(1-\beta\cos\theta)^3} - \frac{1}{\gamma^2} \frac{(\cos\theta-\beta)^2}{(1-\beta\cos\theta)^5} \right] \right. \\ & + \dot{p}_\perp^2 \left[\frac{1}{(1-\beta\cos\theta)^3} - \frac{1}{\gamma^2} \frac{\sin^2\theta\cos^2\phi}{(1-\beta\cos\theta)^5} \right] \\ & \left. - \dot{p}_\parallel\dot{p}_\perp \frac{2}{\gamma^2} \frac{(\cos\theta-\beta)\sin\theta\cos\phi}{(1-\beta\cos\theta)^5} \right\}. \end{aligned} \quad (3.26)$$

By integrating Eq. (3.26) over $\int d\Omega = \int d\phi \int d\theta \sin\theta$, we see immediately that the $\dot{p}_\parallel\dot{p}_\perp$ term drops out while the $\dot{p}_\parallel^2$ term and the $\dot{p}_\perp^2$ term recombine to give the total radiated power

$$\begin{aligned} P_\gamma(t') &= \frac{2r_e}{3m_e c} \gamma^2 \left(\dot{\mathbf{p}}^2 - \frac{1}{c^2} \dot{E}^2 \right) \\ &= \frac{2r_e}{3m_e c} \left(\frac{d\mathbf{p}^2}{dt^\star} - \frac{1}{c^2} \frac{dE^2}{dt^\star} \right), \end{aligned} \quad (3.27)$$

where $t^\star = t'/\gamma$ is the proper time, and the last step of Eq. (3.27) puts the power radiated as a Lorentz-invariant, as it should be. If Eq. (3.27) is expressed with the velocity and acceleration by means of Eq. (3.23), we obtain the Liénard result [48]:

$$P_\gamma(t') = \frac{2r_e}{3m_e c} \gamma^6 [(\dot{\boldsymbol{\beta}})^2 - (\boldsymbol{\beta} \times \dot{\boldsymbol{\beta}})^2]. \quad (3.28)$$

For the case of linear acceleration, we have $\dot{p}_\perp = 0$ and $\dot{p}_\parallel = \gamma^3 m_e c \dot{\beta}$, Eq. (3.26) and Eq. (3.28) becomes

$$\frac{dP_\gamma(t')}{d\Omega} = \frac{r_e \dot{p}_\parallel^2}{4\pi\gamma^6 m_e c} \frac{\sin^2\theta}{(1-\beta\cos\theta)^5}, \quad (3.29)$$

$$P_\gamma(t') = \frac{2r_e (\dot{p}_\parallel)^2}{3mc}. \quad (3.30)$$

For $\beta \ll 1$, we recover Larmor's formulas Eq. (3.18) and Eq. (3.19). But as $\beta \rightarrow 1$, the angular distribution is tipped forward more and more and increase in magnitude. The angle $\theta_{\max}$ for which the intensity is a maximum is

$$\theta_{\max} = \cos^{-1} \left[\frac{1}{3\beta} (\sqrt{1+15\beta^2} - 1) \right] \rightarrow \frac{1}{2\gamma}. \quad (3.31)$$

The RMS of the angular distribution in the relativistic limit is $\langle \theta^2 \rangle^{1/2} = \frac{1}{\gamma}$.

When the electron is executing a circular motion due to a transverse magnetic field, we have the condition, $\dot{p}_{\parallel} = 0$ and $\dot{p}_{\perp} = \gamma m_e c \dot{\beta}$, Eq. (3.26) and Eq. (3.28) then become

$$\frac{dP_{\gamma}(t')}{d\Omega} = \frac{r_e \dot{p}_{\perp}^2}{4\pi \gamma^2 m_e c} \frac{1}{(1 - \beta \cos \theta)^3} \left[1 - \frac{\sin^2 \theta \cos^2 \phi}{\gamma^2 (1 - \beta \cos \theta)^2} \right], \quad (3.32)$$

$$P_{\gamma}(t') = \frac{2r_e (\dot{p}_{\perp})^2}{3mc} \gamma^2 = \frac{2r_e m_e c^3}{3} \frac{\beta^4 \gamma^4}{\rho^2}, \quad (3.33)$$

where $\dot{\beta} = \beta^2 c / \rho$, and ρ is the bending radius. Like the case of linear motion, the angular distribution of the radiation due to circular motion is also confined to a cone of angular width of $\langle \theta^2 \rangle^{1/2} \sim 1/\gamma$. However, the total radiated power from the transverse acceleration is a factor of γ^2 larger than that of longitudinal acceleration.

We can write Eq. (3.33) in more practical units,

$$P_{\gamma}[\text{GeV/sec}] = \frac{c C_{\gamma}}{2\pi} \frac{E[\text{GeV}]^4}{\rho^2}. \quad (3.34)$$

Here we use the definition of Sands' radiation constant for electrons [59]

$$C_{\gamma} = \frac{4\pi}{3} \frac{r_e}{(m_e c^2)^3} = 8.8575 \times 10^{-5} \left[\frac{\text{m}}{\text{GeV}^3} \right]. \quad (3.35)$$

3.1.3 Spectral Distribution of Radiated Power

For a charged particle undergoing arbitrary, extremely relativistic motion the radiation emitted at any instant can be thought of as a coherent superposition of contributions coming from the components of acceleration parallel to and perpendicular to the velocity. However, the radiation from the parallel component has been shown to be $1/\gamma^2$ smaller than that from the perpendicular component. Thus, we may neglect the parallel component. In other words, the radiation emitted by a charged particle in arbitrary, extreme relativistic motion is approximately the same as that emitted by a particle moving instantaneously along the arc of a circular path whose radius of curvature ρ is given by

$$\rho = \frac{v^2}{\dot{v}_{\perp}} \simeq \frac{c^2}{\dot{v}_{\perp}} \quad (3.36)$$

Figure 3.3: Radiation is formed in a characteristic length $l_r \sim \rho/\gamma$.

where $\dot{v}_\perp$ is the perpendicular component of acceleration. From the previous section, we have the angular width of the radiation is of the order $\theta_{\text{rms}} \sim 1/\gamma$, the shape of the radiation spectrum is then determined by the ratio of the angular width ($1/\gamma$) to the total angle $\Delta\theta$ by which the velocity $\mathbf{v}$ is deflected during the entire process of motion. There are two characteristic limiting cases:

(1) $\Delta\theta \gg 1/\gamma$. Here the radiation in a given direction $\mathbf{n}$ is determined by the portion of the trajectory over which the velocity vector $\mathbf{v}$ rotates through an angle of the order $1/\gamma$ (Fig. 3.3). The length of this portion is

$$l_r \sim \frac{\rho}{\gamma} \quad (3.37)$$

and is known as the *radiation formation length*. Thus the particle will illuminate the observer for a time interval $dt' \simeq \rho\theta_{\text{rms}}/c = \rho/(\gamma c)$. To the observer, however, a time interval δt of radiation is given by

$$\delta t \sim \frac{dt}{dt'} \delta t' \sim \frac{1}{\gamma^2} \delta t' = \frac{\rho}{\gamma^3 c}. \quad (3.38)$$

Thus the frequency spectrum will be composed of a broad spectrum up to the critical frequency ω_c .

$$\omega_c \sim \frac{1}{\delta t} \sim \gamma^3 \frac{c}{\rho} \quad (3.39)$$

Synchrotron radiation (Section 3.1.4) is a typical example for this case.

(2) $\Delta\theta \ll 1/\gamma$. Here the radiation emitted in a given direction $\mathbf{n}$ is collected from the entire trajectory (Fig. 3.4), and hence the radiation can be formed over the entire

Figure 3.4: Radiation is formed over the whole oscillation period.

oscillation wavelength λ_0 . The corresponding frequency is then given by

$$\omega_{10} \sim \frac{\gamma^2}{\lambda_0/c} \sim \gamma^2 \omega_0 \quad (3.40)$$

An example is the undulator radiation or channeling radiation (Section 3.1.5).

To obtain the exact frequency dependence, we start with the general form of the power radiated per unit solid angle

$$\frac{dP_\gamma(t)}{d\Omega} = |\mathbf{G}(t)|^2, \quad \mathbf{G}(t) = \left(\frac{1}{\mu_0 c} \right)^{1/2} [R\mathbf{E}]_{\text{ret}}. \quad (3.41)$$

with electric field $\mathbf{E}$ given by Eq. (3.15) and the power is expressed in the observer's time (contrary to the definition of the last section), since we wish to consider a frequency spectrum in terms of the observer's frequencies ω . Using the Fourier transform

$$\mathbf{G}(\omega) = \frac{1}{\sqrt{2\pi}} \int \mathbf{G}(t) e^{i\omega t} dt, \quad \mathbf{G}(t) = \frac{1}{\sqrt{2\pi}} \int \mathbf{G}(\omega) e^{-i\omega t} dt, \quad (3.42)$$

the total energy radiated per unit solid angle is given by

$$\frac{dE_\gamma}{d\Omega} = \int_{-\infty}^{\infty} |\mathbf{G}(t)|^2 dt = \int_{-\infty}^{\infty} |\mathbf{G}(\omega)|^2 d\omega, \quad (\text{Parseval's Theorem [3]}). \quad (3.43)$$

For a real $\mathbf{G}(t)$, the Fourier component has the property: $\mathbf{G}(-\omega) = \mathbf{G}^*(\omega)$. Since the negative frequency is folded back to the positive frequency, we can define the energy radiated per unit solid angle per frequency interval as

$$\frac{dE_\gamma}{d\Omega} = \int_0^\infty \frac{d^2 E_\gamma(\omega, \mathbf{n})}{d\omega d\Omega} d\omega, \quad (3.44)$$

with

$$\frac{d^2 E_\gamma}{d\omega d\Omega} = |\mathbf{G}(\omega)|^2 + |\mathbf{G}(-\omega)|^2 = 2|\mathbf{G}(\omega)|^2. \quad (3.45)$$

The Fourier amplitude $\mathbf{G}(\omega)$ is given by

$$\begin{aligned} \mathbf{G}(\omega) &= \left(\frac{e^2}{32\pi^3 \epsilon_0 c} \right)^{1/2} \int_{-\infty}^{\infty} \left[\frac{\mathbf{n} \times ((\mathbf{n} - \boldsymbol{\beta}) \times \dot{\boldsymbol{\beta}})}{(1 - \mathbf{n} \cdot \boldsymbol{\beta})^3} \right]_{\text{ret}} e^{i\omega t} dt \\ &= \left(\frac{e^2}{32\pi^3 \epsilon_0 c} \right)^{1/2} \int_{-\infty}^{\infty} \left[\frac{\mathbf{n} \times ((\mathbf{n} - \boldsymbol{\beta}) \times \dot{\boldsymbol{\beta}})}{(1 - \mathbf{n} \cdot \boldsymbol{\beta})^2} \right] e^{i\omega(t' + R/c)} dt' \end{aligned} \quad (3.46)$$

Let us assume that the observer is far away, *i.e.*,

$$R = |\mathbf{x} - \mathbf{r}(t')| \simeq x - \mathbf{n} \cdot \mathbf{r}(t'), \quad (3.47)$$

where x is the distance from the origin to the observer. Apart from a constant phase factor, the amplitude of the frequency distribution becomes

$$\mathbf{G}(\omega) = \left(\frac{e^2}{32\pi^3 \epsilon_0 c} \right)^{1/2} \int_{-\infty}^{\infty} \left[\frac{\mathbf{n} \times ((\mathbf{n} - \boldsymbol{\beta}) \times \dot{\boldsymbol{\beta}})}{(1 - \mathbf{n} \cdot \boldsymbol{\beta})^2} \right] e^{i\omega(t' - \mathbf{n} \cdot \mathbf{r}/c)} dt'. \quad (3.48)$$

By using the relation

$$\frac{\mathbf{n} \times ((\mathbf{n} - \boldsymbol{\beta}) \times \dot{\boldsymbol{\beta}})}{(1 - \mathbf{n} \cdot \boldsymbol{\beta})^2} = \frac{d}{dt'} \frac{\mathbf{n} \times (\mathbf{n} \times \boldsymbol{\beta})}{(1 - \mathbf{n} \cdot \boldsymbol{\beta})} \quad (3.49)$$

and integrating by parts, we obtain

$$\mathbf{G}(\omega) = i\omega \left(\frac{e^2}{32\pi^3 \epsilon_0 c} \right)^{1/2} \int_{-\infty}^{\infty} \left[\mathbf{n} \times ((\mathbf{n} - \boldsymbol{\beta}) \times \dot{\boldsymbol{\beta}}) \right] e^{i\omega(t' - \mathbf{n} \cdot \mathbf{r}/c)} dt'. \quad (3.50)$$

Then the energy radiated per unit solid angle per unit frequency interval is accordingly

$$\frac{d^2 E_\gamma}{d\omega d\Omega} = \frac{e^2 \omega^2}{16\pi^3 \epsilon_0 c} \left| \int_{-\infty}^{\infty} \mathbf{n} \times (\mathbf{n} \times \boldsymbol{\beta}) e^{i\omega(t - \mathbf{n} \cdot \mathbf{r}/c)} dt \right|^2. \quad (3.51)$$

The primes on the time variable have been omitted for brevity.

The squared integral in Eq. (3.51) can be written as the product of two integrals over times t_1 and t_2 , *i.e.*,

$$\frac{d^2 E_\gamma}{d\omega d\Omega} = \frac{e^2 \omega^2}{16\pi^3 \epsilon_0 c} \int_{-\infty}^{\infty} dt_1 \int_{-\infty}^{\infty} dt_2 [\mathbf{n} \times (\mathbf{n} \times \boldsymbol{\beta}_1)] [\mathbf{n} \times (\mathbf{n} \times \boldsymbol{\beta}_2)] e^{i(\Phi_1 - \Phi_2)}, \quad (3.52)$$

where we have introduced the notation $\boldsymbol{\beta}_{1,2} = \boldsymbol{\beta}(t_{1,2})$, $\mathbf{r}_{1,2} = \mathbf{r}(t_{1,2})$ and $\Phi_{1,2} = \omega(t_{1,2} - \mathbf{n} \cdot \mathbf{r}_{1,2}/c)$. By using the vector identity

$$[\mathbf{n} \times (\mathbf{n} \times \boldsymbol{\beta}_1)] [\mathbf{n} \times (\mathbf{n} \times \boldsymbol{\beta}_2)] = \boldsymbol{\beta}_1 \cdot \boldsymbol{\beta}_2 - (\mathbf{n} \cdot \boldsymbol{\beta}_1)(\mathbf{n} \cdot \boldsymbol{\beta}_2) \quad (3.53)$$

and integrating by parts:

$$\int dt (\mathbf{n} \cdot \boldsymbol{\beta}) e^{i\omega(t - \mathbf{n} \cdot \mathbf{r}/c)} = \int \frac{e^{i\omega t}}{-i\omega} \frac{d}{dt} (e^{-i\omega \mathbf{n} \cdot \mathbf{r}/c}) = \int dt e^{i\omega(t - \mathbf{n} \cdot \mathbf{r}/c)}, \quad (3.54)$$

we obtain

$$\frac{d^2 E_\gamma}{d\omega d\Omega} = \frac{e^2 \omega^2}{16\pi^3 \epsilon_0 c} \int_{-\infty}^{\infty} dt_1 \int_{-\infty}^{\infty} dt_2 (\boldsymbol{\beta}_1 \cdot \boldsymbol{\beta}_2 - 1) e^{i(\Phi_1 - \Phi_2)}, \quad (3.55)$$

Changing variables of integration to the mean time $t = (t_1 + t_2)/2$ and the relative time $t_0 = t_1 - t_2$, and treating the integrand in the integral with respect to t as the angular spectral distribution of the radiated power at time t , we have

$$\frac{d^2 P_\gamma}{d\omega d\Omega} = \frac{e^2 \omega^2}{16\pi^3 \epsilon_0 c} \int_{-\infty}^{\infty} dt_0 [\boldsymbol{\beta}(t + t_0/2) \cdot \boldsymbol{\beta}(t - t_0/2) - 1] e^{i\omega[t_0 - \frac{1}{c} \mathbf{n} \cdot (\mathbf{r}(t + t_0/2) - \mathbf{r}(t - t_0/2))]} \quad (3.56)$$

Equation (3.56) is completely general and can be employed to calculate the far field radiation pattern of any type of motion once the trajectory is prescribed. The range of t_0 that gives a significant contribution to the integral plays the role of the radiation formation length. We will discuss the radiation spectrum of a circular motion (synchrotron radiation) and quasiperiodic motions (undulator and channeling radiation) in connection with the formation length concept.

Figure 3.5: The angles used in Section 3.1.4.

3.1.4 Synchrotron Radiation

Let us now exam in detail the radiation pattern for a relativistic electron moving on a circular orbit (with radius ρ). Since the radiation is formed over a short segment ρ/γ , we may expand quantities in Eq. (3.56) in a power series in t_0 (this is essentially an expansion in a power series in $1/\gamma$):

$$\begin{aligned} \mathbf{r}(t \pm t_0/2) &= \mathbf{r}(t) \pm \frac{1}{2}t_0\mathbf{v}(t) + \frac{1}{8}t_0^2\dot{\mathbf{v}}(t) \pm \frac{1}{48}t_0^3\ddot{\mathbf{v}}(t) + \dots \\ \boldsymbol{\beta}(t \pm t_0/2) &= \boldsymbol{\beta}(t) \pm \frac{1}{2}t_0\dot{\boldsymbol{\beta}}(t) + \frac{1}{8}t_0^2\ddot{\boldsymbol{\beta}}(t) + \dots \end{aligned} \quad (3.57)$$

Thus, Eq. (3.56) can be written as

$$\frac{d^2P_\gamma}{d\omega d\Omega} = \frac{e^2\omega^2}{16\pi^3\epsilon_0 c} \int_{-\infty}^{\infty} dt_0 \left[-\frac{1}{\gamma^2} - t_0^2 \frac{\dot{\boldsymbol{\beta}}^2}{4} + t_0^2 \frac{\boldsymbol{\beta} \cdot \ddot{\boldsymbol{\beta}}(t)}{4} \right] e^{i\omega[t_0(1-\mathbf{n} \cdot \boldsymbol{\beta}) - t_0^3 \mathbf{n} \cdot \ddot{\boldsymbol{\beta}}/24]}. \quad (3.58)$$

For the circular trajectory (Fig. 3.5), we have

$$\dot{\boldsymbol{\beta}} \simeq \frac{c}{\rho} \equiv \omega_0, \quad \ddot{\boldsymbol{\beta}} \simeq -\frac{c^2}{\rho^2} \boldsymbol{\beta} = -\omega_0^2 \boldsymbol{\beta}, \quad (3.59)$$

and

$$1 - \mathbf{n} \cdot \boldsymbol{\beta} = 1 - \beta \cos \vartheta \cos \varphi \simeq \frac{1}{2}(\gamma^{-2} + \vartheta^2 + \varphi^2), \quad (3.60)$$

where $\vartheta \in (-\pi/2, +\pi/2)$ is the angle between $\mathbf{n}$ and $(\boldsymbol{\beta}, \dot{\boldsymbol{\beta}})$ plane, and $\varphi \in (-\pi, +\pi)$ is the angle between the projection of $\mathbf{n}$ on the $(\boldsymbol{\beta}, \dot{\boldsymbol{\beta}})$ plane and $\boldsymbol{\beta}$. The expansion

in Eq. (3.60) is valid because both ϑ and φ are on the order of $1/\gamma$. Equation (3.58) now becomes

$$\frac{d^2 P_\gamma}{d\omega d(\sin \vartheta)} = \frac{e^2 \omega^2}{16\pi^3 \epsilon_0 c} \int_{-\infty}^{\infty} dt_0 \int_{-\infty}^{\infty} d\varphi \left(-\frac{1}{\gamma^2} - \frac{\omega_0^2 t_0^2}{2} \right) e^{i\omega t_0(\gamma^{-2} + \vartheta^2 + \varphi^2 + \omega_0^2 t_0^2/24)}, \quad (3.61)$$

where the limits of integration with respect to φ have been extended from $\pm\pi$ to $\pm\infty$ because the integrand is very small for $\varphi \sim \pi \gg 1/\gamma$. We introduce new variables x and y instead of t_0 and φ :

$$\omega_0 t_0 = (\gamma^{-2} + \vartheta^2)^{-1/2}(x + y), \quad 2\varphi = (\gamma^{-2} + \vartheta^2)^{-1/2}(x - y). \quad (3.62)$$

Since the Jacobian of the transformation is

$$\left| \frac{\partial(t_0, \varphi)}{\partial(x, y)} \right| = \frac{(\gamma^{-2} + \vartheta^2)}{\omega_0}. \quad (3.63)$$

we get

$$\begin{aligned} \frac{d^2 P_\gamma}{d\omega d(\sin \vartheta)} = \frac{e^2}{16\pi^3 \epsilon_0 c} \frac{\omega^2}{\omega_0} (\gamma^{-2} + \vartheta^2) \int_{-\infty}^{\infty} dx \int_{-\infty}^{\infty} dy \left[-\gamma^{-2} - (\gamma^{-2} + \vartheta^2) \frac{(x + y)^2}{2} \right] \\ \cdot \exp \left[i \frac{3}{2} \xi \left(x + \frac{x^3}{3} + y + \frac{y^3}{3} \right) \right], \end{aligned} \quad (3.64)$$

where

$$\xi = \frac{\omega}{3\omega_0} \left(\frac{1}{\gamma^2} + \vartheta^2 \right)^{3/2} = \frac{\omega}{2\omega_c} (1 + \gamma^2 \vartheta^2)^{3/2}, \quad (3.65)$$

and the critical frequency is defined as

$$\omega_c = \frac{3}{2} \gamma^3 \omega_0 = \frac{3\gamma^3 c}{2\rho}. \quad (3.66)$$

Utilizing the well known Airy integrals (8.433) of Ref. [22],

$$\begin{aligned} \int_0^\infty \cos \left[\frac{3}{2} \xi \left(x + \frac{x^3}{3} \right) \right] dx &= - \int_0^\infty x^2 \cos \left[\frac{3}{2} \xi \left(x + \frac{x^3}{3} \right) \right] dx = \frac{1}{\sqrt{3}} K_{1/3}(\xi), \\ \int_0^\infty x \sin \left[\frac{3}{2} \xi \left(x + \frac{x^3}{3} \right) \right] dx &= \frac{1}{\sqrt{3}} K_{2/3}(\xi), \end{aligned} \quad (3.67)$$

we obtain the following expression for the angular and the spectral distribution of the radiated power:

$$\frac{d^2 P_\gamma}{d\omega d(\sin \vartheta)} = \frac{e^2}{12\pi^3 \epsilon_0 c} \frac{\omega^2}{\omega_0} (\gamma^{-2} + \vartheta^2)^2 \left[K_{2/3}^2(\xi) + \frac{\vartheta^2}{(\gamma^{-2} + \vartheta^2)} K_{1/3}^2(\xi) \right], \quad (3.68)$$

where K_ν is the modified Bessel function of the ν^{th} order.

It can be shown [24, 78] that the first term in the square bracket arises from the polarization vector in the plane of the orbiting electron and the second term arises from the perpendicular direction. On the orbital plane, the radiation is purely plane polarized. Using the asymptotic form for the Bessel function

$$K_\nu(\xi) \sim \begin{cases} 2^{\nu-1} \Gamma(\nu) \xi^{-\nu}, & \text{for } \xi \ll 1, \\ \sqrt{\frac{\pi}{2\xi}} e^{-\xi}, & \text{for } \xi \gg 1, \end{cases} \quad (3.69)$$

we find that the radiation is negligible for $\xi \geq 1$. Thus the radiation is confined within the following region,

$$\omega \leq \frac{2\omega_c}{(1 + \gamma^2 \vartheta^2)^{3/2}}, \quad \langle \vartheta^2 \rangle^{1/2} \leq \frac{1}{\gamma} \left(\frac{\omega_c}{\omega} \right). \quad (3.70)$$

At large angles, the radiation is mostly low frequency, conversely, the high frequency radiation is concentrated in a small angular range.

Integrating Eq. (3.68) over all angular range by using the properties of the Airy functions [24, 78], we skip here the mathematical details to only give the resulting spectral distribution of synchrotron radiation [62, 63]:

$$\begin{aligned} \frac{dP_\gamma}{d\omega} &= \int_{\pi/2}^{\pi/2} \frac{d^2P}{d\omega d(\sin \vartheta)} \cos \vartheta d\vartheta \simeq \int_{\pi/2}^{\pi/2} \frac{d^2P}{d\omega d(\sin \vartheta)} d\vartheta \\ &= \frac{\sqrt{3}e^2\omega_0}{4\pi^2\epsilon_0 c} \gamma \frac{\omega}{\omega_c} \int_{\omega/\omega_c}^{\infty} K_{5/3}(x) dx. \end{aligned} \quad (3.71)$$

To obtain the total power radiated, we integrate Eq. (3.71) with respect to $\omega \equiv \omega_c \chi$:

$$\begin{aligned} P_\gamma &= \int_0^\infty \frac{dP}{d\omega} d\omega = \frac{\sqrt{3}e^2\omega_0\omega_c}{4\pi^2\epsilon_0 c} \gamma \int_0^\infty \chi d\chi \int_\chi^\infty K_{5/3}(x) dx. \\ &= \frac{\sqrt{3}e^2\omega_0\omega_c}{8\pi^2\epsilon_0 c} \gamma \int_0^\infty \chi d\chi^2 K_{5/3}(\chi) \end{aligned} \quad (3.72)$$

Using the integral (6.561.16) of Ref. [22]

$$\int_0^\infty \chi^2 K_{5/3}(\chi) d\chi = \Gamma\left(2 + \frac{1}{3}\right) \Gamma\left(\frac{2}{3}\right) = \frac{4}{9} \frac{2\pi}{\sqrt{3}}, \quad (3.73)$$

Figure 3.6: The universal function $S(x)$ for synchrotron radiation.

we finally have

$$P_\gamma = \frac{e^2 \omega_0 \omega_c}{9\pi^2 \epsilon_0 c} \gamma = \frac{c}{6\pi \epsilon_0} \frac{\gamma^4}{\rho^2} = \frac{c C_\gamma}{2\pi} \frac{E^4}{\rho^2}. \quad (3.74)$$

We see that the power formula agrees with Eq. (3.34). Thus, one can write Eq. (3.71) as

$$\frac{dP_\gamma}{d\omega} = \frac{P_\gamma}{\omega_c} \frac{9\sqrt{3}}{8\pi} \frac{\omega}{\omega_c} \int_{\omega/\omega_c}^{\infty} K_{5/3}(x) dx \equiv \frac{P_\gamma}{\omega_c} S(\omega/\omega_c), \quad (3.75)$$

where the universal function $S(\chi)$ is plotted in Fig. 3.6 and has the following asymptotic approximations:

$$S(\chi) \simeq \begin{cases} 1.333\chi^{1/3}, & \text{for } \chi \ll 1, \\ 0.777\chi^{1/2}e^{-\chi}, & \text{for } \chi \gg 1. \end{cases} \quad (3.76)$$

The spectral distribution of synchrotron radiation depends only on the critical frequency ω_c , the total radiation power and a purely mathematical function. This result was derived originally by Schwinger [62, 63] and independently by Ivanenko and Sokolov [34].

3.1.5 Radiation from Quasiperiodic Motions

Another important type of radiation is generated when relativistic electrons move quasiperiodically in undulators, in laser fields, or in focusing channels such as crystal channels. Different theoretical descriptions and methods were developed independently for each of these phenomena. However, as indicated by Eq. (3.51) or Eq. (3.56), the radiation will have similar characteristics as long as the trajectories of these motions are similar. In this section, we consider the equations of motion and the radiation pattern for a planar undulator and a planar focusing channel.

An undulator has a magnetic field of the form

$$\mathbf{B} = B_u \sin\left(\frac{2\pi}{\lambda_u} z\right) \hat{y} = B_u \sin(k_u z) \hat{y}, \quad (3.77)$$

where λ_u is the period length and k_u is the corresponding wave number. The Lorentz force on the electron determines the equation of motion:

$$e[\mathbf{v} \times \mathbf{B}] = eB_u \sin(k_u z)(-\dot{z}, 0, \dot{x}) = \gamma m(\ddot{x}, 0, \ddot{z}). \quad (3.78)$$

We can integrate the coupled x, z equations to the second order in the deflection angle $\theta_d = eB_u/(\gamma m c k_u) \ll 1$ by setting $\dot{z} \approx \beta c$ and $\dot{x} \approx 0$:

$$\begin{aligned} \dot{x} &\simeq c\theta_d \cos(k_u z) = c\theta_d \cos(\omega_u t), \\ \dot{z} &\simeq \beta c - \frac{\theta_d^2 c}{2} \cos^2(k_u z) = \beta^* c - \frac{\theta_d^2 c}{4} \cos(2\omega_u t), \end{aligned} \quad (3.79)$$

where $\omega_u = k_u \beta^* c$ is the undulator oscillation frequency, and $\beta^* c = \beta c - \theta_d^2 c/4$ is the average velocity in the longitudinal z direction. Integrating over time once more we have

$$x = \frac{c\theta_d}{\omega_u} \sin(\omega_u t), \quad z = \beta^* c t - \frac{\theta_d^2 c}{8\omega_u} \sin(2\omega_u t). \quad (3.80)$$

Boosted to a comoving frame (denoted by a star) with a Lorentz factor

$$\gamma^* = \frac{1}{(1 - \beta^{*2})} \simeq \frac{\gamma}{\sqrt{1 + \gamma^2 \theta_d^2}}, \quad (3.81)$$

the Lorentz transformed coordinates are

$$\begin{aligned}
 x^* &= x = \frac{c\theta_d}{\omega_u} \sin(\omega_u t) \equiv x_0 \sin(\omega_u t), \\
 z^* &= \gamma^*(z - \beta^* ct) = -\frac{\gamma^* \theta_d^2 c}{8\omega_u} \sin(2\omega_u t) = -\frac{\gamma^* \theta_d}{4} x^* \sqrt{1 - \frac{x^{*2}}{x_0^2}} \\
 &= \frac{K_u}{\sqrt{1 + K_u^2/2}} x^* \sqrt{1 - \frac{x^{*2}}{x_0^2}},
 \end{aligned} \tag{3.82}$$

where

$$K_u = \gamma \theta_d = 0.94 B[\text{Tesla}] \lambda_u[\text{cm}] \tag{3.83}$$

is the undulator parameter. Such a motion is periodic (a figure of eight) in the comoving frame. For a weak undulator we have $K_u \ll 1$, the motion in the comoving frame is reduced to a simple harmonic oscillation, and the radiation becomes dipole radiation. Transforming back to the laboratory frame, we obtain as a result for the fundamental frequency of the emitted photon (Doppler effect):

$$\omega_1 = \frac{\omega_u}{1 - \beta^* \cos \theta} = \frac{2\gamma^2 \omega_u}{1 + \gamma^2 \theta^2 + K_u^2/2}. \tag{3.84}$$

For a strong undulator (most often called a wiggler) we have $K_u \geq 1$, the radiation is composed of harmonics of the fundamental frequency.

Now consider a planar focusing system that provides a continuous parabolic potential $K_x x^2/2$, where K_x is the focusing strength. The parabolic potential could be, for example, an approximation of the Lindhard potential in the case of planar crystal channeling [49]. We define the pitch angle of the electron $\theta_p = p_{x0}/p_z$ (p_{x0} being the maximum transverse momentum) and assume that θ_p is always much less than one. By expanding the Hamiltonian to the second order in θ_p , the motion of the electron can be decomposed into a free longitudinal motion and a transverse harmonic oscillation:

$$\begin{aligned}
 H &= \sqrt{m_e^2 c^4 + p_z^2 c^2 + p_x^2 c^2} + \frac{K_x x^2}{2} \\
 &\simeq \sqrt{m_e^2 c^4 + p_z^2 c^2} + \frac{p_x^2 c^2}{2E_z} + \frac{K_x x^2}{2},
 \end{aligned} \tag{3.85}$$

Figure 3.7: Geometry for undulator or channeling radiation.

where $E_z = \sqrt{m_e^2 c^4 + p_z^2 c^2}$. From Hamilton's equation, we obtain

$$\dot{x} = \frac{\partial H}{\partial p_x} = \frac{p_x c^2}{E_z}, \quad \dot{p}_x = -\frac{\partial H}{\partial x} = -K_x x, \quad (3.86)$$

$$\dot{z} = \frac{\partial H}{\partial p_z} = \frac{p_z c^2}{E_z} \left(1 - \frac{\dot{x}^2}{2c^2} \right), \quad \dot{p}_z = -\frac{\partial H}{\partial z} = 0, \quad (3.87)$$

From Eq. (3.86), we have $\ddot{x} = -(K_x c^2 / E_z) x \equiv -\omega_x^2 x$, with ω_x being the transverse oscillation frequency. The solution with initial conditions $x = 0$ and $\dot{x} = c\theta_p$ is simply given by

$$x = \frac{c\theta_p}{\omega_x} \sin(\omega_x t), \quad \text{or} \quad \dot{x} = c\theta_p \cos(\omega_x t). \quad (3.88)$$

From Eq. (3.87), we then have

$$\dot{z} = \frac{p_z c^2}{E_z} \left[1 - \frac{\theta_p^2}{2} \cos^2(\omega_x t) \right] = \beta^* c - \frac{\theta_p^2 c}{4} \cos(2\omega_x t), \quad (3.89)$$

where we have set $p_z c / E_z \approx \beta$ and $\beta^* = \beta(1 - \theta_p^2/4)$. It is now clear that the channeling motion has the same characteristic figure of eight as the undulator motion in the comoving frame to the accuracy desired, with $\gamma\theta_p$ playing the role of the undulator parameter K_u .

We can calculate the radiation spectrum starting from Eq. (3.56) for both undulator and channeling motions. First, we pick θ_0 to represent either θ_d or θ_p and ω_0 to represent either ω_u or ω_x (see Fig. 3.7). Then we write

$$\begin{aligned}\boldsymbol{\beta} &= \left(\theta_0 \cos(\omega_0 t), 0, \beta^* - \frac{\theta_0^2}{4} \cos(2\omega_0 t) \right), \\ \mathbf{r} &= \left(\frac{\theta_0 c}{\omega_0} \sin(\omega_0 t), 0, \beta^* c t - \frac{\theta_0^2 c}{8\omega_0} \sin(2\omega_0 t) \right).\end{aligned}\quad (3.90)$$

Keeping terms up to the second order in θ_0 , we obtain after some algebra:

$$\begin{aligned}\boldsymbol{\beta}(t + t_0/2)\boldsymbol{\beta}(t - t_0/2) - 1 &= -\frac{1}{\gamma^2} \left[1 + \gamma^2 \theta_0^2 \sin\left(\frac{\tau_0}{2}\right) (1 - \cos(2\tau)) \right], \\ \omega \left[t_0 - \frac{1}{c} \mathbf{n} \cdot (\mathbf{r}(t + t_0/2) - \mathbf{r}(t - t_0/2)) \right] &= -u\tau_0 \left[\frac{1}{2\gamma^2} + \frac{\theta^2}{2} + \frac{\theta_0^2}{4} + \frac{\theta_0^2}{4} \frac{\sin \tau_0}{\tau_0} \cos(2\tau) \right. \\ &\quad \left. - \theta\theta_0 \cos \phi \frac{\sin(\tau_0/2)}{(\tau_0/2)} \cos s \right].\end{aligned}\quad (3.91)$$

where we have defined $u = \omega/\omega_0$, $\tau = \omega_0 t$ and $\tau_0 = \omega_0 t_0$ for convenience.

To obtain the spectral distribution of the radiated power, we insert Eq. (3.91) into Eq. (3.56) and integrate over the photon emission angles by the formula [8]

$$\int_0^\infty \theta d\theta \int_0^{2\pi} d\phi \exp[i(a\theta^2 + b\theta \cos \phi)] = \lim_{\epsilon \rightarrow +0} \frac{i\pi}{a + i\epsilon} \exp\left(-i\frac{b^2}{4a}\right). \quad (3.92)$$

Setting $a = -u\tau_0/2$ and $b = u\tau_0\theta_0 \cos \tau \sin(\tau_0/2)/(\tau_0/2)$, we obtain

$$\frac{dP_\gamma}{d\omega} = \frac{ie^2\zeta}{4\pi^2\epsilon_0 c} \int_{-\infty}^\infty \frac{d\tau_0}{\tau_0 - i\epsilon} \left[1 + \gamma^2 \theta_0^2 \sin\left(\frac{\tau_0}{2}\right) (1 - \cos(2s)) \right] e^{-iz_0 \cos(2\tau)} e^{-iz_1}, \quad (3.93)$$

where

$$\begin{aligned}\zeta &= \frac{u}{2\gamma^2} = \frac{\omega}{2\gamma^2\omega_0}, \\ z_0 &= \zeta \gamma^2 \theta_0^2 \left[\frac{\sin(\tau_0/2)}{(\tau_0/2)} - \frac{\sin(\tau_0)}{2} \right], \\ z_1 &= \zeta \tau_0 \left[1 + \frac{\gamma^2 \theta_0^2}{2} \left(1 - \frac{\sin(\tau_0/2)}{(\tau_0/2)} \right) \right].\end{aligned}\quad (3.94)$$

By using the Bessel function $J_\nu(u)$ expansion

$$e^{iz_0 \cos(2\tau)} = \sum_{\nu=-\infty}^{\infty} J_\nu(z_0) e^{i\nu(2\tau+\pi/2)}, \quad (3.95)$$

and by integrating Eq. (3.93) over one oscillation period $\int_0^{2\pi} d\tau$ (indicated by $\langle \rangle$), we have the average radiated power

$$\langle P_\gamma \rangle = \frac{ie^2}{2\pi^2\epsilon_0 c} \omega_0^2 \gamma^2 \int_0^\infty I(\zeta) \zeta d\zeta, \quad (3.96)$$

where

$$I(\zeta) = \int_{-\infty}^{\infty} \frac{d\tau_0}{\tau_0 - i\epsilon} \left\{ J_0(z_0) + \gamma^2 \theta_0^2 \sin^2 \left(\frac{\tau_0}{2} \right) [J_0(z_0) - iJ_1(z_0)] \right\} e^{-iz_1}. \quad (3.97)$$

Equation (3.96) is completely general for any $\gamma\theta_0$. The range of $\tau_0 = \omega_0 t_0$ that gives a significant contribution to the integral can be interpreted as the ratio of the radiation formation length l_r to the reduced oscillation wavelength $\lambda_0 = c/\omega_0$. We consider two opposite limits $\gamma\theta_0 \gg 1$ (wiggler or strong undulator regime) and $\gamma\theta_0 \ll 1$ (weak undulator regime) where Eq. (3.96) can be greatly simplified.

In the wiggler or strong undulator regime, we have $\gamma\theta_0 \gg 1$ or $\theta_0 \gg 1/\gamma$. From Section 3.1.3, the radiation formation length l_r is on the order of $\bar{\rho}/\gamma$, where $\bar{\rho}$ is the average radius of curvature in a half period and can be approximated by

$$\bar{\rho} \simeq \begin{cases} \gamma m_e c / (e \bar{B}_u) \sim 1/(\theta_d k_u) \sim \lambda_u / \theta_d \rightarrow \lambda_0 / \theta_0 & \text{for the undulator,} \\ E / (K_x \bar{x}) \sim c / (\theta_p \omega_x) \sim \lambda_x / \theta_p \rightarrow \lambda_0 / \theta_0 & \text{for the channel.} \end{cases} \quad (3.98)$$

Thus, we have

$$\frac{l_r}{\lambda_0} \sim \frac{1}{\gamma\theta_0} \ll 1, \quad (3.99)$$

i.e., the radiation is formed in a small fraction of the oscillation wavelength. Expand the integrand of Eq. (3.97) for small τ_0 , we obtain

$$\begin{aligned} I(\zeta) &\simeq \int_{-\infty}^{\infty} \frac{d\tau_0}{\tau_0 - i\epsilon} \left(1 + \frac{\gamma^2 \theta_0^2 \tau_0^2}{4} \right) \exp \left[-i\zeta \tau_0 \left(1 + \frac{\gamma^2 \theta_0^2 \tau_0^2}{4} \right) \right] \\ &= i\pi - 2i \int_0^\infty \frac{d\tau_0}{\tau_0} \left(1 + \frac{\gamma^2 \theta_0^2 \tau_0^2}{4} \right) \sin \left[-i\zeta \tau_0 \left(1 + \frac{\gamma^2 \theta_0^2 \tau_0^2}{4} \right) \right] \\ &= -\frac{2i}{\sqrt{3}} \int_\chi^\infty K_{5/3}(x) dx, \end{aligned} \quad (3.100)$$

where $i\pi$ comes from the residue at $\tau_0 = i\epsilon$ and

$$\chi = \frac{4\sqrt{2}}{3} \frac{\zeta}{\gamma\theta_0} = \frac{2\sqrt{2}}{3} \frac{\omega}{\gamma^3\theta_0\omega_0}. \quad (3.101)$$

We have also used (II.14) of Ref. [63] in the last step of Eq. (3.100). Insert Eq. (3.100) into Eq. (3.97), we obtain the radiated power spectrum:

$$\langle P_\gamma \rangle = \frac{9e^2}{32\pi\sqrt{3}\epsilon_0 c} \gamma^4 \theta_0^2 \omega_0^2 \int_0^\infty \chi d\chi \int_\chi^\infty K_{5/3}(x) dx, \quad (3.102)$$

Here χ plays the role of ω/ω_c in Eq. (3.71). Thus, the radiated power spectrum in the limit of large $\gamma\theta_0$ is very similar to that of synchrotron radiation.

In the weak undulator regime, we have $\gamma\theta_0 \ll 1$ or $\theta_0 \ll 1/\gamma$. From Section 3.1.3, the radiation is formed over the entire trajectory and is characterized by the reduced oscillation wavelength λ_0 . Expanding the integrand in Eq. (3.97) to leading orders in the small parameter $g = \gamma^2\theta_0^2$ yields:

$$\begin{aligned} I(\zeta) &\simeq \int_{-\infty}^\infty \frac{d\tau_0}{\tau_0 - i\epsilon} \left(1 + g \sin^2 \frac{\tau_0}{2} \right) \exp \left[-i\zeta \tau_0 \frac{g}{2} \left(1 - \frac{\sin^2(\tau_0/2)}{(\tau_0/2)^2} \right) \right] e^{-i\zeta\tau_0} \\ &\simeq \int_{-\infty}^\infty \frac{d\tau_0}{\tau_0 - i\epsilon} \left[1 + g \sin^2 \frac{\tau_0}{2} - i\zeta \tau_0 \frac{g}{2} \left(1 - \frac{\sin^2(\tau_0/2)}{(\tau_0/2)^2} \right) \right] e^{-i\zeta\tau_0}. \end{aligned} \quad (3.103)$$

Apply the residue theorem to the integration of the type

$$\lim_{\epsilon \rightarrow +0} \int_{-\infty}^\infty \frac{d\tau_0}{(\tau_0 - i\epsilon)^m} e^{iq\tau_0} = \frac{2\pi i}{(m-1)!} (iq)^{m-1} \Theta(q) \quad \text{for } m = 1, 2, \quad (3.104)$$

where

$$\Theta(q) = \begin{cases} 1, & \text{if } q > 0, \\ 0, & \text{if } q < 0 \end{cases} \quad (3.105)$$

is the Heaviside step function, we obtain

$$\langle P_\gamma \rangle = \frac{e^2 \gamma^4 \theta_0^2 \omega_0^2}{4\pi \epsilon_0 c} \int_0^\infty d\zeta \zeta [1 + 2\zeta(\zeta - 1)] \Theta(1 - \zeta). \quad (3.106)$$

Thus, the radiation spectrum is nonzero only if $\zeta = \omega/(2\gamma^2\omega_0) < 1$. This implies that integration over τ_0 in Eq. (3.103) is significant only for $\tau_0 \sim 1$, or the radiation

formation length l_r is of the order λ_0 . We conclude that the radiation frequency distribution has a sharp cutoff at $\omega = \omega_{10} \equiv 2\gamma^2\omega_0$, which is the characteristic of dipole radiation.

In both regimes, we can carry out the integrals in Eq. (3.102) and (3.106) and find the average radiation power to be:

$$\langle P_\gamma \rangle = \frac{e^2}{12\pi\epsilon_0 c} \gamma^4 \theta_0^2 \omega_0^2 = \begin{cases} \frac{e^2}{12\pi\epsilon_0 c} \gamma^2 \frac{e^2 B_u^2}{m_e^2} = \frac{4\pi\epsilon_0}{3} r_e^2 c^3 \gamma^3 B_u^2 & \text{for the undulator,} \\ \frac{e^2}{12\pi\epsilon_0 c} \gamma^2 \frac{K^2 x_0^2}{m_e^2 c^2} = \frac{1}{3} r_e \gamma^2 \frac{K^2 x_0^2}{m_e c} & \text{for the channel.} \end{cases} \quad (3.107)$$

This formula is actually true for any $\gamma\theta_0$ because the total radiated power is always given by Eq (3.27).

3.2 Quantum Theory: An Introduction

All electromagnetic radiation occurs in quanta of discrete energy $\hbar\omega$, where $\hbar = 1.055 \times 10^{-34} \text{J sec}$ is the Planck constant. The classical theory of radiation as developed in the previous section is only correct in so far as one can neglect all effects which arise from the finite value of $\hbar$. This requires that the emitted photon energy $\hbar\omega$ is much less than the energy of the particle. For classical synchrotron radiation, the typical photon energy $\hbar\omega_c = 3\gamma^3\hbar c/2\rho$. One can characterize the quantum effects by a Lorentz invariant parameter Υ [79]:

$$\Upsilon \equiv \frac{2}{3} \frac{\hbar\omega_c}{E} = \frac{\gamma B}{B_c}, \quad (3.108)$$

where $B = c/e\rho$ is the transverse magnetic field and $B_c = m_e^2 c^3 / e\hbar = 4.43 \times 10^9$ Tesla is the critical field according to Schwinger [64]. When $\Upsilon \ll 1$, the radiation is classical, as $\Upsilon \sim 1$ or bigger, the classical synchrotron radiation theory must fail because the photon energy cannot be larger than the particle energy. A quantum treatment of radiation is necessary.

To construct a quantum theory of radiation, it is essential to take into account the interaction between the electron and the second-quantized photon field. In the simplest case where we do not care about the spin degrees of freedom (for a review

on spin-flip radiation, please see Ref. [36], we may subject the wavefunction of the electron $\Psi(\mathbf{r}, t)$ to the Klein-Gordon equation [11] (instead of the Dirac equation):

$$[(\mathbf{p} - e\mathbf{A} - e\mathbf{A}_{\text{rad}})^2 c^2 + m_e^2 c^4] \Psi(\mathbf{r}, t) = \left(i\hbar \frac{\partial}{\partial t} - e\Phi \right)^2 \Psi(\mathbf{r}, t), \quad (3.109)$$

where $\mathbf{p} = -i\hbar\nabla$ is the momentum operator, $\mathbf{A}$ and ϕ are the vector and scalar potentials due to external fields, and $\mathbf{A}_{\text{rad}}$ is the vector potential that acts on the second quantized radiation field by creating and annihilating a photon with polarization $\mathbf{e}_\lambda$ ($\lambda = 1$ or 2), momentum $\hbar\mathbf{k}$ and energy $\hbar\omega$ [23]. We choose the Coulomb gauge $\nabla \cdot \mathbf{A}_{\text{rad}} = 0$ for the radiation field so that $\mathbf{k} \cdot \mathbf{e}_\lambda = 0$. In an arbitrary unit volume of the photon (real) space, we have

$$\mathbf{A}_{\text{rad}} = \sqrt{\frac{\hbar}{2\epsilon_0\omega}} \mathbf{e}_\lambda (\hat{a}^\dagger e^{-i\mathbf{k}\cdot\mathbf{r} + i\omega t} + \hat{a} e^{i\mathbf{k}\cdot\mathbf{r} - i\omega t}), \quad (3.110)$$

where $\hat{a}^\dagger$ and $\hat{a}$ are the creation and annihilation operators on the photon field.

In the absence of radiation, we let $\mathbf{A}_{\text{rad}} = 0$ in Eq. (3.109) and look for the energy levels E_j and the stationary states $\Psi(\mathbf{r}, t) = e^{-iE_j t/\hbar} \psi_j(\mathbf{r})$ that satisfy

$$H_0 \psi_j(\mathbf{r}) = E_j \psi_j(\mathbf{r}), \quad \text{with} \quad H_0 = [(\mathbf{p} - e\mathbf{A})^2 c^2 + m_e^2 c^4]^{1/2} + e\Phi. \quad (3.111)$$

Since the Klein-Gordon equation is a second-order differential equation, the probability density is given by [11]

$$\varrho(\mathbf{r}) = \frac{1}{2m_e c^2} \left[\Psi^* \left(i\hbar \frac{\partial}{\partial t} - e\Phi \right) \Psi - \Psi \left(i\hbar \frac{\partial}{\partial t} - e\Phi \right) \Psi^* \right]. \quad (3.112)$$

If we follow the normalization $\int d\mathbf{r} \varrho(\mathbf{r}) = 1$, we obtain

$$\psi_j(\mathbf{r}) = \sqrt{\frac{m_e c^2}{E_j - e\Phi}} |j\rangle, \quad \text{with} \quad \langle j|j\rangle = 1. \quad (3.113)$$

Coupling between the electron and the radiation field leads to spontaneous emission of photons. Neglecting the $\mathbf{A}_{\text{rad}}^2$ term (double-photon emission), Eq. (3.109)

becomes

$$[(\mathbf{p} - e\mathbf{A})^2 - 2(\mathbf{p} - e\mathbf{A}) \cdot e\mathbf{A}_{\text{rad}} + m_e^2 c^2] c^2 \Psi(\mathbf{r}, t) = \left(i\hbar \frac{\partial}{\partial t} - e\Phi \right)^2 \Psi(\mathbf{r}, t), \quad (3.114)$$

Moving to the interaction representation we write $\Psi(\mathbf{r}, t) = \exp(-iH_0 t/\hbar) \psi(\mathbf{r}, t)$ and assume that ψ is slowly varying with time t . By identifying $(H_0 - e\Phi)^2 = [(\mathbf{p} - e\mathbf{A})^2 c^2 + m_e^2 c^4]$, and neglecting $\ddot{\psi}(t)$ in the expansion of $(i\partial/\partial t - e\Phi)^2 \Psi(t)$ in Eq. (3.114), we obtain

$$\begin{aligned} \dot{\psi}(t) &= \frac{ie}{\hbar} e^{iH_0 t/\hbar} (H_0 - e\Phi)^{-1} (\mathbf{p} - e\mathbf{A}) c^2 \cdot \mathbf{A}_{\text{rad}} e^{-iH_0 t/\hbar} \psi(t) \\ &= \frac{ie}{\hbar} \sqrt{\frac{\hbar}{2\epsilon_0 \omega}} e^{iH_0 t/\hbar} \mathbf{e}_\lambda \cdot \hat{\mathbf{v}} e^{-i\mathbf{k} \cdot \mathbf{r} + i\omega t} e^{-iH_0 t/\hbar} \psi(t), \end{aligned} \quad (3.115)$$

where we have defined $\hat{\mathbf{v}} = (H_0 - e\Phi)^{-1} (\mathbf{p} - e\mathbf{A}) c^2$ for convenience and have dropped out the annihilation part of $\mathbf{A}_{\text{rad}}$ because we are interested in spontaneous emissions.

Using first-order, time-dependent perturbation theory, we expand

$$\psi(t) = \sqrt{\frac{m_e c^2}{H_0 - e\Phi}} \sum_j a_j(t) |j\rangle \quad \text{with} \quad \sum_j |a_j(t)|^2 = 1, \quad (3.116)$$

and approximate $\psi(t)$ at the right hand side of Eq. (3.115) with the initial state

$$\psi(0) = \sqrt{\frac{m_e c^2}{H_0 - e\Phi}} |i\rangle, \quad (3.117)$$

Eq. (3.115) becomes

$$\sqrt{\frac{m_e c^2}{H_0 - e\Phi}} \sum_j \frac{da_j}{dt} |j\rangle = \frac{ie}{\hbar} \sqrt{\frac{\hbar}{2\epsilon_0 \omega}} e^{iH_0 t/\hbar} \mathbf{e}_\lambda \cdot \hat{\mathbf{v}} e^{-i\mathbf{k} \cdot \mathbf{r} + i\omega t} e^{-iH_0 t/\hbar} \sqrt{\frac{m_e c^2}{H_0 - e\Phi}} |i\rangle \quad (3.118)$$

Thus, the transition probability $d\Pi_{fi}$ for the electron to go from an initial state $|i\rangle$ at time $t = 0$ to a final state $|f\rangle$ at time $t = T$ by radiating into the range $d\mathbf{k}$ with both polarizations is

$$\begin{aligned} d\Pi_{fi} &= \frac{d\mathbf{k}}{(2\pi)^3} \sum_{\lambda=1}^2 \frac{|a_f|^2}{T} \\ &= \frac{d^3 k}{(2\pi)^3} \frac{e^2}{2\epsilon_0 \hbar \omega} \left| \int_0^T dt e^{i\omega t} \langle f | e^{iH_0 t/\hbar} \sum_{\lambda=1}^2 \mathbf{e}_\lambda \cdot \hat{\mathbf{v}} e^{-iH_0 t/\hbar} | i \rangle \right|^2, \end{aligned} \quad (3.119)$$

where we have defined

$$\tilde{\mathbf{v}} = \sqrt{\frac{1}{H_0 - e\Phi}}(\mathbf{p} - e\mathbf{A})c^2 e^{-i\mathbf{k}\cdot\mathbf{r}} \sqrt{\frac{1}{H_0 - e\Phi}}. \quad (3.120)$$

At this stage, there are two methods to evaluate the radiated power. In the first method, we can explicitly integrate the time integral by using

$$\exp\left(\frac{iH_0 t}{\hbar}\right)|i, f\rangle = \exp\left(\frac{iE_{i,f} t}{\hbar}\right)|i, f\rangle \quad (3.121)$$

for the matrix element. Let us define the transition rate dW_{fi} as the transition probability per unit time and denote $\omega_{fi} = (E_i - E_f)/\hbar$, in the limit of long time T , we have

$$dW_{fi} = \frac{d\mathbf{k}}{(2\pi)^3} \frac{e^2}{2\epsilon_0 \hbar \omega} \left| \langle f | \sum_{\lambda=1}^2 \mathbf{e}_\lambda \cdot \mathbf{v} e^{-i\mathbf{k}\cdot\mathbf{r}} | i \rangle \right|^2 2\pi \delta(\omega - \omega_{fi}), \quad (3.122)$$

where

$$\mathbf{v} = \frac{(\mathbf{p} - e\mathbf{A})c^2}{\sqrt{(E_i - e\Phi)(E_f - e\Phi)}} \quad (3.123)$$

is the velocity operator. The δ function in Eq. (3.122) expresses the fact that the photon energy comes from the change in electron energy. The total radiated power is then given by

$$\begin{aligned} P_\gamma &= \sum_f \int dW_{fi} \hbar \omega \\ &= \sum_f \int \frac{d\mathbf{k}}{(2\pi)^3} \frac{e^2}{2\epsilon_0} \left| \langle f | \sum_{\lambda=1}^2 \mathbf{e}_\lambda \cdot \mathbf{v} e^{-i\mathbf{k}\cdot\mathbf{r}} | i \rangle \right|^2 2\pi \delta(\omega - \omega_{fi}). \end{aligned} \quad (3.124)$$

This is essentially the approach taken by Sokolov and Ternov [72, 73], except that they used the Dirac equation and took into account the spin degree of freedom. This approach involves the exact forms of wavefunctions and energy levels, and many difficulties, especially those of a mathematical nature, had to be overcome in the calculations. Nevertheless, the detailed knowledge of the stationary states of the electron and thus the transition rate does allow one to investigate the radiation effects

on electron dynamics. It will be employed in Chapter 4 when we consider the effects of focusing to the radiation damping and quantum excitation.

An operator approach was initiated by Schwinger [64], and fully developed into a “quasiclassical” theory of radiation by Baier and Katkov [5, 6, 7]. They realized that the exact solutions of the Dirac equation are not necessary for the radiation calculations and only the commutation relations of the operators has to be taken into account for quantum effects. To illustrate this operator approach for a scalar particle (spin neglected), we write Eq. (3.119) as a double-time integral:

$$d\Pi_{fi} = \frac{d\mathbf{k}}{(2\pi)^3} \frac{e^2 c^2}{2\epsilon_0 \hbar \omega} \int_0^T dt_1 e^{-i\omega t_1} \int_0^T dt_2 e^{i\omega t_2} \langle i | \sum_{\lambda=1}^2 (\mathbf{e}_\lambda \cdot \tilde{\boldsymbol{\beta}}_1)^* | f \rangle \langle f | (\mathbf{e}_\lambda \cdot \tilde{\boldsymbol{\beta}}_2) | i \rangle, \quad (3.125)$$

where

$$\begin{aligned} \tilde{\boldsymbol{\beta}}_l &= e^{iH_0 t_l / \hbar} \frac{\tilde{\mathbf{v}}}{c} e^{-iH_0 t_l / \hbar} \quad (l = 1, 2) \\ &= \sqrt{\frac{1}{H_0 - e\Phi}} e^{iH_0 t_l / \hbar} (\mathbf{p} - e\mathbf{A}) c e^{-i\mathbf{k} \cdot \mathbf{r}} e^{-iH_0 t_l / \hbar} \sqrt{\frac{1}{H_0 - e\Phi}} \end{aligned} \quad (3.126)$$

are the Heisenberg operators.

Sum over all final states f by using

$$\sum_f |f\rangle \langle f| = I, \quad (3.127)$$

we obtain the transition probability to all possible states as

$$d\Pi_i = \frac{d\mathbf{k}}{(2\pi)^3} \frac{e^2 c^2}{2\epsilon_0 \hbar \omega} \int_0^T dt_1 e^{-i\omega t_1} \int_0^T dt_2 e^{i\omega t_2} \langle i | \sum_{\lambda=1}^2 (\mathbf{e}_\lambda \cdot \tilde{\boldsymbol{\beta}}_1)^* (\mathbf{e}_\lambda \cdot \tilde{\boldsymbol{\beta}}_2) | i \rangle, \quad (3.128)$$

For a sufficiently extended time interval T , we can change variables of integration to the mean time $t = (t_1 + t_2)/2$ and relative time $t_0 = t_2 - t_1$, and regard the t integrand as the transition rate (to all possible final states) per unit time:

$$dW_i = \frac{d\mathbf{k}}{(2\pi)^3} \frac{e^2 c^2}{2\epsilon_0 \hbar \omega} \int_{-\infty}^{\infty} dt_0 e^{i\omega t_0} \langle i | \sum_{\lambda=1}^2 \mathbf{e}_\lambda \cdot \tilde{\boldsymbol{\beta}}(t - t_0/2)^* \mathbf{e}_\lambda \cdot \tilde{\boldsymbol{\beta}}(t + t_0/2) | i \rangle. \quad (3.129)$$

If the commutation of the Heisenberg operators is not important, the expectation value of these operators corresponds to the classical trajectory.

In evaluating the matrix elements of Eq. (3.129), Baier and Katkov [5, 6, 7] recognizes that there are two types of quantum effects. The first of these is related to the quantum nature of the electron motion. The non-commutativity of the dynamic variables of the electron arising in this case is of order $\hbar\omega_0/E$ (where ω_0 is the revolution or oscillation frequency). The second type of quantum effects is associated with the recoil of the electron accompanying the emission of radiation and is of order $\hbar\omega/E$ (where ω is the photon frequency and is much larger than ω_0). Thus, one can neglect the commutator relations between an electron's dynamics variables (treating the electron orbit classically), but retained the commutator relations between electron and photon variables (taking into account the recoil). Unlike Schwinger [64], who expanded all commutators to the order of $\hbar$, the Baier-Katkov method is essentially an expansion in $1/\gamma$ because the motion of an electron in a magnetic field becomes more “classical” as the energy is increased. The first step of the Baier-Katkov method is to bring $\exp(\pm i\mathbf{k}\cdot\mathbf{r})$ to the center of the matrix by using the commutation relation [5, 7]

$$H_0 e^{-i\mathbf{k}\cdot\mathbf{r}} = e^{-i\mathbf{k}\cdot\mathbf{r}} (H_0 - \hbar\omega) \quad (3.130)$$

Then we have

$$\begin{aligned} dW_i = \frac{d\mathbf{k}}{(2\pi)^3} \frac{e^2 c^2}{2\epsilon_0 \hbar\omega} \int_{-\infty}^{\infty} dt_0 e^{i\omega t_0} \langle i | \sum_{\lambda=1}^2 \sqrt{\frac{1}{H_0 - e\Phi}} \mathbf{e}_\lambda \cdot (\mathbf{p} - e\mathbf{A})_1 c \sqrt{\frac{1}{H_0 - \hbar\omega - e\Phi}} \times \\ e^{i\mathbf{k}\cdot\mathbf{r}_1} e^{-i\mathbf{k}\cdot\mathbf{r}_2} \sqrt{\frac{1}{H_0 - \hbar\omega - e\Phi}} \mathbf{e}_\lambda \cdot (\mathbf{p} - e\mathbf{A})_2 c \sqrt{\frac{1}{H_0 - e\Phi}} | i \rangle. \end{aligned} \quad (3.131)$$

The crucial step of the Baier-Katkov method is the evaluation of

$$e^{i\mathbf{k}\cdot\mathbf{r}_1} e^{-i\mathbf{k}\cdot\mathbf{r}_2} \simeq \exp \left\{ -i\omega t_0 + i\omega \frac{H_0 - e\Phi}{H_0 - \hbar\omega - e\Phi} \left[t_0 - \frac{1}{c} \mathbf{n} \cdot (\mathbf{r}_2 - \mathbf{r}_1) \right] \right\}, \quad (3.132)$$

which is not trivial at all [5, 7]. By now, we have taken into account explicitly the commutation relations between electron and photon variables. We can therefore take the “quasiclassical” step to substitute the electron operators with their classical

correspondences and treat the transition rate as the rate of photon emissions:

$$\begin{aligned} \frac{dP_\gamma}{\hbar\omega} = & \frac{d\mathbf{k}}{(2\pi)^3} \frac{e^2 c^2}{2\epsilon_0 \hbar\omega} \int_{-\infty}^{\infty} \frac{dt_0}{1-y} \sum_{\lambda=1}^2 (\mathbf{e}_\lambda \cdot \boldsymbol{\beta}_1)(\mathbf{e}_\lambda \cdot \boldsymbol{\beta}_2) \\ & \cdot \exp \left\{ \frac{i\omega}{(1-v)} \left[t_0 - \frac{1}{c} \mathbf{n} \cdot (\mathbf{r}_2 - \mathbf{r}_1) \right] \right\}, \end{aligned} \quad (3.133)$$

where $\boldsymbol{\beta}_{1,2}$ and $\mathbf{r}_{1,2}$ are the values of the classical trajectory at time $t_1 = (t - t_0/2)$ and $t_2 = (t + t_0/2)$ respectively, and $v = \hbar\omega/(E - e\Phi)$. By using the polarization sum

$$\sum_{\lambda=1}^2 (\mathbf{e}_\lambda \cdot \boldsymbol{\beta}_1)(\mathbf{e}_\lambda \cdot \boldsymbol{\beta}_2) = \boldsymbol{\beta}_1 \cdot \boldsymbol{\beta}_2 - (\mathbf{n} \cdot \boldsymbol{\beta}_1)(\mathbf{n} \cdot \boldsymbol{\beta}_2) \quad (3.134)$$

and applying Eq. (3.54), we finally arrive at

$$\begin{aligned} \frac{1}{\hbar\omega} \frac{d^2 P_\gamma}{d\omega d\Omega} = & \frac{e^2}{16\pi^3 \epsilon_0 c \hbar} \frac{\omega}{(1-v)} \int_{-\infty}^{\infty} dt_0 [\boldsymbol{\beta}(t + t_0/2) \cdot \boldsymbol{\beta}(t - t_0/2) - 1] \\ & \cdot \exp \left\{ \frac{i\omega}{1-v} \left[t_0 - \frac{1}{c} \mathbf{n} \cdot (\mathbf{r}(t + t_0/2) - \mathbf{r}(t - t_0/2)) \right] \right\}, \end{aligned} \quad (3.135)$$

Divide Eq. (3.56) by $\hbar\omega$ and interpret the left hand side as the rate of photon emissions per unit frequency and per unit solid angle, we see that the quantum rate is just the same as the classical one with the substitution

$$\omega \rightarrow \frac{\omega}{(1-v)}. \quad (3.136)$$

For instance, to find out the quantum correction for synchrotron radiation, we can follow the expansion and integration techniques developed in Section 3.1.4 and obtain the Sokolov-Ternov spectrum formula for spinless particles [72, 73]:

$$\frac{dP_\gamma}{d\omega} = \frac{\sqrt{3}e^2\omega_0}{4\pi^2\epsilon_0 c} \gamma \frac{\omega}{\omega_c} \int_{\chi_q}^{\infty} K_{5/3}(x) dx, \quad (3.137)$$

where

$$\chi_q = \frac{\omega}{\omega_c} \frac{1}{1-v} = \frac{2\hbar\omega}{3\Upsilon(E - \hbar\omega)}. \quad (3.138)$$

Therefore, the Sokolov-Ternov power spectrum has the same low energy behavior as the classical formula Eq. (3.71) ($\propto \omega^{1/3}$), but the high energy part is truncated at $\omega = E/\hbar$, which is required by energy conservation.

Chapter 4

Radiation Damping and Quantum Excitation

In the preceding chapter both the classical and the quantum theory of radiation from relativistic electrons were discussed. It is evident that the emitted radiation carries off energy and momentum and so must perturb the subsequent motion of the electrons. The question arises of what accumulated effects the perturbation will have on the stability of the electron trajectories in various guiding fields. The investigation of this question in electron synchrotron and storage rings led to the well-established results of radiation damping and quantum excitation [43, 38, 72, 59]. Among them, the work of Robinson and Sands are particularly noteworthy. Robinson [38] considered the effects of radiation on the six-dimensional phase space and derived a damping criterion that connects the individual damping rates. In the treatise by Sands [59], the quantum nature of radiation is modeled as the statistical noise of the classical, continuous spectrum of bending magnet radiation and quantum excitation is treated quasiclassically as diffusion. The interplay between radiation damping and quantum excitation gives rise to equilibrium emittances for a storage ring, and the art of lattice design in modern synchrotron radiation sources or damping rings is to minimize these emittances under various constraints.

Although the quasiclassical model of quantum radiation is a good approximation in most practical applications, it could fail in certain cases and may lead to new

perspective about ultra-low emittance generation. Recently, we investigated such cases in a series of papers [25, 26, 27, 28, 29, 31, 33] and found that radiation reaction in a focusing system is fundamentally different from that in a bending system. In particular, quantum excitation to the transverse emittances can not exist in a straight, continuous focusing channel, and will be suppressed by the focusing environment in a bending and focusing combined system.

The organization of this chapter falls into three parts. In Section 4.1, we pay special attention to the assumptions that lead to the quasiclassical approach of radiation damping and quantum excitation in electron storage rings. We derive all the standard results in a consistent and compact manner by following the evolution of single particle invariants (in the absence of radiation). In Sections 4.2 and 4.3, we study straight focusing channels where both the radiation and the radiation reaction arise from the focusing environment. The discussion of quantum excitation is quantum mechanical in origin because the quasiclassical assumptions are not valid in such systems. By comparing a focusing channel with an undulator that generates a very similar radiation pattern, we illustrate the fundamental difference in terms of radiation reaction between focusing and bending systems. Finally, in Section 4.4, we employ the quantum mechanical perturbation approach to calculate the radiation damping and quantum excitation in a system where both bending and focusing are important. The general results obtained in this section unify those of Section 4.1 and Section 4.2 and may have important consequence in reaching the coolest state for electron beams.

4.1 Electron Storage Rings

4.1.1 Introduction

In an electron synchrotron or storage ring, the electron executes stable betatron and synchrotron oscillations in the transverse and longitudinal degrees of freedom. In the absence of radiation, the particle dynamics is Hamiltonian and we can find constants of motion such as oscillation amplitudes, actions and normalized emittances.

However, emission of synchrotron radiation induced by bending magnets causes the appearance of a reactive force on the emitting electron [73]. On the average, the reactive force is directly against the direction of motion, causing the damping of the oscillatory motions.

The instantaneous radiation power radiated by a relativistic electron at energy E is given by Eq. (3.34), i.e.,

$$P_\gamma = \frac{cC_\gamma}{2\pi} \frac{E^4}{\rho^2} = \frac{e^2 c^3 C_\gamma}{2\pi} E^2 B^2, \quad (4.1)$$

where B is the magnetic field strength, ρ is the local radius of curvature and C_γ is the radiation constant defined in Eq. (3.35). For the electron at the synchronous energy E_0 , the total energy radiated in one revolution is

$$U_0 = \oint dt P_\gamma = \frac{C_\gamma E_0^4}{2\pi} \oint \frac{ds}{\rho^2} \quad (4.2)$$

Therefore we have the average radiation power

$$\langle P_\gamma \rangle = \frac{U_0}{T_0} = \frac{cC_\gamma E_0^4}{2\pi} \oint \frac{ds}{2\pi R} \frac{1}{\rho^2} \quad (4.3)$$

where $T_0 = c/2\pi R$ is the revolution period, and R is the average radius of the storage ring.

The fact that higher energy electrons in a bunch lose more energy than lower energy electrons will contribute to radiation damping in the longitudinal phase space. Furthermore, the fact that electrons on the average lose momenta in all three degrees of freedom to the radiation will provide the phase space damping of transverse phase space. Thus, both the longitudinal and the transverse damping rates are proportional to the energy damping rate which is given by a characteristic damping rate for the bending:

$$\Gamma_b = \frac{\langle P_\gamma \rangle}{E_0} = \frac{cC_\gamma E_0^3}{2\pi} \left\langle \frac{1}{\rho^2} \right\rangle_s, \quad (4.4)$$

where the index s indicates averaging around the ring.

Nevertheless, particle motion does not contract to a point in phase space because synchrotron radiation occurs in quanta of discrete energies. In an electron damping

ring, each time a photon is emitted the energy of the electron makes a small discontinuous jump. This quantum “noise” disturbs the electron orbit. The cumulative effect of many such disturbances introduces diffusion into oscillation modes. The amplitude of oscillation will grow until quantum excitation is, on average, balanced by the damping of the oscillations. While radiation damping depends on the average rate of energy emission and not on any of its statistical properties, the excitation effects are due to fluctuations in the radiation about its average rate.

Such quasiclassical statements about quantum radiation can be justified by the following points [72, 59]: First, as we see from Section 3.1.3, the typical length associated with a photon emission (the radiation formation length) is on the order of ρ/γ , which is usually much shorter than the average betatron and synchrotron oscillation length in a normal storage ring. Thus, one can model the quantum emission to be instantaneous. Secondly, emission times of the individual quanta are statistically independent. Since the energy of each photon is very small fraction of the electron energy, we may consider the emission of successive quanta to be a purely random (Poisson) process that follows the continuous, classical radiation spectrum.

Let us define the number of photons emitted per unit time with energies between $\hbar\omega$ and $\hbar(\omega + d\omega)$ in the direction $\mathbf{n}$ that contains a solid angle $d\Omega$:

$$\dot{n}_\gamma(\omega, \mathbf{n}) = \frac{1}{\hbar\omega} \frac{d^2 P_\gamma}{d\omega d\Omega}, \quad (4.5)$$

where $d^2 P_\gamma/(d\omega d\Omega)$ is the classical angular spectral distribution of the radiated power calculated in Section 3.1. As we see from Section 3.2, $\dot{n}_\gamma(\omega, \mathbf{n})$ corresponds to the classical limit of the transition rate between states that allow for such photon emissions. The expected rate of change for an invariant J (in the absence of radiation) due to the radiation, averaged over one revolution period T_0 , is then given by

$$\left\langle \frac{dJ}{dt} \right\rangle = \oint \frac{dt}{T_0} \int \int d\omega d\Omega [\delta J(\omega, \mathbf{n}) \dot{n}_\gamma(\omega, \mathbf{n})], \quad (4.6)$$

where $\delta J(\omega, \mathbf{n})$ is the change of J after a photon with energy $\hbar\omega$ is emitted in the direction $\mathbf{n}$. We use the convention that $\delta J(\omega, \mathbf{n})$ is negative if J decreases after the emission. For example, the rate of energy decay $\langle dE/dt \rangle$ is obtained by replacing δJ

with $\delta E = -\hbar\omega$ and is just the negative of the radiated power. In general, this quasiclassical approach can give rise to radiation damping as well as quantum excitation because it incorporates both the quantum picture of a single photon emission and the continuous, classical spectrum of radiation.

4.1.2 Transverse Damping and Excitation

Let us employ the above quasiclassical approach to study the radiation effects on the horizontal and the vertical betatron motions. In the horizontal plane, the total displacement is the sum of the betatron displacement and the equilibrium orbit displacement, i.e.

$$x = x_\beta + \eta \frac{E - E_0}{E_0}, \quad (4.7)$$

where $\eta(s)$ is the dispersion function that satisfies Eq. (A.18).

As an electron *suddenly* emits a photon with energy $\hbar\omega$ that recoils *directly* against the electron direction on average, it will not change its actual position and direction (this statement is only approximately true even under the instantaneous emission assumption, see the discussion of the vertical betatron motion on the opening angle effect). However, the position of a particle with respect to the equilibrium orbit is changed because the sudden jump of the energy of the electron changes the equilibrium orbit, i. e.,

$$\begin{aligned} \delta x = 0 = \delta x_\beta - \eta \frac{\hbar\omega}{E_0} &\implies \delta x_\beta = \eta \frac{\hbar\omega}{E_0}, \\ \delta x' = 0 = \delta x'_\beta - \eta' \frac{\hbar\omega}{E_0} &\implies \delta x_\beta = \eta' \frac{\hbar\omega}{E_0}, \end{aligned} \quad (4.8)$$

where $\eta'(s) = d\eta/ds$. From Appendix A, the horizontal action (an invariant in the absence of radiation) is

$$J_x = \frac{p_0}{2\beta_x} \left[x_\beta^2 + (\beta_x x'_\beta - \frac{\beta'_x}{2} x_\beta)^2 \right], \quad (4.9)$$

where $\beta_x(s)$ and $\beta'_x(s) = d\beta/ds$ are the horizontal betatron function and its derivative, respectively. The resulting change in the horizontal action after a photon is emitted

is then given by

$$\begin{aligned} \delta J_x = & -J_x \left(\frac{\hbar\omega}{E_0} \right) + \frac{p_0}{\beta_x} \left[\eta x_\beta + \left(\beta_x \eta' - \frac{\beta'_x}{2} \eta \right) \left(\beta_x x'_\beta - \frac{\beta'_x}{2} x_\beta \right) \right] \left(\frac{\hbar\omega}{E_0} \right) \\ & + \frac{p_0}{2\beta_x} \left[\eta^2 + \left(\beta_x \eta' - \frac{\beta'_x}{2} \eta \right)^2 \right] \left(\frac{\hbar\omega}{E_0} \right)^2. \end{aligned} \quad (4.10)$$

Since δJ_x in Eq. (4.10) does not depend on the photon direction $\mathbf{n}$, applying Eq. (4.6) to J_x yields:

$$\begin{aligned} \left\langle \frac{dJ_x}{dt} \right\rangle &= \oint \frac{dt}{T_0} \int d\omega \frac{\delta J_x(\omega)}{\hbar\omega} \frac{dP_\gamma}{d\omega} \\ &= -J_x \oint \frac{dt}{T_0} \frac{P_\gamma}{E_0} + \oint \frac{dt}{T_0} \left(\frac{P_\gamma}{E_0} \right) \frac{p_0}{\beta_x} \left[\eta x_\beta + \left(\beta_x \eta' - \frac{\beta'_x}{2} \eta \right) \left(\beta_x x'_\beta - \frac{\beta'_x}{2} x_\beta \right) \right] \\ &\quad + \oint \frac{dt}{T_0} \frac{p_0}{2\beta_x} \left[\eta^2 + \left(\beta_x \eta' - \frac{\beta'_x}{2} \eta \right)^2 \right] \int d\omega \frac{\hbar\omega}{E_0^2} \frac{dP_\gamma}{d\omega}, \end{aligned} \quad (4.11)$$

The first term of Eq. (4.11) is the normal radiation damping term. With the characteristic damping coefficient Γ_b defined in Eq. (4.4), we can write

$$\left\langle \frac{dJ_x}{dt} \right\rangle_1 = -J_x \Gamma_b. \quad (4.12)$$

Contrary to a popular misstatement that the damping of the beam emittance “occurs” in the RF cavity when energy lost is restored, our approach clearly shows that *radiation damping occurs when radiation takes place*. There is no contradiction, however, because our approach uses the invariant action J_x which is ultimately related to the normalized emittance. As stated in Section 2.3, while the geometric emittance can be adiabatically damped during the RF acceleration, the normalized emittance is an adiabatic invariant under acceleration, and can only be damped by dissipative forces such as the radiation reaction.

To compute the second term of Eq. (4.11), we first note that

$$dt = \frac{1}{c} \left(1 + \frac{x}{\rho} \right) ds. \quad (4.13)$$

Use the fact that

$$P_\gamma \propto E^2 B^2 \propto E^2 (B_0 + B_1 x)^2, \quad (4.14)$$

we can take into account the explicit x dependence of P_γ to the first order in x (i.e., neglect the radiation due to the focusing field alone):

$$P_\gamma(x) = P_\gamma \left(1 + \frac{2B_1}{B_0}x \right) = P_\gamma (1 + 2k_q \rho x), \quad (4.15)$$

where $k_q(s) = B_1/(B_0\rho)$ is the focusing function defined in Appendix A. Thus, the second term in Eq. (4.11) can be written as

$$\begin{aligned} \left\langle \frac{dJ_x}{dt} \right\rangle_2 &= \oint \frac{ds}{cT_0} \left(\frac{P_\gamma}{E_0} \right) \frac{p_0}{\beta_x} \left(1 + \frac{x}{\rho} \right) (1 + 2k_q \rho x) \\ &\times \left[\eta x_\beta + \left(\beta_x \eta' - \frac{\beta'_x}{2} \eta \right) \left(\beta_x x'_\beta - \frac{\beta'_x}{2} x_\beta \right) \right] \end{aligned} \quad (4.16)$$

To relate the right hand side of Eq. (4.16) to the horizontal action itself, we invoke the transformation equations (A.24) of Appendix A:

$$\begin{aligned} x_\beta &= \sqrt{\frac{2J_x \beta_x}{p_0}} \cos \phi, \\ x'_\beta &= -\sqrt{\frac{2J_x}{p_0 \beta_x}} \left(\sin \phi - \frac{1}{2} \beta'_x \cos \phi \right), \end{aligned} \quad (4.17)$$

or

$$\beta_x x'_\beta - \frac{\beta'_x}{2} x_\beta = -\sqrt{\frac{2J_x \beta_x}{p_0}} \sin \phi. \quad (4.18)$$

After averaging over the fast oscillation (phase oscillation) and keeping only the leading non-vanishing term, we have

$$\begin{aligned} \left\langle \frac{dJ_x}{dt} \right\rangle_2 &= \oint \frac{ds}{cT_0} \left(\frac{P_\gamma}{E_0} \right) \frac{p_0}{\beta_x} \left(\frac{x_\beta}{\rho} + 2k_q \rho x_\beta \right) \eta x_\beta \\ &= \left[\oint \frac{ds}{2\pi R} \left(\frac{P_\gamma}{E_0} \right) \left(\frac{1}{\rho} + 2k_q \rho \right) \right] \eta J_x \equiv \mathcal{D} \Gamma_b J_x, \end{aligned} \quad (4.19)$$

where

$$\mathcal{D} = \frac{1}{\Gamma_b} \oint \frac{ds}{2\pi R} \left(\frac{P_\gamma}{E_0} \right) \left(\frac{1}{\rho} + 2k_q \rho \right) \eta = \frac{\langle \eta(1 + 2\rho^2 k_q)/\rho^3 \rangle_s}{\langle 1/\rho^2 \rangle_s}. \quad (4.20)$$

Hence Eq. (4.19) can be damping or anti-damping depending on the sign of $\mathcal{D}$. The second term in the numerator of Eq. (4.20) becomes significant for combined-function magnets (where $\rho k_q \neq 0$) and vanishes for separated-function magnets (where $\rho k_q = 0$). For an isomagnetic ($\rho(s) = \rho_0$ at dipoles), separated-function ring, we have

$$\mathcal{D} = \frac{1}{2\pi\rho_0} \oint \frac{\eta(s)}{\rho_0} ds = \frac{\alpha_c R}{\rho_0} \ll 1, \quad (4.21)$$

where $\alpha_c = \langle \eta/\rho \rangle_s$ is the momentum compaction factor and is usually much less than 1. However, for an isomagnetic, combined-function ring, one can use the smooth approximation ($\eta \simeq \bar{\beta}^2/\rho_0$ and $k_q \simeq 1/\bar{\beta}^2$) to prove that

$$\mathcal{D} = 2 + \frac{\alpha_c R}{\rho_0} \simeq 2. \quad (4.22)$$

Combining Eq. (4.19) with Eq. (4.12), we have

$$\left\langle \frac{dJ_x}{dt} \right\rangle_{\text{RD}} = -(1 - \mathcal{D})\Gamma_b J_x \equiv -\mathcal{J}_x \Gamma_b J_x, \quad (4.23)$$

where $\mathcal{J}_x = 1 - \mathcal{D}$ is the horizontal damping partition number. By adjusting $\mathcal{D}$ through proper arrangement of focusing and bending magnets, the horizontal action can be either damped ($\mathcal{J}_x > 0$) or anti-damped ($\mathcal{J}_x < 0$).

The third term of Eq. (4.11) is quantum excitation because it is positive and $\hbar$ dependent. Let us write

$$\left\langle \frac{dJ_x}{dt} \right\rangle_{\text{QE}} = \hbar \frac{p_0}{2E_0^2} \oint \frac{ds}{2\pi R} \mathcal{H}(s) \int_0^\infty d\omega \omega \frac{dP_\gamma}{d\omega}, \quad (4.24)$$

where the $\mathcal{H}$ function is a property of the guide field:

$$\mathcal{H} = \frac{1}{\beta_x} [\eta^2 + (\beta_x \eta' - \frac{\beta'_x}{2} \eta)^2] = \beta_x \eta'^2 + 2\alpha_x \eta \eta' + \gamma_x \eta^2, \quad (4.25)$$

and $dP_\gamma/d\omega$ is the synchrotron radiation power spectrum given by Eq. (3.75). Thus, we have

$$\begin{aligned} \int_0^\infty d\omega \omega \frac{dP_\gamma}{d\omega} &= \frac{9\sqrt{3}}{8\pi} P_\gamma \int_0^\infty d\omega \left(\frac{\omega}{\omega_c} \right)^2 \int_{\omega/\omega_c}^\infty K_{5/3}(x) dx \\ &= \frac{9\sqrt{3}}{8\pi} P_\gamma \omega_c \int_0^\infty d\chi \chi^2 \int_\chi^\infty K_{5/3}(x) dx \\ &= \frac{3\sqrt{3}}{8\pi} P_\gamma \omega_c \int_0^\infty \chi^3 K_{5/3}(\chi) d\chi \end{aligned} \quad (4.26)$$

By using the integral (6.561.16) of Ref. [22]

$$\int_0^\infty \chi^3 K_{5/3}(\chi) d\chi = 4\Gamma\left(2 + \frac{5}{6}\right) \Gamma\left(2 - \frac{5}{6}\right) = \frac{55\pi}{27}, \quad (4.27)$$

and the definition $\omega_c = 3c\gamma_0^3/(2\rho)$, we can write

$$\left\langle \frac{dJ_x}{dt} \right\rangle_{\text{QE}} = \hbar \frac{55\sqrt{3}}{96} \gamma_0^3 \oint \frac{ds}{2\pi R} \frac{\mathcal{H}}{\rho} \frac{P_\gamma}{E_0} = \hbar \frac{55\sqrt{3}}{96} \Gamma_b \frac{\gamma_0^3 \langle \mathcal{H}/\rho^3 \rangle_s}{\langle 1/\rho^2 \rangle_s}. \quad (4.28)$$

Therefore, the expected rate of change for the horizontal action including radiation damping and quantum excitation is

$$\left\langle \frac{dJ_x}{dt} \right\rangle = -\mathcal{J}_x \Gamma_b J_x + \hbar \frac{55\sqrt{3}}{96} \Gamma_b \frac{\gamma_0^3 \langle \mathcal{H}/\rho^3 \rangle_s}{\langle 1/\rho^2 \rangle_s}. \quad (4.29)$$

In the case that $\mathcal{J}_x > 0$, one can find the equilibrium horizontal action by setting $\langle dJ_x/dt \rangle = 0$ in Eq. (4.29), i.e., when the radiation damping is balanced by the quantum excitation. Averaging over the beam distribution, we see from Section 2.4 that the normalized emittance and the action are related through $\varepsilon_n = \langle J \rangle / (mc)$. Thus, we obtain the equilibrium horizontal normalized emittance in a storage ring as

$$\varepsilon_x^n = \frac{55\sqrt{3}}{96} \lambda_c \frac{\gamma_0^3 \langle \mathcal{H}/\rho^3 \rangle_s}{j_x \langle 1/\rho^2 \rangle_s}. \quad (4.30)$$

where

$$\lambda_c = \frac{\hbar}{m_e c} = 3.86 \times 10^{-13} \text{m} \quad (4.31)$$

is the Compton wavelength of the electron. For isomagnetic storage rings, the result can be simplified to

$$\varepsilon_x^n = \frac{55\sqrt{3}}{96} \lambda_c \frac{\gamma_0^3 \langle \mathcal{H} \rangle_s}{\mathcal{J}_x \rho_0}, \quad (4.32)$$

where $\langle \mathcal{H} \rangle_s$ is evaluated in dipoles with

$$\langle \mathcal{H} \rangle_s = \frac{1}{2\pi\rho_0} \int_{\text{dipole}} \mathcal{H} ds. \quad (4.33)$$

In the vertical plane the bending radius $\rho \rightarrow \infty$. If we apply the same analysis as in the horizontal plane, we see that the equilibrium vertical emittance reduces to zero

from Eq. (4.30) or Eq. (4.32). In fact, we have neglected the fact that synchrotron radiation photons are emitted not strictly in the forward direction but rather into a small angle $\pm 1/\gamma$. Photons emitted at a slight angle exert a recoil on the electron normal to the direction of the trajectory. A photon emitted at an angle ϑ with respect to the horizontal plane causes a variation of the vertical slope by

$$\delta y' = -\frac{\hbar\omega}{E_0} \sin \vartheta \approx -\frac{\hbar\omega}{E_0} \vartheta \quad (4.34)$$

while the position is not changed due to the instantaneous emission. This leads to a change in the vertical action

$$\delta J_y = -J_y \left(\frac{\hbar\omega}{E_0} \right) - p_0 \left(\beta_y y' - \frac{\beta_y'}{2} y \right) \left(\frac{\hbar\omega}{E_0} \right) \vartheta + \frac{p_0 \beta_y}{2} \left(\frac{\hbar\omega}{E_0} \right)^2 \vartheta^2. \quad (4.35)$$

The first term again gives the damping rate similar to Eq. (4.12). The second term vanishes after averaging over the phase oscillation. Thus, the total vertical damping rate is given by

$$\left\langle \frac{dJ_y}{dt} \right\rangle_{\text{RD}} = -\mathcal{J}_y \Gamma_b J_y, \quad \text{with} \quad \mathcal{J}_y = 1. \quad (4.36)$$

The rate of quantum excitation arisen from the third term of Eq. (4.35) can be derived analogous to the general derivation above

$$\begin{aligned} \left\langle \frac{dJ_y}{dt} \right\rangle_{\text{QE}} &= \hbar \frac{p_0}{2E_0^2} \oint \frac{ds}{2\pi R} \beta_y \int \int d\omega d\Omega \vartheta^2 \omega \frac{d^2 P_\gamma}{d\omega d\Omega} \\ &= \hbar \frac{p_0}{2E_0^2} \oint \frac{ds}{2\pi R} \beta_y \int \int d\omega d(\sin \vartheta) \vartheta^2 \omega \frac{d^2 P_\gamma}{d\omega d(\sin \vartheta)}, \end{aligned} \quad (4.37)$$

where $\frac{d^2 P_\gamma}{d\omega d(\sin \vartheta)}$ is given by Eq. (3.68). The double integration with respect to ω and ϑ is carried out in Ref. [55]. Combining with Eq. (4.36), the total rate of change for the vertical action is

$$\left\langle \frac{dJ_y}{dt} \right\rangle_{\text{RD}} = -\mathcal{J}_y \Gamma_b J_y, + \hbar \frac{13\sqrt{3}}{96} \Gamma_b \frac{\gamma_0 \langle \beta_y \rangle_s}{\rho}. \quad (4.38)$$

When relating the action to the normalized emittance and setting the total rate of change equal to zero, we find the equilibrium vertical normalized emittance

$$\begin{aligned}\varepsilon_y^n &= \frac{13\sqrt{3}}{96}\lambda_c \frac{\gamma_0 \langle \beta_y / \rho^3 \rangle_s}{\mathcal{J}_y \langle 1/\rho^2 \rangle_s} \\ &= \frac{13\sqrt{3}}{96}\lambda_c \frac{\gamma_0 \langle \beta_y \rangle_s}{\mathcal{J}_y \rho_0}, \quad \text{for isomagnetic rings.}\end{aligned}\tag{4.39}$$

In order to compare with Eq. (4.30), we assume the storage ring is isomagnetic and separated function ($\mathcal{J}_x = \mathcal{J}_y = 1$). By using smooth approximation ($\beta_x = \beta_y = \bar{\beta}$, $\eta(s) \simeq \bar{\beta}^2/\rho_0$, and $\beta'_{x,y} = \eta' = 0$), we obtain

$$\begin{aligned}\varepsilon_x^n &\simeq \frac{55\sqrt{3}}{96}\lambda_c \frac{\bar{\beta}^3}{(\rho_0/\gamma_0)^3}, \\ \varepsilon_y^n &\simeq \frac{13\sqrt{3}}{96}\lambda_c \frac{\bar{\beta}}{(\rho_0/\gamma_0)}.\end{aligned}\tag{4.40}$$

Thus, the equilibrium vertical emittance is an order of $\gamma_0^2 \bar{\beta}^2 / \rho_0^2$ smaller than the horizontal one. It is therefore justified to neglect this term in the calculation of the horizontal beam emittance. In reality we observe a larger beam emittance in the vertical plane due to coupling or due to vertical steering errors which create a small vertical dispersion and, consequently, a small vertical beam emittance [55].

Since the radiation formation length ρ_0/γ is always much shorter than the reduced betatron wavelength $\bar{\beta}$ in a normal storage ring, Eq. (4.40) states that the transverse normalized emittances in equilibrium are always much larger than the Compton wavelength. For example, the SLC damping ring can damp both the electron and the positron beams to $\varepsilon_{x,y}^n \sim 10^{-5}$ m [20], which is about eight orders of magnitude larger than the Compton wavelength. However, Eq. (4.40) also suggests that the equilibrium normalized emittance can be reduced to approach the Compton wavelength as the radiation formation length is made closer to the average beta function. Nevertheless, the extrapolation stops at some points because the quasiclassical approximation of instantaneous radiation fails when the radiation formation length is comparable to the betatron wavelength. Before we investigate this new parameter regime, we examine the longitudinal damping and excitation for completeness.

4.1.3 Longitudinal Damping and Excitation

Electrons execute synchrotron oscillations in the longitudinal phase space (δ, φ) , where $\delta = \Delta E/E_0$ is the fractional energy difference, and φ is the phase relative to the synchronized RF phase. For small amplitude oscillations, we have [78]:

$$\frac{\Delta E}{E_0} = A_\delta \sin(\omega_s t), \quad \varphi = \frac{h\omega_0\eta_c}{\omega_s} A_\delta \cos(\omega_s t), \quad (4.41)$$

where

$$\omega_s = \omega_0 \sqrt{\frac{h|\eta_c|eV_0 \cos \psi_s}{2\pi\beta E_0}} \quad (4.42)$$

is the synchrotron frequency, $h = \omega_{rf}/\omega_0$ is the RF harmonic number, $\eta_c = \alpha_c - 1/\gamma^2$ is the momentum compaction, V_0 is the peak RF voltage and ψ_s is the synchronous phase. The peak energy spread A_δ is a constant of motion given by

$$A_\delta^2 = \left(\frac{\Delta E}{E_0}\right)^2 + \varphi^2 \left(\frac{\omega_s}{h\omega_0\eta_c}\right)^2. \quad (4.43)$$

When a photon with energy $\hbar\omega$ is emitted, it does not change the phase suddenly (because the radiation formation length is always much smaller than the reduced synchrotron wavelength c/ω_s). Thus, we have

$$\delta(A_\delta^2) = -2 \left(\frac{\Delta E}{E_0}\right) \left(\frac{\hbar\omega}{E_0}\right) + \left(\frac{\hbar\omega}{E_0}\right)^2 \quad (4.44)$$

Applying Eq. (4.6) to $\delta(A_\delta^2)$ yields:

$$\left\langle \frac{d(A_\delta^2)}{dt} \right\rangle = -2 \oint \frac{dt}{T_0} \left(\frac{P_\gamma}{E_0}\right) \left(\frac{\Delta E}{E_0}\right) + \frac{\hbar}{E_0^2} \oint \frac{dt}{T_0} \int d\omega \omega \frac{dP_\gamma}{d\omega} \quad (4.45)$$

The damping term can be calculated in the following way: First, using $P_\gamma \propto E^2 B^2$, we expand P_γ around $P_{\gamma 0}(E_0, B_0)$:

$$P_\gamma = P_{\gamma 0} \left(1 + \frac{\Delta E}{E_0} + 2k_q \rho x\right). \quad (4.46)$$

Together with Eq. (4.13), we obtain

$$\left\langle \frac{d(A_\delta^2)}{dt} \right\rangle_{\text{RD}} = -2 \oint \frac{ds}{2\pi R} \frac{P_{\gamma 0}}{E_0} \left(1 + \frac{x}{\rho}\right) \left(1 + 2\frac{\Delta E}{E_0} + 2k_q \rho x\right) \left(\frac{\Delta E}{E_0}\right). \quad (4.47)$$

Writing $x = x_\beta + \eta \Delta E / E_0$, and averaging over betatron and synchrotron oscillation, we arrive at

$$\begin{aligned} \left\langle \frac{d(A_\delta^2)}{dt} \right\rangle_{\text{RD}} &= -2 \oint \frac{ds}{2\pi R} \frac{P_{\gamma 0}}{E_0} \left(2 + \frac{\eta}{\rho} + 2k_q \rho \eta \right) \left(\frac{\Delta E}{E_0} \right)^2 \\ &= - \oint \frac{ds}{2\pi R} \frac{P_{\gamma 0}}{E_0} \left(2 + \frac{\eta}{\rho} + 2k_q \rho \eta \right) A_\delta^2 \\ &= -(2 + \mathcal{D}) \Gamma_b A_\delta^2 \equiv -\mathcal{J}_s \Gamma_b A_\delta^2, \end{aligned} \quad (4.48)$$

where Γ_b and $\mathcal{D}$ are defined in Eq. (4.4) and Eq. (4.20), and $\mathcal{J}_s = 2 + \mathcal{D}$ is the longitudinal damping partition number. It is noteworthy that

$$\begin{aligned} \sum \mathcal{J}_i &= \mathcal{J}_x + \mathcal{J}_y + \mathcal{J}_s = 4, \quad \text{or} \\ \mathcal{J}_x &= 1 - \mathcal{D}, \quad \mathcal{J}_y = 1, \quad \mathcal{J}_s = 2 + \mathcal{D}. \end{aligned} \quad (4.49)$$

The fact that the damping rates in three degrees of freedom are related through a sum rule is well-known as the *Robinson damping criterion*. It was first derived by Robinson [38] under a very general consideration. Thus, the damping partition numbers and the damping rates between the horizontal and the longitudinal dimensions can be adjusted through the $\mathcal{D}$ parameter.

The fluctuating nature of quantum emission is reflected in the second term of Eq. (4.45), which leads to quantum excitation to the energy spread:

$$\left\langle \frac{d(A_\delta^2)}{dt} \right\rangle_{\text{QE}} = \frac{55\sqrt{3}}{48} \frac{\hbar}{m_e c} \gamma_0^2 \oint \frac{dt}{T_0} \frac{1}{\rho} \frac{P_\gamma}{E_0} = \frac{55\sqrt{3}}{48} \lambda_c \gamma_0^2 \Gamma_b \frac{\langle 1/\rho^3 \rangle_s}{\langle 1/\rho^2 \rangle_s}. \quad (4.50)$$

We have used Eq. (4.26) and Eq. (4.27) in order to obtain the above result. The equilibrium energy spread is reached when the damping effect balances the average effect of quantum fluctuation. For a Gaussian distribution of a damped electron bunch, the RMS energy spread is given by

$$\begin{aligned} \sigma_\delta^2 &= \frac{1}{2} A_\delta^2 = \frac{55\sqrt{3}}{96} \lambda_c \frac{\gamma_0^2}{\mathcal{J}_s} \frac{\langle 1/\rho^3 \rangle_s}{\langle 1/\rho^2 \rangle_s} \\ &= \frac{55\sqrt{3}}{96} \lambda_c \frac{\gamma_0^2}{\mathcal{J}_s \rho_0}, \quad \text{for isomagnetic rings.} \end{aligned} \quad (4.51)$$

Thus, the equilibrium RMS energy spread in an electron storage ring depends only on the beam energy and the bending radius. Nevertheless, the bunch length can still be controlled by the RF cavity and lattice functions. From Eq. (4.41), the RMS bunch length at equilibrium is given by

$$\sigma_s = \lambda_{rf} \frac{\sigma_\varphi}{2\pi} = \frac{c|\eta_c|}{\omega_s} \sigma_\delta = \frac{\sqrt{2\pi}c}{\omega_0} \sqrt{\frac{\eta_c E_0}{heV_0 \cos \psi_s}} \sigma_\delta. \quad (4.52)$$

where λ_{rf} is the RF wavelength. Since the energy spread can be reduced by adiabatic damping in a linear accelerator, it is meaningful to define an invariant normalized longitudinal emittance in the longitudinal phase space:

$$\varepsilon_s^n \equiv \gamma \sigma_\delta \sigma_s. \quad (4.53)$$

4.2 Straight, Continuous Focusing Channels

To illustrate the effects of focusing on radiation damping and quantum excitation, we now study a straight, continuous focusing system where both the radiation and the radiation reaction are generated by the linearly varying focusing field alone. Recent developments in advanced acceleration concepts [1] require very strong transverse focusing to maintain beam stability, and novel ideas such as channeling acceleration [15, 14, 16] utilize the super-strong microscopic focusing field existing in a crystal channel. Electron or positron channeling in crystals gives rise to intense channeling radiation [44], which will in turn affect the electron dynamics. Experimental investigation of radiative cooling in strong crystalline fields is also in progress [10]. Thus, it is important both conceptually and practically to understand the radiation effects of a continuous focusing field.

4.2.1 Lack of Quantum Excitation and the Transverse Ground State

Let us take the generic focusing model of Section 3.1.5: a continuous, transverse focusing force $(-K_x \mathbf{x})$ and a free, relativistic longitudinal z motion. We postpone

the discussion of the other transverse dimension to Section 4.2.4. The Hamiltonian and the equations of motion have been give in Section 3.1.5. Let us rewrite the expanded Hamiltonian here:

$$H = E_z + \frac{p_x^2 c^2}{2E_z} + \frac{K_x x^2}{2}, \quad \text{with} \quad E_z \equiv \sqrt{m_e^2 c^4 + p_z^2 c^2}. \quad (4.54)$$

A simple canonical transformation from (x, p_x) to the action-angle variables (J_x, ϕ) is given by

$$x = \sqrt{\frac{2J_x \omega_x}{K_x}} \cos \phi, \quad p_x = \sqrt{\frac{2J_x \omega_x E_z}{c^2}} \sin \phi, \quad (4.55)$$

where $\omega_x = \sqrt{K_x c^2 / E_z}$ is the transverse oscillation frequency. Thus, we obtain

$$H = \sqrt{m_e^2 c^4 + p_z^2 c^2} + J_x \omega_x. \quad (4.56)$$

It is obvious that both p_z and J_x are constants of motion because their conjugate variables are absent in the Hamiltonian.

The radiation spectrum has been calculated in Section 3.1.5. To find out the radiation effects on the transverse oscillation, we follow the spirit of the quasiclassical approach outlined in Section 4.1.1 to look for changes of the transverse action J_x after a photon is emitted. However, unlike in Section 4.1.2, we cannot assume *a priori* how the instantaneous position x and the momentum p_x change after the photon emission because the radiation may be formed over many oscillation wavelengths (see Section 3.1.5) and the transverse focusing force may not guarantee the recoil is directly against the electron direction. Instead, we invoke the quantum mechanical treatment to directly calculate the changes of invariants (corresponding to certain quantum numbers).

Since we do not care about the spin degrees of freedom, we employ the Klein-Gordon equation (i.e. Eq. (3.109) of Chapter 3) to describe the wavefunction $\Psi(\mathbf{r}, t)$ of the channeled electrons:

$$[(-i\hbar \nabla - e \mathbf{A}_{\text{rad}})^2 c^2 + m_e^2 c^4] \Psi(\mathbf{r}, t) = \left(i\hbar \frac{\partial}{\partial t} - \frac{1}{2} K_x x^2 \right)^2 \Psi(\mathbf{r}, t) \quad (4.57)$$

In the absence of radiation, we let $\mathbf{A}_{\text{rad}} = 0$ and look for the energy levels E and the stationary states $\Psi(\mathbf{r}, t) = e^{-iEt/\hbar}\psi(\mathbf{r})$ of Eq. (4.57), i.e., we need to solve for

$$\left[-\hbar^2 c^2 \left(\frac{\partial^2}{\partial x^2} + \frac{\partial^2}{\partial z^2} \right) + m_e^2 c^4 \right] \psi(x, z) = \left(E - \frac{1}{2} K_x x^2 \right)^2 \psi(x, z). \quad (4.58)$$

Because there is no z dependence in the unperturbed Hamiltonian, we can assume the solution is of the form $X(x) \exp(ip_z/\hbar z)$. Insert this into Eq. (4.58), we obtain a Schrödinger equation for the transverse wavefunction $X(x)$:

$$\left(-\hbar^2 c^2 \frac{\partial^2}{\partial x^2} + E K_x x^2 \right) X(x) = (E^2 - p_z^2 c^2 - m_e^2 c^4) X(x) = (E^2 - E_z^2) X(x), \quad (4.59)$$

where we have ignore $(K_x x^2)^2$ term because $\theta_p \ll 1$. Dividing both sides of Eq. (4.59) by $2E \simeq 2E_z$ yields:

$$\left(-\frac{\hbar^2 c^2}{2E_z} \frac{\partial^2}{\partial x^2} + \frac{1}{2} K_x x^2 \right) X(x) = (E - E_z) X(x) \equiv E_x X(x). \quad (4.60)$$

This is the standard harmonic oscillator equation [47] with an effective mass E_z/c^2 . The quantization of Eq. (4.60) gives rise to the transverse energy level $E_x = (n_x + 1/2)\hbar\omega_x$, with $n_x = 0, 1, 2, \dots$ being the transverse quantum number. Thus, we have the eigenenergy

$$E(n_x, p_z) = E_z + E_x = \sqrt{m_e^2 c^4 + p_z^2 c^2} + (n_x + 1/2)\hbar\omega_x. \quad (4.61)$$

If we follow the normalization of Section 3.2, the eigenstates can be written in the form

$$\psi_{n_x, p_z}(\mathbf{r}) = \sqrt{\frac{m_e c^2}{E}} |n_x, p_z\rangle, \quad \text{with} \quad (4.62)$$

$$|n_x, p_z\rangle = \sqrt{\frac{1}{L_c}} \sqrt{\frac{C_{n_x}}{x_0}} \exp\left(i \frac{p_z}{\hbar} z\right) \exp\left(\frac{-x^2}{2x_0^2}\right) H_{n_x}\left(\frac{x}{x_0}\right), \quad (4.63)$$

where L_c is the length of the channel, $C_n = (2^n n! \sqrt{\pi})^{-1}$ is a normalization constant, $x_0 = \sqrt{\hbar c^2 / \omega_x E_z}$ is the ground state ($n_x = 0$) oscillation amplitude, and H_n is the n^{th} order Hermite polynomial. Thus, both the eigenenergies E and the eigenstates $\psi(\mathbf{r})$

are controlled by n_x and p_z . Since the transverse energy $E_x = (n_x + 1/2)\hbar\omega_x = \omega_x J_x$, the transverse action J_x is related to the transverse quantum number through

$$J_x = \frac{E_x}{\omega_x} = (n_x + 1/2)\hbar \simeq n_x \hbar \quad \text{for large } n_x. \quad (4.64)$$

The expected change of the transverse quantum number n_x (and action) due to spontaneous radiation can be calculated by

$$\left\langle \frac{dn_x}{dt} \right\rangle = \sum_f \int dW_{fi}(n_{xf} - n_{xi}), \quad (4.65)$$

where the transition rate dW_{fi} from an initial state $|n_{xi}, p_{zi}\rangle$ into a final state $|n_{xf}, p_{zf}\rangle$ with the emission of photons in the range $\mathbf{k}$ to $\mathbf{k} + d\mathbf{k}$ is given by Eq. (3.122). In the case of channeling, we have

$$\mathbf{v} \simeq \frac{-i\hbar\nabla c^2}{\sqrt{E_i E_f}} = \frac{-i\hbar c^2}{\sqrt{E_i E_f}} \left(\frac{\partial}{\partial x}, \quad 0, \quad \frac{\partial}{\partial z} \right) \quad (4.66)$$

for the electron velocity operator, then Eq. (3.122) is

$$dW_{fi} = \frac{d\mathbf{k}}{(2\pi)^3} \frac{e^2 \hbar c^4}{2\epsilon_0 \omega E_i E_f} \left| \langle n_{xf}, p_{zf} | \sum_{\lambda=1}^2 \nabla \cdot \mathbf{e}_\lambda e^{-i\mathbf{k}\cdot\mathbf{r}} | n_{xi}, p_{zi} \rangle \right|^2 2\pi \delta(\omega - \omega_{fi}). \quad (4.67)$$

where $\omega_{fi} = (E_i - E_f)/\hbar$, and $\mathbf{e}_{1,2}$ are the two orthogonal unit polarization vectors ($\mathbf{e}_{1,2} \cdot \mathbf{k} = 0$) as before.

The matrix element $\langle n_{xf}, p_{zf} | (\nabla \cdot \mathbf{e}_\lambda) e^{-i\mathbf{k}\cdot\mathbf{r}} | n_{xi}, p_{zi} \rangle$ can be evaluated by integrating over the coordinate space. In particular, since the eigenstates of the electron have plane-wave form in the z direction, the integration over z simply gives rise to $\delta(p_{zi} - p_{zf} - k \cos \theta)$, where θ is the angle between $\mathbf{k}$ and the longitudinal z direction. This δ function expresses the conservation of the total longitudinal momentum in the electron-photon system due to the translational invariance. Together with the conservation of the total energy (i.e. $\delta(\omega - \omega_{fi})$ in Eq. (4.67)), the change of the transverse quantum number (or action) is completely determined. First, let us rewrite the two conservation laws as

$$\delta E = -\hbar\omega, \quad \delta p_z c = -\hbar\omega \cos \theta. \quad (4.68)$$

From Eq. (4.56), we have

$$\delta E = \delta E_z + J_x \delta \omega_x + \delta J_x \omega_x. \quad (4.69)$$

Both δE_z and $\delta \omega_x$ are related to δp_z by

$$\begin{aligned} \delta E_z &= \beta \delta p_z c + \frac{(\delta p_z)^2 c^2}{2\gamma^2 E_z}, \\ \delta \omega_x &= -\frac{\omega_x}{2} \frac{\beta \delta p_z c}{E_z} + \frac{3\omega_x}{8} \frac{(\beta \delta p_z c)^2}{E_z^2}, \end{aligned} \quad (4.70)$$

where $\beta \simeq p_z c / E_z$. Using the approximation

$$\theta_p^2 = \frac{p_{x,max}^2}{p_z^2} \simeq \frac{2E_x}{E_z} = \frac{2J_x \omega_x}{E_z}, \quad (4.71)$$

and combining Eq. (4.68), Eq. (4.69) and Eq. (4.70), the change of the transverse action is found to be

$$\delta J_x = -\frac{\hbar \omega}{\omega_x} \left(1 - \beta \cos \theta + \frac{\theta_p^2}{4} \right) - \frac{(\hbar \omega)^2}{2E_z} \left(\frac{1}{\gamma^2} + \frac{3\theta_p^2}{8} \right). \quad (4.72)$$

The first term in Eq. (4.72) is always damping because $1 - \beta \cos \theta \simeq \frac{1}{2\gamma^2} + \frac{\theta^2}{2}$ is definite positive. The second term in Eq. (4.72) is quantum correction to the classical damping instead of quantum excitation because the sign is definite negative. Hence we have shown that the transverse action always decreases in spite of random photon direction of emissions, i.e., there is *no opening angle effect* of quantum excitation in a straight focusing channel.

As pointed out in Ref. [25, 27, 26] and illustrated in Fig. 4.1, the above analysis reveals a unique feature of channeling radiation reaction: while the particle recoils against the emitted photon in the longitudinal direction to conserve the longitudinal momentum of the system, the existence of a transverse focusing environment absorbs the recoil in the transverse direction. As a result, the net recoil of the particle is not opposite to the direction of the photon emission, but always has a component pointing towards the focusing axis. Therefore, quantum excitation of the transverse action is absent in such a focusing system, and the radiation damping is always faster in the transverse direction than in the longitudinal direction.

Figure 4.1: The schematic drawing of the radiation reaction in a straight, continuous focusing channel.

Such an excitation-free, asymmetric damping effect leads to a classical point in the transverse phase space for the electron beams. In quantum mechanics, the corresponding state is the transverse ground state ($n_x = 0$) that is stable against further radiation. In the ground state of the harmonic oscillator, the minimum transverse action is given by

$$J_x = \hbar \left(n_x + \frac{1}{2} \right) = \frac{\hbar}{2} \quad \text{for } n_x = 0. \quad (4.73)$$

This $\hbar/2$ is the well-known zero-point fluctuation of the harmonic oscillator and arises from the fact that the Heisenberg uncertainty principle sets a limit on the knowledge of two conjugate variables by

$$\delta x \delta p_x \geq \frac{\hbar}{2}. \quad (4.74)$$

Relating this minimum action to a normalized emittance by averaging over the beam distribution, we obtain the minimum normalized emittance

$$\varepsilon_{\min}^n = \frac{\hbar/2}{m_e c} = \frac{\lambda_c}{2}, \quad (4.75)$$

where $\lambda_c = 3.86 \times 10^{-13}$ m is the Compton wavelength of the electron. Eq. (4.75) sets a quantum mechanical limit on the normalized emittance of electron or positron beams. A beam of N electrons can all line up in the same transverse ground state at different points in the longitudinal phase space or different spin states. Although it is far from

being reached with the present accelerator technology, the above analysis has shown that in a straight, continuous focusing channel, the transverse normalized emittance can in principle be damped to one half of the Compton wavelength, the fundamental emittance limited only by the wave nature of the electron. We note the similarity that the phase space of a photon beam is limited to one half of the reduced light wavelength due to diffraction effects [78]. However, the limit is routinely obtainable with the diffraction-limited photon beams.

4.2.2 Asymmetric Damping

Although we can calculate the damping of the transverse action with the use of the transition rate Eq. (4.67) [25, 27], it is much simpler to use Eq. (4.6) and replace δI with the first term of δJ_x in Eq. (4.72) because the radiation damping is a classical phenomenon. Furthermore, since $\delta J_x/(\hbar\omega) \simeq -(1 - \beta \cos \theta + \theta_p^2/4)/\omega_x$ is independent of the photon frequency, we can integrate Eq. (4.6) over $d\omega$ to obtain

$$\left\langle \frac{dJ_x}{dt} \right\rangle = - \int_0^{T_0} \frac{dt}{2\pi} \int d\Omega \left(1 - \beta \cos \theta + \frac{\theta_p^2}{4} \right) \frac{dP_\gamma}{d\Omega}, \quad (4.76)$$

where the oscillation period is $T_0 = 2\pi/\omega_x$ and the angular power spectrum $dP_\gamma/d\Omega$ was given by Eq (3.24).

Following Section 3.1.2, we choose the direction of the instantaneous momentum $\mathbf{p}$ as the z' axis, $\mathbf{p}$ and $\dot{\mathbf{p}}$ plane as the $x'z'$ plane (Fig. 4.2). From Eq. (3.88), we have that $\dot{\mathbf{p}} = -K_x \mathbf{x} = \dot{p}_\perp \mathbf{x}' + \dot{p}_\parallel \mathbf{z}' \propto \sin \omega_x t$, and that the longitudinal direction z oscillates with an angle $\theta_p \cos \omega_x t$ from the z' axis. Then in the $x'y'z'$ coordinate system, we have

$$\begin{aligned} \mathbf{n} &= (\sin \theta' \cos \phi', \sin \theta' \sin \phi', \cos \theta') \\ \mathbf{z} &= (\sin(\theta_p \cos \omega_x t), 0, \cos(\theta_p \sin \omega_x t)). \end{aligned} \quad (4.77)$$

Thus, we obtain

$$\cos \theta = \mathbf{n} \cdot \mathbf{z} = \sin \theta' \sin(\theta_p \cos \omega_x t) \cos \phi' + \cos \theta' \cos(\theta_p \sin \omega_x t). \quad (4.78)$$

Figure 4.2: The primed and the unprimed coordinate systems used for channeling motion

Equation (3.26) then takes the form

$$\begin{aligned} \frac{dP_\gamma(t)}{d\Omega} = \frac{r_e}{4\pi\gamma^2 m_e c} \left\{ \dot{p}_\parallel^2 \left[\frac{(1-\beta^2)^2}{(1-\beta\cos\theta')^3} - \frac{1}{\gamma^2} \frac{(\cos\theta' - \beta)^2}{(1-\beta\cos\theta')^5} \right] \right. \\ \left. + \dot{p}_\perp^2 \left[\frac{1}{(1-\beta\cos\theta')^3} - \frac{1}{\gamma^2} \frac{\sin^2\theta' \cos^2\phi'}{(1-\beta\cos\theta')^5} \right] \right. \\ \left. - \dot{p}_\parallel \dot{p}_\perp \frac{2(\cos\theta' - \beta) \sin\theta' \cos\phi'}{\gamma^2 (1-\beta\cos\theta')^5} \right\}. \end{aligned} \quad (4.79)$$

Integration over $d\Omega = \int d\phi' \int d\theta' \sin\theta'$ yields the total radiated power that is given by Eq (3.27). In the case of channeling, we have $(\dot{\mathbf{p}})^2 = (K_x x)^2 = 2K_x E_x \sin^2 \omega_x t$ and $\dot{E}^2/c^2 = \beta^2 \dot{p}_\parallel^2 \sim \theta_p^2 (\dot{\mathbf{p}})^2$. Averaging over one oscillation period and keeping only the leading order term in θ_p^2 , we find

$$\left\langle \frac{dE}{dt} \right\rangle \simeq -\frac{4r_e}{3mc} \gamma^2 K_x E_x \langle \sin^2 \omega_x t \rangle \simeq -\frac{2}{3} \frac{r_e K_x}{m_e c} \gamma^2 J_x \omega_x, \quad (4.80)$$

By putting Eq. (4.78) and Eq. (4.79) into Eq. (4.76) and carrying out the angular integration and time averaging, it is now straightforward to show that the damping

rate of transverse action is

$$\begin{aligned}\left\langle \frac{dJ_x}{dt} \right\rangle &= \frac{1}{\omega_x} \left[\left(\frac{1}{\gamma^2} + \frac{\theta_p^2}{4} \right) \left\langle \frac{dE}{dt} \right\rangle + \frac{\theta_p^2}{2} \left\langle \frac{dE}{dt} \cos^2 \omega_x t \right\rangle \right] \\ &= \frac{1}{\omega_x} \left[\left(\frac{1}{\gamma_z^2} + \frac{3\theta_p^2}{8} \right) \right] \left\langle \frac{dE}{dt} \right\rangle\end{aligned}\quad (4.81)$$

$$= -\frac{2r_e K_x}{3m_e c} \left(J_x + \frac{3}{4} \sqrt{\frac{K_x}{m_e^3 c^4}} \gamma^{1/2} J_x^2 \right), \quad (4.82)$$

where we have used the relation

$$\left\langle \frac{dE}{dt} \cos^2 \omega_x t \right\rangle = 2 \left\langle \frac{dE}{dt} \right\rangle \langle \cos^2 \omega_x t \sin^2 \omega_x t \rangle = \frac{1}{4} \left\langle \frac{dE}{dt} \right\rangle. \quad (4.83)$$

It is clear from Eq. (4.81) that the damping of the transverse action consists of two competing terms that differ by a factor of $\gamma^2 \theta_p^2$. In the weak undulator regime where the pitch angle θ_p is much smaller than the radiation opening angle $1/\gamma$, the first term in Eq. (4.81) dominates and gives

$$\left\langle \frac{dJ_x}{dt} \right\rangle \simeq \frac{1}{\omega_x} \frac{1}{\gamma^2} \left\langle \frac{dE}{dt} \right\rangle = -\frac{2r_e K_x}{3m_e c} J_x \equiv -\Gamma_c J_x, \quad (4.84)$$

which shows that the transverse action damps exponentially with an energy independent damping constant $\Gamma_c = (2r_e K_x/3m_e c)$ [25, 27, 26]. We also notice that the relative damping rate of the transverse action is much faster than that of the energy in this regime since

$$\Gamma_c = \left| \frac{1}{J_x} \left\langle \frac{dJ_x}{dt} \right\rangle \right| \gg \left| \frac{1}{E} \left\langle \frac{dE}{dt} \right\rangle \right| \simeq \frac{\Gamma_c}{2} \gamma^2 \theta_p^2. \quad (4.85)$$

In the opposite regime where $\theta_p \gg 1/\gamma$, the second term in Eq. (4.81) dominates and gives

$$\left\langle \frac{dJ_x}{dt} \right\rangle \simeq \frac{1}{\omega_x} \frac{3\theta_p^2}{8} \left\langle \frac{dE}{dt} \right\rangle. \quad (4.86)$$

By applying Eq. (4.71), we obtain

$$\frac{1}{J_x} \left\langle \frac{dJ_x}{dt} \right\rangle \simeq \frac{3}{4} \frac{1}{E} \left\langle \frac{dE}{dt} \right\rangle, \quad (4.87)$$

which shows that the relative damping rate of the transverse action is comparable to the relative energy decay rate, similar to the radiation damping in a storage ring.

Therefore, we have obtained general results on the radiation reaction for a channeled particle with arbitrary oscillation amplitude $\gamma\theta_p$. We can understand these results by recalling the discussion on the radiation formation length in Section 3.1.5. For very large $\gamma\theta_p$ ($\gg 1$), the radiation formation length l_r is much less than the oscillation wavelength λ_x , and the photon emission takes place in a small fraction of one oscillation period. In this case, the focusing environment is ineffective in suppressing the transverse oscillations, so that both the transverse and the longitudinal dimensions of the particle damp with comparable rates because the electron *almost* recoils directly against the photon. As $\gamma\theta_p$ becomes much smaller than 1, the radiation is formed over the whole oscillation period, and the focusing environment takes away a fixed proportion of the transverse action. Thus the transverse action damps exponentially and the radiation reaction is predominantly transverse.

It is instructive to look at the time evolution of the transverse action. The simple analytical results (i.e. Eq. (4.80) and Eq. (4.82)) of channeling radiation damping, derived by quasiclassical approach, can be regarded as two coupled differential equations between J_x and E . Defining a constant $C_c = \sqrt{K_x/m_e^4 c^6}$ and omitting the bracket on the left hand sides of Eq. (4.80) and Eq. (4.82), we obtain

$$\begin{aligned}\frac{dE}{dt} &= -\Gamma_c C_c E^{3/2} J_x, \\ \frac{dJ_x}{dt} &= -\Gamma_c J_x - \frac{3}{4}\Gamma_c C_c E^{1/2} J_x^2.\end{aligned}\tag{4.88}$$

Suppose that the particle enters the channel with the transverse action J_{x0} , the energy E_0 and thus the parameter $\gamma_0\theta_{p0} = \sqrt{2C_c J_{x0}/E_0^{1/2}}$, then the general solution to these coupled equations is

$$\begin{aligned}J_x(t) &= J_{x0} \left\{ 1 + \frac{5}{8}\gamma_0^2\theta_{p0}^2 [1 - \exp(-\Gamma_c t)] \right\}^{-3/5} \exp(-\Gamma_c t), \\ E(t) &= E_0 \left\{ 1 + \frac{5}{8}\gamma_0^2\theta_{p0}^2 [1 - \exp(-\Gamma_c t)] \right\}^{-4/5}.\end{aligned}\tag{4.89}$$

Therefore, the transverse action always has an exponential damping factor that dominates in the asymptote, while the energy eventually reaches a constant value: a factor

of $(1 + \frac{5}{8}\gamma_0^2\theta_{p0}^2)^{4/5}$ reduction from the initial energy.

To illustrate the time evolution of the transverse action and energy, we plot the normalized transverse action J_x/J_{x0} and the normalized energy E/E_0 versus the scaled time $\Gamma_c t$ in Fig. 4.3 for three different initial conditions of $\gamma_0\theta_{p0}$. For large $\gamma_0\theta_{p0}$, both the transverse action and the energy initially damp with power laws, i.e.,

$$\begin{aligned} \text{when } \Gamma_c t \ll 1, J_x(t) &\simeq J_{x0} \left(1 + \frac{5}{8}\gamma_{z0}^2\theta_{p0}^2\Gamma_c t\right)^{-3/5}, \\ E(t) &\simeq E_0 \left(1 + \frac{5}{8}\gamma_{z0}^2\theta_{p0}^2\Gamma_c t\right)^{-4/5}. \end{aligned} \quad (4.90)$$

However, the exponential damping factor in the transverse action becomes more important for longer time and takes over when the particle damps to the weak undulator regime, i.e.,

$$\begin{aligned} \text{when } \Gamma_c t \gg 1, J_x(t) &\simeq J_{x0} \left(1 + \frac{5}{8}\gamma_0^2\theta_{p0}^2\right)^{-3/5} \exp(-\Gamma_c t), \\ E(t) &\simeq E_0 \left(1 + \frac{5}{8}\gamma_0^2\theta_{p0}^2\right)^{-4/5}. \end{aligned} \quad (4.91)$$

For small $\gamma_0\theta_{p0}$, the exponential damping begins immediately, i.e.,

$$\begin{aligned} J_x(t) &\simeq J_{x0} \exp(-\Gamma_c t), \\ E(t) &\simeq E_0 \left[1 - \frac{1}{2}\gamma_0^2\theta_{p0}^2(1 - \exp(-\Gamma_c t))\right]. \end{aligned} \quad (4.92)$$

Note that electrons with the same initial energy but different initial pitch angles will all end up in the transverse ground state with an energy spread, caused by amplitude dependence of the radiated power. In the case of small $\gamma_0\theta_{p0}$, we can use Eq. (4.92) to write down the relative energy spread

$$\delta = \left\langle \frac{E_i - E_f}{E_i} \right\rangle = \frac{1}{2}\gamma_0^2\langle\theta_{p0}^2\rangle = \gamma_0 \frac{\langle J_{x0} \rangle \omega_x}{m_e c^2} = \gamma_0 \frac{\varepsilon_0^n}{\beta_x} \ll 1, \quad (4.93)$$

where ε_0^n is the initial normalized transverse emittance and $\beta_x = c/\omega_x$ is the reduced oscillation wavelength or the average betatron function.

Figure 4.3: Evolution of the normalized transverse action J_x/J_{x0} and the normalized energy E/E_0 with the scaled time $\Gamma_c t$ for (a) $\gamma_0^2 \theta_{p0}^2 = 100$, (b) $\gamma_0^2 \theta_{p0}^2 = 1$ and (c) $\gamma_0^2 \theta_{p0}^2 = 0.1$.

4.2.3 Comparison with Undulators

In Section 3.1.5, we have shown that the electron motion and the radiation spectrum are very similar in a focusing channel and in an undulator. This does not necessarily imply that the radiation reaction in these two systems are also similar. In fact, the radiation reaction is determined by the nature of the forces and will be completely different for the focusing system and the bending system (the undulator).

This point can be best made in the longitudinal comoving frames of both systems. Consider first the case of channeling in the small amplitude limit when $\gamma\theta_p \ll 1$, the longitudinal translational invariance guarantees that the electron sees a one-dimensional (transverse) harmonic potential with the focusing strength $K_x^* = \gamma K_x$ in such a frame (denoted by a star). The electron gives away transverse energy $E_x^* = \langle K_x^* x^2 \rangle$ through dipole radiation [35] by dropping the transverse levels until it reaches the ground state. The damping rate is given by

$$\Gamma_c^* = \frac{1}{E_x^*} \frac{dE_x^*}{dt^*} = \frac{1}{\langle K_x^* x^2 \rangle} \frac{2}{3} \frac{r_e}{m_e c} \langle (K_x^* x)^2 \rangle = \frac{2}{3} \frac{r_e}{m_e c} K_x^*. \quad (4.94)$$

When transforming back to the laboratory frame, we get back the energy-independent transverse damping rate Γ_c of Eq (4.84). Note that although this over-simplified picture did not take into account the longitudinal recoil after the radiation is emitted, and is only valid in the small $\gamma\theta_p$ limit, it does have the advantage when making comparison with the undulator. In the electron's comoving frame, the magnetic field of the undulator is equivalent to a plane wave of virtual photons [23, 35]. Interaction of the electron and these virtual photons is described by Compton scattering [23] or Thomson scattering [35]. Quantum excitation to the transverse emittance exists because the electron recoils directly against the scattered photons. We will leave the calculation of quantum excitation rate to Chapter 5 in which real photons (from the laser field) instead of virtual photons interact with the electron. Therefore, even in the weak undulator limit where the radiation formation length is comparable to the undulator wavelength, the lack of transverse focusing is essential for the existence of quantum excitation in the undulator. In other words, the excitation-free damping is purely due to the effect of focusing.

4.2.4 Generalizations and Practical Considerations

Sections 4.2.1 and 4.2.2 show that no quantum excitation is induced in a straight, continuous focusing system, and that the radiation damping rate of the transverse action is independent of the electron energy in the small oscillation limit. In this section, we relax some of the previous assumptions and generalize the results to a non-harmonic transverse potential in two transverse degrees of freedom.

We start by considering the other transverse dimension y . If the y direction is free of any force, the particle radiating a photon with a momentum component in the y direction must recoil by the same magnitude to conserve total momentum in this direction. Thus, quantum excitation is present in a force-free dimension. However, if a continuous focusing force also exists in the y direction, and if both transverse oscillations satisfy the conditions $\gamma\theta_p^x \ll 1$ and $\gamma\theta_p^y \ll 1$, then as we will see in Section 4.4.2 that radiation effects in the x and the y directions are completely decoupled. Photons are emitted by changing either n_x or n_y by one, and all the previous results apply equally well to both transverse dimensions. In the case where the oscillation amplitude is large in the x or in the y direction, there is some coupling between the two transverse degrees of freedom. But if we define the total transverse energy

$$E_{\perp} = \frac{p_x^2 c^2}{2E_z} + \frac{K_x x^2}{2} + \frac{p_y^2 c^2}{2E_z} + \frac{K_y y^2}{2}, \quad (4.95)$$

from the conservation of both the total energy and the longitudinal momentum in the electron-photon system, i.e., Eq. (4.68), it follows that

$$\delta E_{\perp} = -\hbar\omega(1 - \beta \cos \theta) < 0. \quad (4.96)$$

Hence $E_{\perp}$ always decreases after a random photon emission. Combining this with the existence of a focusing axis in the continuous focusing system, we conclude that the electron will damp to a mutual transverse ground state ($n_x = 0$ and $n_y = 0$) that is stable against further radiation. In fact, we can generalize the above results to a non-harmonic potential. Suppose we denote the transverse coordinates with $\mathbf{r}_{\perp} = (x, y)$ and the transverse momenta with $\mathbf{p}_{\perp} = (p_x, p_y)$, then the transverse energy can be

defined as

$$E_{\perp} = \frac{\mathbf{p}_{\perp}^2 c^2}{2E_z} + U(\mathbf{r}_{\perp}), \quad (4.97)$$

where $U(\mathbf{r}_{\perp})$ is an arbitrary potential well that does not depend on the longitudinal coordinate z . The change of the transverse energy will follow Eq. (4.96) after the same kinematic argument. We can also quantize the transverse motion and define the transverse quantum levels (not equally spaced for non-harmonic potential). Thus, we reach the same conclusion that the electron damps to the ground state of such a potential by the virtue of radiation reaction.

Nevertheless, such an absolute damping (without any quantum excitation) is normally a negligible effect for conventional focusing devices used in accelerators. For instance, suppose the quadrupole field gradient is about $g = 100$ T/m, corresponding to a focusing strength $K_x \simeq 0.3g[\text{Tesla/m}] \simeq 30[\text{GeV/m}^2]$. The damping constant $\Gamma_c = (2r_e K_x / 3m_e c) \sim (30\text{sec})^{-1}$, so that the damping time is extremely slow. On the other hand, the focusing strength for a typical crystal channel is $K_x \sim 10^{11}\text{GeV/m}^2$ [44], so $\Gamma_c \sim (10\text{nsec})^{-1}$, and the damping distance is on the order of meters. The radiation damping could be a noticeable effect. In such cases, it has been shown [45, 4] that multiple Coulomb scattering is the primary excitation mechanism competing against the radiation damping. The transverse emittance growth due to the multiple scattering can be expressed in the form [45, 4]:

$$\left\langle \frac{d\varepsilon_x^n}{dt} \right\rangle_{\text{ms}} = c \frac{\gamma\beta_x}{2} \frac{d}{dz} \langle \theta_p^2 \rangle, \quad (4.98)$$

where

$$\frac{d}{dz} \langle \theta_p^2 \rangle = \frac{1}{\gamma^2 L_{\text{ms}}}, \quad (4.99)$$

is the mean square angle of multiple scattering by valence electrons that is characterized by a γ^2 dependence and a material dependent parameter L_{ms} . Since $\beta_x \simeq \sqrt{\gamma m_e / K_x}$, then we have the scaling law

$$\left\langle \frac{d\varepsilon_x^n}{dt} \right\rangle_{\text{ms}} \sim \frac{\gamma\sqrt{\gamma}}{\gamma^2} = \frac{1}{\gamma^{1/2}}. \quad (4.100)$$

However, from Eq. (4.84), the radiation damping rate of the transverse emittance is energy-independent in the small oscillation limit. Without any acceleration, the fact that the energy of the electrons decrease due to radiation loss guarantees that the multiple scattering dominates over the radiation damping after a short distance (the so called dechanneling length [44]).

Such a picture will change if the electrons are under external acceleration. Since both the action and the stationary states are adiabatic invariants, the results of Section 4.2.1 and 4.2.2 are not affected by adiabatic acceleration along the longitudinal direction. The condition for adiabatic acceleration is given by

$$\frac{dE_{accel}}{dt} \ll \omega_x E \simeq \sqrt{K_x E} \quad . \quad (4.101)$$

Using the previous examples, we get $\omega_x E \sim 2\text{GeV/m}$ for a conventional focusing device and 10^5GeV/m for a crystal channel when the energy of the particle is only 100MeV. Obviously, the above inequality is guaranteed by any foreseeable acceleration mechanism. As discussed in Ref. [16] for crystal channeling accelerators, radiation damping will eventually dominate over multiple scattering as the energy of the electrons increase. We conclude that the particle, once damped to its transverse ground state in a continuous focusing channel, can be accelerated adiabatically along the channel without any further radiation loss. Therefore, the theoretical minimum transverse emittance can be retained at a much higher accelerated electron energy, and the relative longitudinal energy spread can be also reduced through acceleration.

4.3 Periodic Focusing Channels

So far we have considered a focusing system where the focusing strength is independent of the longitudinal z parameter. However, a more realistic model of a focusing channel is an alternating-gradient focusing system where both focusing quadrupoles and defocusing quadrupoles are employed to focus electrons in both transverse directions. Strictly speaking, electrons moving along crystal channels are also subject to periodic forces determined by the lattice structure. The continuum Lindhard potential [49] is only a valid approximation when the binary interactions with individual

nuclei are swamped by the interaction with the collection of atoms forming the atomic string.

In this section, we examine the process of radiation damping and quantum excitation in a straight, periodic focusing channels. We then apply the results to the most simple periodic lattice–FODO lattice, composed of a focusing (F) and a defocusing (D) quadrupole with a drift space (O) in between. From Appendix A, in the absence of bending, we can take the limit $\rho \rightarrow \infty$ and $s \rightarrow z$. Treating z as the independent variable and $-p_z$ as the new Hamiltonian, we have from Eq A.10

$$-p_z = -p + \frac{p_x^2}{2p} + pk_x \frac{x^2}{2}, \quad (4.102)$$

where $p = \sqrt{H^2 - m_e^2 c^4} = \gamma \beta m_e c$ is the kinetic momentum, and k_x is the periodic focusing function with periodicity L_0 . Making a canonical transformation with the generating function

$$F_2(x, \tilde{p}_x, z) = \frac{p}{2\beta_x} \left(\frac{\beta'_x}{2} - \tan \varphi \right) x^2 + \sqrt{\frac{\bar{\beta}}{\beta_x}} \frac{x \tilde{p}_x}{\cos \varphi} - \frac{\bar{\beta}}{2p} (\tilde{p}_x)^2 \tan \varphi. \quad (4.103)$$

Here the prime means derivative with respect to z . The betatron function β_x satisfies Eq. (A.23) and

$$\frac{1}{\bar{\beta}} = \frac{1}{L_0} \int_0^{L_0} \frac{ds}{\beta_x}, \quad \varphi' = \frac{1}{\beta_x} - \frac{1}{\bar{\beta}}. \quad (4.104)$$

The new “Hamiltonian” is transformed to

$$-\tilde{p}_z = -p_z + \frac{\partial F_2}{\partial z} = -p + p \frac{\tilde{x}^2}{2\bar{\beta}^2} + \frac{\tilde{p}_x^2}{2p}. \quad (4.105)$$

The old coordinates and the new coordinates are related through

$$\begin{pmatrix} x \\ p_x \end{pmatrix} = \begin{pmatrix} A & B \\ C & D \end{pmatrix} \begin{pmatrix} \tilde{x} \\ \tilde{p}_x \end{pmatrix}, \quad (4.106)$$

where

$$A(z) = \sqrt{\frac{\beta_x}{\bar{\beta}}} \cos \varphi, \quad B(z) = \frac{1}{p} \sqrt{\beta_x \bar{\beta}} \sin \varphi, \quad (4.107)$$

$$C(z) = \frac{p}{\sqrt{\beta_x \bar{\beta}}} \left(\frac{\beta'_x}{2} \cos \varphi - \sin \varphi \right), \quad D(z) = \sqrt{\frac{\beta_x}{\bar{\beta}}} \left(\cos \varphi + \frac{\beta'_x}{2} \sin \varphi \right) \quad (4.108)$$

Changing the independent variable from z back to t in Eq. (4.105), we have the real Hamiltonian

$$H \simeq \sqrt{\tilde{p}_z^2 c^2 + m^2 c^4} + \beta \frac{\tilde{p}_x^2 c}{2p} + pc \frac{\tilde{x}^2}{2\beta^2}. \quad (4.109)$$

Thus, the equation of motion in the transformed phase space $(\tilde{x}, \tilde{p}_x, z, \tilde{p}_z)$ is completely the same as in the continuous potential case of Section 4.2.1. We can also quantize the system by using the Klein-Gordon equation and obtain the transverse quantum level n_x that is ultimately connected with the transverse normalized emittance. To calculate the expected rate of change for the traverse levels n_x , we combine Eq. (4.65) and (3.122) to obtain

$$\begin{aligned} \left\langle \frac{dn_x}{dt} \right\rangle &= \sum_f (n_{xf} - n_{xi}) \int dW_{fi} \\ &= \sum_{n_{xf}} \sum_{\tilde{p}_{xf}} \delta n_x \int \frac{d\mathbf{k}}{(2\pi)^3} \frac{e^2}{2\epsilon_0 \hbar \omega} \left| \langle f | \sum_{\lambda=1}^2 \mathbf{e}_\lambda \cdot \mathbf{v} e^{-i\mathbf{k} \cdot \mathbf{r}} | i \rangle \right|^2 2\pi \delta(\omega - \omega_{fi}). \end{aligned} \quad (4.110)$$

Suppose (θ, ϕ) are the emission angles defined in Section 3.1.5, the two polarization vectors are then given by

$$\mathbf{e}_1 = (\cos \theta \cos \phi, \cos \theta \sin \phi, -\sin \theta), \quad \mathbf{e}_2 = (\sin \phi, -\cos \phi, 0). \quad (4.111)$$

In order to evaluate the matrix element of Eq. (4.110), we must transform all the operators to the new phase space. For example, the velocity operator is given by

$$\begin{aligned} \mathbf{v} &\simeq \frac{(\mathbf{p} - e\mathbf{A})c^2}{E} = \frac{c^2}{E} (p_x, 0, p_z - eA_z), \\ &= \frac{c^2}{E} \left(C\tilde{x} + D\tilde{p}_x, \quad 0, \quad \tilde{p}_z + \frac{\partial F_2}{\partial z} + pk_x x^2 \right). \end{aligned} \quad (4.112)$$

Unlike in Section 4.2.1, although $\tilde{p}_z$ is an invariant, the integration over z does not yield momentum conservation in z direction because of the z dependence in the velocity operator and in the radiation field operator which has a factor

$$\begin{aligned} e^{i\mathbf{k} \cdot \mathbf{r}} &= e^{ik(x \sin \theta \cos \phi + z \cos \theta)} \\ &= e^{ik[(A\tilde{x} + B\tilde{p}_x) \sin \theta \cos \phi + z \cos \theta]} \\ &= e^{ikz \cos \theta} [1 + ik(A\tilde{x} + B\tilde{p}_x) \sin \theta \cos \phi + \mathcal{O}(x^2)]. \end{aligned} \quad (4.113)$$

For simplicity, we assume the transverse oscillation amplitude is small so that we can use the dipole approximation [25, 27] to neglect terms of order x^2 , xp_x and p_x^2 in Eqs. (4.112) and (4.113). First, we write Eq. (4.110) as

$$\left\langle \frac{dn_x}{dt} \right\rangle = \sum_{n_{xf}} \sum_{\tilde{p}_{xf}} \delta n_x \int d\Omega \int d\omega \frac{\omega}{(2\pi)^2} \frac{e^2 c}{2\epsilon_0 E_i E_f \hbar} \delta(\omega - \omega_{fi}) (|M_1|^2 + |M_2|^2), \quad (4.114)$$

where

$$\begin{aligned} M_1 &= \int \frac{dz}{L_c} \exp \left[i \left(\frac{\tilde{p}_{zi} - \tilde{p}_{zf}}{\hbar} - \frac{\omega}{c} \cos \theta \right) z \right] \langle n_{xf} | O_1(z) | n_{xi} \rangle, \\ M_2 &= \int \frac{dz}{L_c} \exp \left[i \left(\frac{\tilde{p}_{zi} - \tilde{p}_{zf}}{\hbar} - \frac{\omega}{c} \cos \theta \right) z \right] \langle n_{xf} | O_2(z) | n_{xi} \rangle, \end{aligned} \quad (4.115)$$

and

$$\begin{aligned} O_1(z) &= [C(z)\tilde{x} + D(z)\tilde{p}_x] \cos \theta \cos \phi - \tilde{p}_z \left(-i\frac{\omega}{c} \right) [A(z)\tilde{x} + B(z)\tilde{p}_x] \sin^2 \theta \cos \phi, \\ O_2(z) &= [C(z)\tilde{x} + D(z)]\tilde{p}_x \sin \phi. \end{aligned} \quad (4.116)$$

Secondly, we express $\tilde{x}$ and $\tilde{p}_x$ in terms of the raising and lowering operators the harmonic oscillator [47]:

$$\tilde{x} = \sqrt{\frac{\beta \hbar}{2p}} (a_x + a_x^\dagger), \quad \tilde{p}_x = -i\sqrt{\frac{p\hbar}{2\beta}} (a_x - a_x^\dagger), \quad (4.117)$$

with

$$a_x |n_{xi}\rangle = \sqrt{n_{xi}} |n_{xi} - 1\rangle, \quad a_x^\dagger |n_{xi}\rangle = \sqrt{n_{xi} + 1} |n_{xi} + 1\rangle. \quad (4.118)$$

Insert Eq. (4.117) and Eq. (4.108) into Eq. (4.116), we have

$$\begin{aligned} O_1 &= \sqrt{\frac{p\hbar}{2}} \cos \theta \cos \phi \left[\left(\frac{\beta'_x}{2\sqrt{\beta_x}} - \frac{i}{\sqrt{\beta_x}} \right) e^{-i\varphi} a_x + \left(\frac{\beta'_x}{2\sqrt{\beta_x}} + \frac{i}{\sqrt{\beta_x}} \right) e^{+i\varphi} a_x^\dagger \right] \\ &\quad + i \left(\frac{\omega}{c} \right) \sqrt{\frac{p\hbar}{2}} \sin^2 \theta \cos \phi \left[\sqrt{\beta_x} e^{-i\varphi} a_x + \sqrt{\beta_x} e^{+i\varphi} a_x^\dagger \right] \\ O_2 &= \sqrt{\frac{p\hbar}{2}} \sin \phi \left[\left(\frac{\beta'_x}{2\sqrt{\beta_x}} - \frac{i}{\sqrt{\beta_x}} \right) e^{-i\varphi} a_x + \left(\frac{\beta'_x}{2\sqrt{\beta_x}} + \frac{i}{\sqrt{\beta_x}} \right) e^{+i\varphi} a_x^\dagger \right] \end{aligned} \quad (4.119)$$

We can Fourier expand all the z dependence of the operator coefficients, keeping in mind that we have by design

$$\beta_x(z) = \beta_x(z + L_0), \quad \beta_x(-z) = \beta_x(z). \quad (4.120)$$

Suppose we define

$$\begin{aligned} \left(\frac{\beta'_x}{2\sqrt{\beta_x}} \pm \frac{i}{\sqrt{\beta_x}} \right) e^{\pm i\varphi} &= \sum_{m=-\infty}^{+\infty} F_m^{\pm} \exp \left(-imz \frac{2\pi}{L_0} \right), \\ \sqrt{\beta_x} e^{\pm i\varphi} &= \sum_{m=-\infty}^{+\infty} G_m^{\pm} \exp \left(-imz \frac{2\pi}{L_0} \right), \end{aligned} \quad (4.121)$$

where the Fourier coefficients are

$$F_m^{\pm} = \int_{-L_0/2}^{L_0/2} \frac{dz}{L_0} \left(\frac{\beta'_x}{2\sqrt{\beta_x}} \pm \frac{i}{\sqrt{\beta_x}} \right) e^{\pm i\varphi} \exp \left(+imz \frac{2\pi}{L_0} \right), \quad (4.122)$$

$$G_m^{\pm} = \int_{-L_0/2}^{L_0/2} \frac{dz}{L_0} \sqrt{\beta_x} e^{\pm i\varphi} \exp \left(+imz \frac{2\pi}{L_0} \right). \quad (4.123)$$

By using the relation

$$\frac{d}{dz}(\sqrt{\beta_x} e^{\pm i\varphi}) = \left[\frac{\beta'_x}{2\sqrt{\beta_x}} \pm \sqrt{\beta_x} i \left(\frac{1}{\beta_x} - \frac{1}{\beta} \right) \right] e^{\pm i\varphi} \quad (4.124)$$

and integration by parts for Eq. (4.122), we obtain

$$F_m^{\pm} = -i \left(\frac{2\pi m}{L_0} \mp \frac{1}{\beta} \right) \int_{-L_0/2}^{L_0/2} \frac{dz}{L_0} \sqrt{\beta_x} e^{\pm i\varphi} \exp \left(+imz \frac{2\pi}{L_0} \right) = -i \left(\frac{2\pi m}{L_0} \mp \frac{1}{\beta} \right) G_m^{\pm}, \quad (4.125)$$

from which we deduce that

$$F_{-m}^{-} = -F_m^{+}. \quad (4.126)$$

Substituting Eq. (4.121) into Eq. (4.115), we have

$$\begin{aligned} M_1 &= \sqrt{\frac{p\hbar}{2}} \sum_{m=-\infty}^{+\infty} \int \frac{dz}{L_c} \exp \left[i \left(\frac{\delta \tilde{p}_z}{\hbar} + \frac{\omega}{c} \cos \theta + \frac{2\pi m}{L_0} \right) z \right] \times \\ &\quad \left[\cos \theta \cos \phi \langle n_{xf} | (F_m^{-} a_x + F_m^{+} a_x^{\dagger}) | n_{xi} \rangle + i \frac{\omega}{c} \sin^2 \theta \cos \phi \langle n_{xf} | (G_m^{-} a_x + G_m^{+} a_x^{\dagger}) | n_{xi} \rangle \right], \\ M_2 &= \sqrt{\frac{p\hbar}{2}} \sum_{m=-\infty}^{+\infty} \int \frac{dz}{L_c} \exp \left[i \left(\frac{\delta \tilde{p}_z}{\hbar} + \frac{\omega}{c} \cos \theta + \frac{2\pi m}{L_0} \right) z \right] \langle n_{xf} | (F_m^{-} a_x + F_m^{+} a_x^{\dagger}) | n_{xi} \rangle. \end{aligned} \quad (4.127)$$

By now we have completely separated the longitudinal integration from the transverse one. Integrating over z yields a Dirac δ function that expresses the momentum conservation between the electron, the photon and the lattice mode (phonon) in the z direction:

$$\delta \tilde{p}_z c = -\hbar \omega \cos \theta - \hbar c \frac{2\pi m}{L_0}. \quad (4.128)$$

Together with the energy conservation between the electron and the photon ($\delta E = -\hbar \omega$), we can determine the change of the transverse quantum level n_x . When the oscillation amplitude is small, $\omega_x \simeq (\beta c)/\bar{\beta}$ remains constant, then we have

$$\delta n_x \hbar \omega_x = \delta E - \beta \delta \tilde{p}_z c \simeq -\hbar \omega (1 - \beta \cos \theta) + \hbar \beta c \frac{2\pi m}{L_0}. \quad (4.129)$$

In contrast to a continuous focusing channel, we cannot uniquely determine the sign of δn_x by Eq. (4.129). Quantum excitation to the transverse quantum level can exist in an alternating-gradient focusing system because the electron can absorb lattice modes while emitting a photon. Eq. (4.129) can be treated as a dispersion relation that determines the photon frequency:

$$\frac{\omega}{c} = \frac{\beta}{(1 - \beta \cos \theta)} \left(\frac{2\pi m}{L_0} - \frac{\delta n_x}{\bar{\beta}} \right), \quad (4.130)$$

If we restrict ourselves to the situation $\bar{\beta} > L_0/(2\pi)$ (corresponding to the phase advance per period is small compared with 2π), and since the dipole selection rule is $n_{xf} = n_{xi} \pm 1$, then we have these three cases:

$$\begin{aligned} m=0, \quad \delta n_x &= -1, & \text{damping;} \\ m>0, \quad \delta n_x &= -1, & \text{damping;} \\ m>0, \quad \delta n_x &= +1, & \text{anti-damping and excitation.} \end{aligned}$$

By using Eq. (4.125), the orthogonality of the delta functions with different mode

number m , and the dispersion relation Eq. (4.130), we obtain

$$\begin{aligned} \int \omega d\omega \sum_{\tilde{p}_{xf}} \delta(\omega - \omega_{fi}) |M_1|^2 &= \frac{pc\hbar}{2} \frac{(\cos\theta - \beta)^2}{(1 - \beta \cos\theta)^4} \cos^2\phi \left[\frac{1}{\beta} |F_0^-|^2 n_{xi} \delta_{\delta n_x, -1} \right. \\ &\quad \left. + \sum_{m=1}^{+\infty} \left(\frac{2\pi m}{L_0} - \frac{\delta n_x}{\beta} \right) (|F_m^-|^2 n_{xi} \delta_{\delta n_x, -1} + |F_m^+|^2 (n_{xi} + 1) \delta_{\delta n_x, +1}) \right], \\ \int \omega d\omega \sum_{\tilde{p}_{xf}} \delta(\omega - \omega_{fi}) |M_2|^2 &= \frac{pc\hbar}{2} \frac{1}{(1 - \beta \cos\theta)^2} \sin^2\phi \left[\frac{1}{\beta} |F_0^-|^2 n_{xi} \delta_{\delta n_x, -1} \right. \\ &\quad \left. + \sum_{m=1}^{+\infty} \left(\frac{2\pi m}{L_0} - \frac{\delta n_x}{\beta} \right) (|F_m^-|^2 n_{xi} \delta_{\delta n_x, -1} + |F_m^+|^2 (n_{xi} + 1) \delta_{\delta n_x, +1}) \right]. \end{aligned} \quad (4.131)$$

Hence the summation over n_{xf} in Eq. (4.110) is greatly simplified by the Kronecker δ functions in Eq. (4.131) to give the expected rate of change for the transverse quantum level:

$$\begin{aligned} \left\langle \frac{dn_x}{dt} \right\rangle &= \frac{e^2 c}{16\pi^2 \epsilon_0 E} \int \frac{d\Omega}{(1 - \beta \cos\theta)^2} \left[\left(\frac{\cos\theta - \beta}{1 - \beta \cos\theta} \right)^2 \cos^2\phi + \sin^2\phi \right] \left[-\frac{1}{\beta} |F_0^-|^2 n_x \right. \\ &\quad \left. - \sum_{m=1}^{+\infty} \left(\frac{2\pi m}{L_0} + \frac{1}{\beta} \right) |F_m^-|^2 n_x + \sum_{m=1}^{+\infty} \left(\frac{2\pi m}{L_0} - \frac{1}{\beta} \right) |F_m^+|^2 (n_x + 1) \right], \end{aligned} \quad (4.132)$$

where we have replaced n_{xi} by n_x without ambiguity.

Integration over the solid angle in Eq. (4.132) yields $8\pi\gamma^2/3$ to the leading order. In the limit of continuous focusing, the focusing function k_x is a constant, and only $|F_0|^2 = 1/\bar{\beta} = \sqrt{k_x}$ term contributes to Eq. (4.132). For this special case, we now have

$$\left\langle \frac{dn_x}{dt} \right\rangle = -\frac{e^2 c}{16\pi^2 \epsilon_0 E} \frac{8\pi^2 \gamma^2}{3} \frac{1}{\bar{\beta}^2} n_x = -\frac{2r_e c}{3} \gamma k_x n_x. \quad (4.133)$$

If we define the energy-independent focusing strength $K_x = Ek_x = \gamma mc^2 k_x$, and multiply both sides of Eq. (4.133) by $\hbar$, we recover the exponential damping Eq. (4.84) without any quantum excitation.

With the help of Eq. (4.126), we can write Eq. (4.132) as

$$\left\langle \frac{dn_x}{dt} \right\rangle = \frac{2r_e c \gamma}{3} \left[-n_x \sum_{m=-\infty}^{+\infty} \left(\frac{2\pi m}{L_0} + \frac{1}{\beta} \right) |F_m^-|^2 + \sum_{m=1}^{+\infty} \left(\frac{2\pi m}{L_0} - \frac{1}{\beta} \right) |F_m^+|^2 \right]. \quad (4.134)$$

The first term in the bracket is radiation damping and the second one is quantum excitation. Furthermore, another suggestive form can be written by considering

$$\frac{d}{dz} \left[\left(\frac{\beta'_x}{2\sqrt{\beta_x}} \pm \frac{i}{\sqrt{\beta_x}} \right) \exp \left(\pm i \int_0^z \frac{dz}{\beta_x} \right) \right] = -k_x \sqrt{\beta_x} \exp \left(\pm i \int_0^z \frac{dz}{\beta_x} \right), \quad (4.135)$$

where Eq. (A.23) is used to reach the right hand side. Using this equation and integration by part for Eq. (4.122), we have

$$\begin{aligned} F_m^\pm &= \int_{-L_0/2}^{L_0/2} \frac{dz}{L_0} \left(\frac{\beta'_x}{2\sqrt{\beta_x}} \pm \frac{i}{\sqrt{\beta_x}} \right) \exp \left(\pm i \int_0^z \frac{dz}{\beta_x} \right) \exp \left[+iz \left(\frac{2\pi m}{L_0} \mp \frac{1}{\beta} \right) \right], \\ &= - \frac{i}{\left(\frac{2\pi m}{L_0} \mp \frac{1}{\beta} \right)} \int_{-L_0/2}^{L_0/2} \frac{dz}{L_0} \sqrt{\beta_x} k_x e^{\pm i\varphi} \exp \left(+iz \frac{2\pi m}{L_0} \right). \end{aligned} \quad (4.136)$$

Thus, Eq. (4.134) becomes

$$\left\langle \frac{dn_x}{dt} \right\rangle = \frac{2r_e c \gamma}{3} \left[-n_x \sum_{m=-\infty}^{+\infty} \frac{1}{\left(\frac{2\pi m}{L_0} + \frac{1}{\beta} \right)} |D_m^-|^2 + \sum_{m=1}^{+\infty} \frac{1}{\left(\frac{2\pi m}{L_0} - \frac{1}{\beta} \right)} |D_m^+|^2 \right], \quad (4.137)$$

where

$$D_m^\pm = \int_{-L_0/2}^{L_0/2} \frac{dz}{L_0} \sqrt{\beta_x} k_x e^{\pm i\varphi} \exp \left(+imz \frac{2\pi}{L_0} \right). \quad (4.138)$$

Therefore, the equilibrium transverse energy level (as well as the equilibrium normalized transverse emittance) can be obtained by setting Eq. (4.134) or (4.137) to zero for any periodic focusing system.

We can perform another integration by parts on the Fourier coefficient $D_m^\pm$:

$$\begin{aligned} D_m^\pm &= \int_{-L_0/2}^{L_0/2} \frac{dz}{L_0} \sqrt{\beta_x} k_x \exp \left(\pm i \int_0^z \frac{dz}{\beta_x} \right) \exp \left[+iz \left(\frac{2\pi m}{L_0} \mp \frac{1}{\beta} \right) \right] \\ &= - \frac{i}{\left(\frac{2\pi m}{L_0} \mp \frac{1}{\beta} \right)} \int_{-L_0/2}^{L_0/2} \frac{dz}{L_0} \exp \left[+iz \left(\frac{2\pi m}{L_0} \mp \frac{1}{\beta} \right) \right] \frac{d}{dz} \left[\sqrt{\beta_x} k_x \exp \left(\pm i \int_0^z \frac{dz}{\beta_x} \right) \right]. \end{aligned} \quad (4.139)$$

In an idealized FODO lattice where the focusing function k_x is piecewise constant with the magnitude given by k_0 (Fig. 4.4), the derivative of k_x is a series of delta

functions at the discontinuities, and hence the last integration is still integrable. We can now estimate the upper bound for $|D_m^\pm|^2$ for the FODO lattice when the magnet length L is small compared with the lattice period L_0 [78]:

$$|D_m^\pm|^2 \lesssim \frac{k_0^2 (\sqrt{\beta_x^+} + \sqrt{\beta_x^-})^2}{\left(2\pi m \mp \frac{L_0}{\beta}\right)^2}, \quad (4.140)$$

where β_x^+ and β_x^- are the beta function at the center of the focusing and the defocusing quadrupoles, respectively. If we use the thin lens approximation and define the focal length $f = (k_0 L)^{-1}$, and the FODO parameter $\kappa = 2f/L_0$ [78], then we have

$$\beta_x^+ = \frac{L_0}{2} \frac{\kappa(\kappa + 1)}{\sqrt{\kappa^2 - 1}}, \quad \text{and} \quad \beta_x^- = \frac{L_0}{2} \frac{\kappa(\kappa - 1)}{\sqrt{\kappa^2 - 1}}. \quad (4.141)$$

Hence the upper bound for the quantum excitation term is given by

$$\sum_{m=1}^{+\infty} \frac{1}{\left(\frac{2\pi m}{L_0} - \frac{1}{\beta}\right)} |D_m^+|^2 \lesssim \frac{L_0 k_0^2 (\sqrt{\beta_x^+} + \sqrt{\beta_x^-})^2}{(2\pi)^3} \sum_{m=1}^{+\infty} \frac{1}{(m - \mu_x)^3}, \quad (4.142)$$

where $\mu_x = L_0/(2\pi\bar{\beta}) \simeq 2/\kappa < 1$ is the betatron phase advance per cell (in fraction of 2π). The summation on the right hand side of Eq. (4.142) can be expressed as the generalized Riemann's Zeta function $\zeta(3, -\mu_x)$ [22] and is clearly convergent. When $\mu_x \ll 1$, the summation approaches a numerical value given by $\zeta(3) \simeq 1.20206$.

The dominant contribution of radiation damping comes from the average focusing effect which is the $m = 0$ term, with

$$|D_0^-|^2 = \left| \int_{-L_0/2}^{L_0/2} \frac{dz}{L_0} \sqrt{\beta_x} k_x e^{-i\varphi} \right|^2 \simeq \frac{k_0^2 L^2}{L_0^2} (\sqrt{\beta_x^+} - \sqrt{\beta_x^-})^2 \quad (4.143)$$

We can estimate the summation from $m = 1$ to $+\infty$ and from $m = -1$ to $-\infty$ the same way as the quantum excitation summation, and they cancel each other to a very large degree. Thus, the final equilibrium energy level is given by

$$n_x \lesssim \frac{L_0^3}{(2\pi)^3 \bar{\beta} L^2} \frac{(\sqrt{\beta_x^+} + \sqrt{\beta_x^-})^2}{(\sqrt{\beta_x^+} - \sqrt{\beta_x^-})^2} \sim \frac{L_0^2 \kappa}{\pi^3 L^2} \sim \left(\frac{L_0}{L}\right)^2 \frac{2}{\pi^3 \mu_x}. \quad (4.144)$$

This equation clearly shows that the equilibrium energy level is no more than a few for a FODO lattice, and the equilibrium emittance obtainable in a straight FODO

Figure 4.4: The focusing function in an idealized FODO lattice.

channel is close to the Compton wavelength. Therefore, even though quantum excitation to the transverse emittance is not totally forbidden in a periodic focusing channel because the lattice modes can provide the additional longitudinal recoil, the probability of quantum excitation is small in a relatively smooth focusing system.

We can also compute the expected rate of energy loss (the negative of the radiated power) by replacing δn_x with

$$\delta E = -\hbar\omega = -\hbar c \frac{\beta}{(1 - \beta \cos \theta)} \left(\frac{2\pi m}{L_0} - \frac{\delta n_x}{\beta} \right) \sim \hbar c \gamma^2 \left(\frac{2\pi m}{L_0} - \frac{\delta n_x}{\beta} \right) \quad (4.145)$$

in Eq. (4.110), we then arrive at

$$\left\langle \frac{dE}{dt} \right\rangle = -\frac{2r_e \hbar c^2 \gamma^3}{3} \left(n_x \sum_{m=-\infty}^{+\infty} |D_m^-|^2 + \sum_{m=1}^{+\infty} |D_m^+|^2 \right). \quad (4.146)$$

When n_x is large, we can drop the second term in the bracket and use the Parseval's Theorem [3] for

$$\sum_{m=-\infty}^{+\infty} |D_m^-|^2 = \int_{-L_0/2}^{L_0/2} \frac{dz}{L_0} \beta_x k_x^2, \quad (4.147)$$

hence we obtain

$$\begin{aligned} \left\langle \frac{dE}{dt} \right\rangle &= - \frac{2r_e \hbar n_x c^2 \gamma^3}{3} \int_{-L_0/2}^{L_0/2} \frac{dz}{L_o} \beta_x k_x^2. \\ &\simeq - \frac{2r_e \gamma^2}{3mc} \int_{-L_0/2}^{L_0/2} \frac{dz}{L_o} \frac{J_x}{p} \beta_x K_x^2, \end{aligned} \quad (4.148)$$

where $J_x \simeq \hbar n_x$ is the transverse action, $K_x = Ek_x$ is the focusing strength and the integration over z can be regarded as the average of the square of the transverse focusing force $K_x x$, coinciding with Eq. (3.33).

4.4 Bent Focusing Systems

In Sections 4.2 and 4.3, we show that the radiation reaction in a focusing channel is fundamentally different from a bending magnet in an electron storage ring. Although the transverse focusing quadrupoles are present in a storage ring to confine the beam, and they can modify the individual radiation damping rates by coupling with the bending fields in a combined-function system (i.e., through the damping partition parameter $\mathcal{D}$), their contributions to the overall radiation effects are usually negligible compared to the bending dipoles in a normal storage ring. In this section, we study the radiation effects in a storage system with arbitrarily strong bending and focusing present. The general results obtained here unify the two limiting cases of Section 4.1 and Section 4.2, and also point to an interesting regime that might be useful for ultra-low emittance generation.

4.4.1 Limitations of the Quasiclassical Approach

Before we proceed with the general treatment, let us examine closely the underlying assumptions in the quasiclassical approach outlined in Section 4.1.1. In a normal electron storage ring, the length associated with a typical photon emission (the radiation formation length) is on the order of ρ/γ . The standard treatment of quantum excitation can be quasiclassical because the radiation formation length is much shorter than the oscillation wavelengths associated with all three degrees of freedom. Thus, one

can model the radiation to be instantaneous with a continuous spectrum of frequencies and treat the quantum nature of radiation as fluctuations about the average rate, as we did in Section 4.1. In Ref. [72, 73], radiation damping and quantum excitation were analyzed by a rigorous quantum mechanical approach for a weak focusing synchrotron. The results agree with those of Section 4.1 and confirm the quasiclassical picture of quantum excitation.

In a straight focusing channel, although we follow the steps of the quasiclassical approach to look for the change of the transverse action after a photon emission, the treatment for the lack of quantum excitation is quantum mechanical because we do not invoke any quasiclassical assumptions for this purpose. Instead, we only use the invariants of the system in the absence of radiation to characterize the changes due to emissions of photons. The translational invariance plus the energy conservation uniquely determine the sign of these changes. The radiation reaction to the transverse action can then be calculated quasiclassically because there is no quantum excitation (thus no $\hbar$ involved) in a straight focusing system.

When we move to a bent system, the translational invariance is nonexistent and the sign of changes of the transverse actions becomes undetermined. There could be quantum excitation to the horizontal and vertical actions. As the strength of the transverse focusing increases or as the bending field gradually decreases, the radiation formation length and the transverse oscillation wavelengths may become comparable. The radiation in this case cannot be regarded as instantaneous, and thus the quasiclassical picture of quantum excitation fails because we do not know how an instantaneous quantity such as x and x' changes. It is therefore necessary to invoke a quantum mechanical perturbation approach [25, 27, 31, 33] to calculate the transition rate and the change of transverse quantum levels, which are then related back to the transverse actions and emittances.

4.4.2 Suppression of Transverse Excitation

We consider here a simple model of storage rings with a continuous, linear focusing field around a circular electron orbit provided by a uniform magnetic field. The

model for the focusing field used below is electrostatic in origin such as that created by a dilute cloud of positive ions. The more realistic magnetic focusing field will be discussed later. Suppose that a reference electron with momentum p_0 has a circular trajectory with radius ρ , the three components of the vector potential $\mathbf{A}$ for the uniform bending field in the familiar curvilinear coordinates system (x, s, y) are given by Eq. (A.8) by setting the quadrupole focusing function $k_q = 0$:

$$\begin{aligned} A_x &= A_y = 0, \\ A_s &\equiv (\mathbf{A} \cdot \hat{\mathbf{s}}) \left(1 + \frac{x}{\rho}\right) = -\frac{p_0}{e} \left(\frac{x}{\rho} + \frac{x^2}{2\rho^2}\right). \end{aligned} \quad (4.149)$$

We assume the constant focusing strengths K_x in the horizontal x direction and K_y in the vertical y direction, the total energy of the electron can be decomposed as

$$\begin{aligned} E &= \sqrt{m_e^2 c^4 + p_x^2 c^2 + p_y^2 c^2 + \frac{(p_s - e A_s)^2 c^2}{(1 + x/\rho)^2}} + \frac{1}{2} K_x x^2 + \frac{1}{2} K_y y^2 \\ &\simeq E_s + \frac{p_x^2 c^2}{2E_s} + \frac{1}{2} \tilde{K}_x (x - x_\epsilon)^2 - \frac{1}{2} K'_x x_\epsilon^2 + \frac{p_y^2 c^2}{2E_s} + \frac{1}{2} K_y y^2 \end{aligned} \quad (4.150)$$

where

$$\begin{aligned} E_s &= \sqrt{m_e^2 c^4 + p_s^2 c^2}, \\ \tilde{K}_x &= K_x + \frac{[p_0^2 c^2 + 3(p_s - p_0)p_0 c^2]}{(E_s \rho^2)} \simeq K_x, \\ x_\epsilon &= \frac{(p_s - p_0)c}{(K_x \rho)} \quad (\text{equilibrium orbit}) \\ \omega_x &= \sqrt{\frac{K_x c^2}{E_s}} \quad \text{and} \quad \omega_y = \sqrt{\frac{K_y c^2}{E_s}} \end{aligned} \quad (4.151)$$

are all functions of p_s . Thus, both transverse motions are harmonic oscillations that are coupled with the longitudinal momentum. Following the treatment of Section 4.2.1, the eigenenergies of the electron in this system are

$$E(n_x, n_y, p_s) = E_s + \hbar \omega_x \left(n_x + \frac{1}{2}\right) - \frac{1}{2} K_x x_\epsilon^2 + \hbar \omega_y \left(n_y + \frac{1}{2}\right), \quad (4.152)$$

and the eigenstates are

$$\begin{aligned}
\psi_{n_x, n_y, p_s}(\mathbf{r}) &= \sqrt{\frac{m_e c^2}{E}} \bar{\psi}_{n_x, n_y, p_s}(\mathbf{r}) \quad \text{with} \\
\bar{\psi}_{n_x, n_y, p_s}(\mathbf{r}) &= \frac{1}{\sqrt{2\pi\rho}} \exp\left(i\frac{p_s}{\hbar}s\right) X_{n_x, p_s}(x) Y_{n_y, p_s}(y), \\
X_{n_x, p_s}(x) &= \sqrt{\frac{C_{n_x}}{x_0}} \exp\left[-\frac{(x-x_\epsilon)^2}{2x_0^2}\right] H_{n_x}\left(\frac{x-x_\epsilon}{x_0}\right), \\
Y_{n_y, p_s}(y) &= \sqrt{\frac{C_{n_y}}{y_0}} \exp\left(-\frac{y^2}{2y_0^2}\right) H_{n_y}\left(\frac{y}{y_0}\right),
\end{aligned} \tag{4.153}$$

where n_x and n_y are the transverse quantum levels, $C_n = (2^n n! \sqrt{\pi})^{-1}$ is the normalization constant, $x_0 = \sqrt{\hbar c^2 / E_s \omega_x}$ and $y_0 = \sqrt{\hbar c^2 / E_s \omega_y}$ are the respective ground state ($n_{x,y} = 0$) oscillation amplitudes, and H_n is the n^{th} order Hermite polynomial. Both the eigenenergies and eigenstates are functions of n_x , n_y and p_s , the quantum numbers that correspond to the invariant horizontal action, the vertical action and the canonical momentum conjugate to the s variable.

The change of the transverse quantum levels $n_{x,y}$ due to spontaneous radiation is described by Eq. (4.65), with the transition rate dW_{fi} from an initial state $|n_{xi}, n_{yi}, p_{si}\rangle$ to a final state $|n_{xf}, n_{yf}, p_{sf}\rangle$ by spontaneously emitting a photon $\mathbf{k} = k\mathbf{n}$ into the range $d\mathbf{k}$ is still given by Eq. (3.122), i.e.,

$$dW_{fi} = \frac{d\mathbf{k}}{(2\pi)^3} \frac{e^2}{2\epsilon_0 \hbar \omega} \left| \int d\mathbf{r} \bar{\psi}_f^*(\mathbf{r}) \sum_{\lambda=1}^2 \mathbf{e}_\lambda \cdot \mathbf{v} e^{-i\mathbf{k} \cdot \mathbf{r}} \bar{\psi}_i(\mathbf{r}) \right|^2 2\pi \delta(\omega - \omega_{fi}), \tag{4.154}$$

The electron velocity operator, when expressed in the Cartesian coordinates, is

$$\begin{aligned}
\mathbf{v} &\simeq \frac{(\mathbf{p} - e\mathbf{A})c^2}{\sqrt{E_i E_f}} \\
&\simeq \left(p_x \cos \frac{s}{\rho} - \frac{p_s - eA_s}{1 + x/\rho} \sin \frac{s}{\rho}, \quad p_y, \quad p_x \sin \frac{s}{\rho} + \frac{p_s - eA_s}{1 + x/\rho} \cos \frac{s}{\rho} \right) \frac{c^2}{E_0},
\end{aligned} \tag{4.155}$$

where E_0 is the synchronous energy and the momentum operators are

$$p_x = -i\hbar \frac{\partial}{\partial x}, \quad p_y = -i\hbar \frac{\partial}{\partial y}, \quad \text{and} \quad p_s = -i\hbar \frac{\partial}{\partial s}. \tag{4.156}$$

Because of the curvilinear coordinates used for the electron, we do not have momentum conservation between the electron and the photon in the s direction even though the eigenstates of the electron have plane-wave form in s .

Since we are interested in the total radiation effects instead of the spectrum and polarization properties of the emitted photons, we can sum over the photon polarization and integrate Eq. (4.154) over the momentum space of the photons. First, let us expand the δ function

$$\delta(\omega - \omega_{fi}) = \frac{1}{2\pi} \int_{-\infty}^{+\infty} dt e^{-i(\omega - \omega_{fi})t}, \quad (4.157)$$

and write Eq. (4.154) as

$$\begin{aligned} W_{fi} = & \frac{e^2}{4\pi^2 \epsilon_0 \hbar c} \int_{-\infty}^{+\infty} dt e^{i\omega_{fi}t} \int \int \frac{k dk d\Omega}{4\pi} e^{-ikct} \sum_{\lambda=1}^2 \int d\mathbf{r}_1 \bar{\psi}_f^*(\mathbf{r}_1) e^{-i\mathbf{k} \cdot \mathbf{r}_1} (\mathbf{v}_1 \cdot \mathbf{e}_\lambda) \bar{\psi}_i(\mathbf{r}_1) \\ & \times \int d\mathbf{r}_2 \bar{\psi}_f(\mathbf{r}_2) e^{i\mathbf{k} \cdot \mathbf{r}_2} (\mathbf{v}_2 \cdot \mathbf{e}_\lambda) \bar{\psi}_i^*(\mathbf{r}_1), \end{aligned} \quad (4.158)$$

where $\mathbf{v}_{1,2}$ is used to distinguish between the velocity operators that operate on $\mathbf{r}_1$ and $\mathbf{r}_2$, respectively. By applying the polarization sum

$$\sum_{\lambda=1}^2 (\mathbf{v}_1 \cdot \mathbf{e}_\lambda)(\mathbf{v}_2 \cdot \mathbf{e}_\lambda) = \mathbf{v}_1 \cdot \mathbf{v}_2 - (\mathbf{v}_1 \cdot \mathbf{n})(\mathbf{v}_2 \cdot \mathbf{n}), \quad (4.159)$$

and introducing the Green's function [72]

$$G(t, r) = - \int \int \frac{k dk d\Omega}{4\pi} e^{-ikct + i\mathbf{k} \cdot \mathbf{r}} = \lim_{\epsilon \rightarrow +0} \frac{1}{c^2(t - i\epsilon)^2 - r^2}, \quad (4.160)$$

we obtain

$$\begin{aligned} W_{fi} = & \frac{e^2 c}{4\pi^2 \epsilon_0 \hbar} \int_{-\infty}^{+\infty} dt e^{i\omega_{fi}t} \int \int d\mathbf{r}_1 d\mathbf{r}_2 \bar{\psi}_f^*(\mathbf{r}_1) \bar{\psi}_f(\mathbf{r}_2) \\ & \times G(t, |\mathbf{r}_1 - \mathbf{r}_2|) \left(1 - \frac{\mathbf{v}_1 \cdot \mathbf{v}_2}{c^2}\right) \bar{\psi}_i(\mathbf{r}_1) \bar{\psi}_i^*(\mathbf{r}_2). \end{aligned} \quad (4.161)$$

We make the change of variables $\phi = (s_1 - s_2)/\rho$ and $\phi' = (s_1 + s_2)/\rho$. Insert

Eq. (4.153) into Eq. (4.161) and integrate over ϕ' , we arrive at

$$\begin{aligned}
 W_{fi} = & \frac{e^2 c}{\pi \hbar} \int_{-\infty}^{+\infty} dt e^{i\omega_{fi} t} \int_{-2\pi}^{2\pi} \frac{d\phi}{2\pi} \exp \left[i \frac{(p_s - p_{sf}) \rho \phi}{\hbar} \right] \\
 & \times \int dx_1 dx_2 dy_1 dy_2 X_f(x_1) X_f(x_2) Y_f(y_1) Y_f(y_2) \\
 & \times GV X_i(x_1) X_i(x_2) Y_i(y_1) Y_i(y_2),
 \end{aligned} \tag{4.162}$$

where the Green's function

$$G = \left[c^2(t - i\epsilon)^2 - (\rho + x_1)^2 - (\rho + x_2)^2 + 2(\rho + x_1)(\rho + x_2) \cos \phi - (y_1 - y_2)^2 \right]^{-1}, \tag{4.163}$$

and the factor

$$\begin{aligned}
 V &= 1 - \frac{\mathbf{v}_1 \cdot \mathbf{v}_2}{c^2} \simeq 1 - \frac{(\mathbf{p}_1 - e\mathbf{A}_1) \cdot (\mathbf{p}_2 - e\mathbf{A}_2)}{E_0^2/c^2} \\
 &\simeq 1 - \frac{(p_{x1}p_{x2} + p_s^2)c^2}{E_0^2} \cos \phi - \frac{(p_{x1} + p_{x2})p_s c^2}{E_0^2} \sin \phi - \frac{p_{y1}p_{y2}c^2}{E_0^2} + \mathcal{O} \left(\frac{x_{1,2}^2}{\rho^2} \right).
 \end{aligned} \tag{4.164}$$

In the last equation, p_s is the eigenvalue of both operators p_{s1} and p_{s2} . We have used the approximation that $p_s \simeq p_0$ because it is sufficient to consider the case when the electron is initially on the ideal circular orbit.

For simplicity, we consider small transverse oscillations in the weak undulator regime (i.e., $\gamma\theta_p^x \ll 1$ and $\gamma\theta_p^y \ll 1$). Thus, we can use the dipole approximation [25, 27] by expanding all the operators to the first order in x or p_x , as we did in Eq. (4.164). We can also neglect the small betatron frequency shifts due to their p_s dependence. From Eq. (4.152), we obtain

$$\omega_{fi} \simeq v(p_{si} - p_{sf})/\hbar + \omega_x(n_{xi} - n_{xf}) + \omega_y(n_{yi} - n_{yf}), \tag{4.165}$$

with $v = p_0 c^2 / E_0$. However, the change of the equilibrium orbit must be properly taken into account. Expanding the final horizontal wavefunction in terms of the initial equilibrium orbit displacement, we have

$$\begin{aligned}
 X_{n_{xf}, p_{sf}}(x) &= \left[1 + \frac{(p_{si} - p_{sf})c}{K_x \rho} \partial_x \right] X_{n_{xf}, p_{si}}(x) + \mathcal{O}(\partial_x^2) \\
 &= \left[1 + i \frac{(p_{si} - p_{sf})c}{K_x \rho \hbar} p_x \right] X_{n_{xf}, p_{si}}(x) + \mathcal{O}(p_x^2).
 \end{aligned} \tag{4.166}$$

Introduce the notation $(p_{si} - p_{sf})\rho/\hbar = l$, $n_{xf} - n_{xi} = \delta n_x$ and $n_{yf} - n_{yi} = \delta n_y$, we arrive at

$$\begin{aligned}
 W_{fi} = & \frac{e^2 c}{4\pi^2 \epsilon_0 \hbar} \int_{-\infty}^{+\infty} dt \exp[-i(\delta n_x \omega_x + \delta n_y \omega_y)t] \int_{-2\pi}^{2\pi} \frac{d\phi}{2\pi} \exp\left[il\left(\phi - \frac{vt}{\rho}\right)\right] \\
 & \times \int dx_1 dx_2 dy_1 dy_2 X_{n_{xf}}(x_1) X_{n_{xf}}(x_2) Y_{n_{yf}}(y_1) Y_{n_{yf}}(y_2) \left(1 + il \frac{p_{x1}c}{K_x \rho^2}\right) \\
 & \times \left(1 + il \frac{p_{x2}c}{K_x \rho^2}\right) GV X_{n_{xi}}(x_1) X_{n_{xi}}(x_2) Y_{n_{yi}}(y_1) Y_{n_{yi}}(y_2), \tag{4.167}
 \end{aligned}$$

where we have dropped the subscript p_s from all the transverse wavefunctions to simplify the notations.

From Eq. (4.65), the expected rate of change of the horizontal quantum number is given by

$$\left\langle \frac{dn_x}{dt} \right\rangle = \sum_{n_{xf}, n_{yf}, p_{sf}} (n_{xf} - n_{xi}) W_{fi} = \sum_{\delta n_x, \delta n_y, l} \delta n_x W_{fi}. \tag{4.168}$$

The sum over l can be first carried out using the set of relations

$$\begin{aligned}
 \sum_l \exp\left[il\left(\phi - \frac{vt}{\rho}\right)\right] &= 2\pi \delta_p\left(\phi - \frac{vt}{\rho}\right), \\
 \sum_l il \exp\left[il\left(\phi - \frac{vt}{\rho}\right)\right] &= 2\pi \delta'_p\left(\phi - \frac{vt}{\rho}\right), \tag{4.169}
 \end{aligned}$$

where $\delta_p(\phi)$ is the periodic delta function with periodicity 2π , and the prime means derivative with respect to ϕ . Integration by parts over ϕ yields

$$\begin{aligned}
 \left\langle \frac{dn_x}{dt} \right\rangle = & \frac{e^2 c}{4\pi^2 \epsilon_0 \hbar} \sum_{\delta n_x} \delta n_x \sum_{\delta n_y} \int_{-\infty}^{+\infty} dt \exp[-i(\delta n_x \omega_x + \delta n_y \omega_y)t] \\
 & \times \int dx_1 dx_2 dy_1 dy_2 X_{n_{xf}}(x_1) X_{n_{xf}}(x_2) Y_{n_{yf}}(y_1) Y_{n_{yf}}(y_2) \left(1 - \frac{p_{x1}c}{K_x \rho^2} \frac{\partial}{\partial \phi}\right) \\
 & \times \left(1 - \frac{p_{x2}c}{K_x \rho^2} \frac{\partial}{\partial \phi}\right) GV X_{n_{xi}}(x_1) X_{n_{xi}}(x_2) Y_{n_{yi}}(y_1) Y_{n_{yi}}(y_2), \tag{4.170}
 \end{aligned}$$

where the derivative with respect to ϕ is to be evaluated at $\phi = vt/\rho$ due to the delta functions in Eq. (4.169).

The Green's function in Eq. (4.163) plays the role of determining the major contribution of the time integral. Let us define a dimensionless time variable $\tau = ct/\rho$ and expand $\cos \phi$ in the denominator of Eq. (4.163) to obtain

$$G \simeq \left[I(\tau, \phi) - \left(\frac{x_1 - x_2}{\rho} \right)^2 - \frac{x_1 + x_2}{\rho} \phi^2 - \left(\frac{y_1 - y_2}{\rho} \right)^2 \right]^{-1} \rho^{-2}, \quad (4.171)$$

where $I(\tau, \phi) = (\tau - i\epsilon)^2 - \phi^2 + \phi^4/12 \simeq \tau^2(\gamma^{-2} + \tau^2/12)$ since $\phi = vt/\rho$. The time integral is significant only when $\tau \sim \phi \sim 1/\gamma$, or $ct \sim \rho/\gamma$ (the radiation formation length). Thus, we can also expand Eq. (4.164) for small ϕ to obtain

$$V \simeq \frac{1}{\gamma^2} + \frac{\phi^2}{2} + \frac{p_{x1}p_{x2}c^2}{E_0^2} - \frac{(p_{x1} + p_{x2})c}{E_0}\phi + \frac{p_{y1}p_{y2}c^2}{E_0^2} + \mathcal{O}\left(\frac{x_{1,2}^2}{\rho^2}\right). \quad (4.172)$$

We can further expand the Green's function to order x^2/ρ^2 and y^2/ρ^2 :

$$G \simeq \frac{1}{\rho^2} \left[\frac{1}{I} + \frac{(x_1 - x_2)^2}{\rho^2} \frac{1}{I^2} + \frac{(x_1 + x_2)}{\rho} \frac{\phi^2}{I^2} + \frac{(x_1 + x_2)^2}{\rho^2} \frac{\phi^4}{I^3} + \frac{(y_1 - y_2)^2}{\rho^2} \frac{1}{I^2} \right] \quad (4.173)$$

To evaluate the integrals of the transverse coordinates in Eq. (4.170), let us write the coordinates and the momenta of Eq. (4.172), and Eq. (4.163) in terms of the raising and the lowering operators (a and $a^\dagger$) of the transverse harmonic oscillators [47]:

$$p_x = -i\sqrt{\frac{E_0\omega_x\hbar}{2c^2}}(a_x - a_x^\dagger), \quad x - x_\epsilon = \sqrt{\frac{c^2\hbar}{2E_0\omega_x}}(a_x + a_x^\dagger). \quad (4.174)$$

$$p_y = -i\sqrt{\frac{E_0\omega_y\hbar}{2c^2}}(a_y - a_y^\dagger), \quad y = \sqrt{\frac{c^2\hbar}{2E_0\omega_y}}(a_y + a_y^\dagger). \quad (4.175)$$

Applying Eq. (4.174) to the horizontal wavefunctions leads to three types of selection rule for δn_x . Those generated by constant terms have the selection rule $\delta n_x = 0$, and thus have no contribution to the summation over δ due to the multiplying factor δn_x in Eq. (4.170). Those generated by terms proportional to $p_{x1}p_{x2}$, x_1x_2 , $p_{x1}x_2$ and $p_{x2}x_1$ have the selection rule $\delta n_x = \pm 1$, and are the lowest order terms. Those generated by $x_1^2x_2^2$, $x_1^2x_2p_{x2}$ and $x_1p_{x1}x_2^2$ have the selection rule $\delta n_x = \pm 2$, but they are higher order terms in $\gamma\theta_p$ [25], and will be ignored (consistent with the dipole approximation).

Thus, the summation over δn_x can be greatly reduced by the selection rule $\delta n_x = \pm 1$. Similarly, applying Eq. (4.175) to the vertical wavefunctions leads to the same three types of selection rule for δn_y . The leading order terms (in $\gamma\theta_p$) are those correspond to the selection rule $\delta n_y = 0$, and the integration over y variables simply collapse the vertical wavefunctions to identity. Let us define for convenience a weighted average of an operator Q

$$\langle Q \rangle_x \equiv \sum_{\delta n_x} \delta n_x e^{-i\delta n_x \nu_x \tau} \int \int dx_1 dx_2 X_{n_{xf}}(x_1) X_{n_{xf}}(x_2) Q X_{n_{xi}}(x_1) X_{n_{xi}}(x_2), \quad (4.176)$$

where $\nu_x = \rho/\beta_x$ is roughly the horizontal tune for this smooth storage ring and $\beta_x = c/\omega_x$ is the reduced betatron wavelength or the average beta function. Use Eq. (4.118) and write n_{xi} as n_x , we obtain

$$\begin{aligned} \langle p_{x1} p_{x2} \rangle_x &= \frac{E_0 \hbar}{2c\beta_x} [n_x e^{i\nu_x \tau} - (n_x + 1) e^{-i\nu_x \tau}], \\ \langle x_1 x_2 \rangle_x &= -\frac{c\beta_x \hbar}{2E_0} [n_x e^{i\nu_x \tau} - (n_x + 1) e^{-i\nu_x \tau}], \\ \langle p_{x1} x_2 \rangle_x &= \langle p_{x2} x_1 \rangle_x = i [n_x e^{i\nu_x \tau} + (n_x + 1) e^{-i\nu_x \tau}]. \end{aligned} \quad (4.177)$$

Equation (4.170) can now be reduced to

$$\begin{aligned} \left\langle \frac{dn_x}{dt} \right\rangle &= \frac{r_e c}{\pi \gamma \rho^2} \int_{-\infty}^{+\infty} d\tau \left\{ i \left[\frac{\tau^3}{I} - \frac{4\tau^3(\gamma^{-2} + \tau^2/2)}{\nu_x^2 I^3} \right] [n_x e^{i\nu_x \tau} + (n_x + 1) e^{-i\nu_x \tau}] \right. \\ &\quad \left. + \left[\frac{\nu_x}{2I} - \frac{2\tau^2}{\nu_x I^2} + \frac{4\tau^2 - \nu_x^2(\tau^4 - I)(\gamma^{-2} + \tau^2/2)}{\nu_x^3 I^3} \right] [n_x e^{i\nu_x \tau} - (n_x + 1) e^{-i\nu_x \tau}] \right\} \end{aligned} \quad (4.178)$$

The time integral can be performed using the residue technique in the complex τ plane (Fig. 4.5). Since $\nu_x > 0$, we can close the contour in the upper-half plane to compute the integral of the type

$$\begin{aligned} \overline{(m, n)} &\equiv \frac{1}{\pi} \int_{-\infty}^{+\infty} \frac{d\tau e^{i\nu_x \tau}}{(\tau - i\epsilon)^m (\gamma^{-2} + \tau^2/12)^n} \\ &= 2(12)^n i \left\{ \frac{1}{(m-1)!} \left(\frac{d}{d\tau} \right)^{m-1} \left[\frac{e^{i\nu_x \tau}}{(\tau^2 + 12/\gamma^2)^n} \right] \right|_{\tau=0} \\ &\quad + \frac{1}{(n-1)!} \left(\frac{d}{d\tau} \right)^{n-1} \left[\frac{e^{i\nu_x \tau}}{\tau^m (\tau + i\sqrt{12}/\gamma)^n} \right] \Big|_{\tau=i\sqrt{12}/\gamma} \right\}, \end{aligned} \quad (4.179)$$

Figure 4.5: Contours of integration for Eqs. (4.179) and (4.180).

and then close the contour in the lower-half plane to compute the integral

$$\begin{aligned}
 \underline{(m, n)} &\equiv \frac{1}{\pi} \int_{-\infty}^{+\infty} \frac{d\tau e^{-i\nu_x \tau}}{(\tau - i\epsilon)^m (\gamma^{-2} + \tau^2/12)^n} \\
 &= -2(12)^n i \frac{1}{(n-1)!} \left(\frac{d}{d\tau} \right)^{n-1} \left[\frac{e^{i\nu_x \tau}}{\tau^m (\tau + i\sqrt{12}/\gamma)^n} \right] \Big|_{\tau = -i\sqrt{12}/\gamma}.
 \end{aligned} \tag{4.180}$$

Using the definitions

$$\begin{aligned}
 (m, n)_+ &= \overline{(m, n)} + \underline{(m, n)}, \\
 (m, n)_- &= \overline{(m, n)} - \underline{(m, n)},
 \end{aligned} \tag{4.181}$$

we can write Eq. (4.178) as

$$\begin{aligned}
\left\langle \frac{dn_x}{dt} \right\rangle = & \frac{r_e c}{\gamma \rho^2} n_x \left\{ \frac{\nu_x}{2} (2, 1)_- + i(1, 2)_+ - \frac{2}{\nu_x} (2, 2)_- \right. \\
& - \frac{1}{\nu_x} \left[\frac{1}{\gamma^2} ((2, 3)_- - (4, 2)_-) + \frac{1}{2} ((0, 3)_- - (2, 2)_-) \right] \\
& - \frac{4i}{\nu_x^2} \left[\frac{1}{\gamma} (3, 3)_+ + \frac{1}{2} (1, 3)_+ \right] + \frac{4}{\nu_x^3} \left[\frac{1}{\gamma^2} (4, 3)_- + \frac{1}{2} (2, 3)_- \right] \Big\} \\
& + \frac{r_e c}{\gamma \rho^2} \left\{ - \frac{\nu_x}{2} \underline{(2, 1)} + i \underline{(1, 2)} + \frac{2}{\nu_x} \underline{(2, 2)} \right. \\
& + \frac{1}{\nu_x} \left[\frac{1}{\gamma^2} (\underline{(2, 3)} - \underline{(4, 2)}) + \frac{1}{2} (\underline{(0, 3)} - \underline{(2, 2)}) \right] \\
& - \frac{4i}{\nu_x^2} \left[\frac{1}{\gamma} \underline{(3, 3)} + \frac{1}{2} \underline{(1, 3)} \right] - \frac{4}{\nu_x^3} \left[\frac{1}{\gamma^2} \underline{(4, 3)} + \frac{1}{2} \underline{(2, 3)} \right] \Big\}.
\end{aligned} \tag{4.182}$$

After some lengthy but straightforward algebraic manipulations, we obtain

$$\left\langle \frac{dn_x}{dt} \right\rangle = -\frac{2}{3} \frac{r_e c \gamma^3}{\rho^2} (\varsigma_x^2 - 1) n_x + \frac{r_e c \gamma^3}{\rho^2} \frac{\exp(-2\sqrt{3}\varsigma_x)}{144\varsigma_x^3} F_x(\varsigma_x), \tag{4.183}$$

where

$$F_x(\varsigma_x) = 55\sqrt{3} + 330\varsigma_x + 262\sqrt{3}\varsigma_x^2 + 300\varsigma_x^3 + 48\sqrt{3}\varsigma_x^4, \tag{4.184}$$

and $\varsigma_x = (\rho/\gamma)/\beta_x$ is the ratio of the radiation formation length to the reduced horizontal betatron wavelength.

Similarly, we can find the expected rate of change for the vertical quantum number with the selection rules $\delta n_y = \pm 1$ and $\delta n_x = 0$ to obtain

$$\begin{aligned}
\left\langle \frac{dn_y}{dt} \right\rangle &= \sum_{\delta n_y, \delta n_y, l} \delta n_y W_{fi} \\
&= \frac{r_e c}{\pi \gamma \rho^2} \int_{-\infty}^{+\infty} d\tau \left[\frac{\nu_y}{2I} + \left(\frac{1}{\gamma^2} + \frac{\tau^2}{2} \right) \frac{1}{\nu_y I^2} \right] [n_y e^{i\nu_y \tau} - (n_y + 1) e^{-i\nu_y \tau}] \\
&= \frac{r_e c}{\gamma \rho^2} n_y \left[\frac{\nu_y}{2} (2, 1)_- + \frac{1}{2\nu_y} (2, 2)_- + \frac{1}{\nu_y \gamma^2} (4, 2)_- \right] \\
&\quad - \frac{r_e c}{\gamma \rho^2} \left[\frac{\nu_y}{2} \underline{(2, 1)} + \frac{1}{2\nu_y} \underline{(2, 2)} + \frac{1}{\nu_y \gamma^2} \underline{(4, 2)} \right] \\
&= -\frac{2}{3} \frac{r_e c \gamma^3}{\rho^2} (\varsigma_y^2 + 1) n_y + \frac{r_e c \gamma^3}{\rho^2} \frac{\exp(-2\sqrt{3}\varsigma_y)}{144\varsigma_y} F_y(\varsigma_y),
\end{aligned} \tag{4.185}$$

where

$$F_y(\varsigma_y) = 13\sqrt{3} + 30\varsigma_y + 12\sqrt{3}\varsigma_y^2. \quad (4.186)$$

and $\varsigma_y = (\rho/\gamma)/\beta_y$ is the ratio of the radiation formation length to the reduced vertical betatron wavelength $\beta_y = c/\omega_y$.

From Eq. (4.64), the transverse action J (J_x or J_y) is related to the transverse quantum levels n (n_x or n_y) by $J = \hbar(n + \frac{1}{2})$. Thus, we have

$$\left\langle \frac{dJ_x}{dt} \right\rangle = -\Gamma_b \left[(\varsigma_x^2 - 1) \left(J_x - \frac{\hbar}{2} \right) - \hbar \frac{\exp(-2\sqrt{3}\varsigma_x)}{96\varsigma_x^3} F_x(\varsigma_x) \right], \quad (4.187)$$

$$\left\langle \frac{dJ_y}{dt} \right\rangle = -\Gamma_b \left[(\varsigma_y^2 + 1) \left(J_y - \frac{\hbar}{2} \right) - \hbar \frac{\exp(-2\sqrt{3}\varsigma_y)}{96\varsigma_y} F_y(\varsigma_y) \right], \quad (4.188)$$

where $\Gamma_b = 2cr_e\gamma^3/(3\rho^2)$ is the characteristic damping coefficient due to the bending field (i.e. Eq. (4.4)). Equations (4.187) and (4.188) describe the general results of radiation (anti-)damping (the first term) and quantum excitation (the second term) to the transverse actions in this combined-function system when the betatron oscillation amplitudes are small. The relative amount of radiation damping and quantum excitation in each transverse plane can be determined by a single dimensionless parameter ς_x or ς_y respectively, which is a measure of the radiation formation length in units of the reduced betatron wavelength.

In normal synchrotrons and storage rings, the radiation formation length is much shorter than the reduced betatron wavelength, i.e., $\rho/\gamma \ll \beta_{x,y}$ or $\varsigma_{x,y} \ll 1$, Equations (4.187) and (4.188) become

$$\left\langle \frac{dJ_x}{dt} \right\rangle = -\Gamma_b \left[-\left(J_x - \frac{\hbar}{2} \right) - \hbar \frac{55\sqrt{3}\beta_x^3}{96(\rho/\gamma)^3} \right], \quad (4.189)$$

$$\left\langle \frac{dJ_y}{dt} \right\rangle = -\Gamma_b \left[\left(J_y - \frac{\hbar}{2} \right) - \hbar \frac{13\sqrt{3}\beta_y}{96(\rho/\gamma)} \right]. \quad (4.190)$$

Compared with Eqs. (4.29) and (4.38), both Eqs. (4.189) and (4.190) give the same results on radiation damping and quantum excitation as using the quasiclassical approach in a smooth storage ring. Note that the first term of Eq. (4.189) is anti-damping instead of damping because the combined-function system studied here has a negative horizontal damping partition number ($\mathcal{J}_x = -1$).

In the opposite limit where $\rho \rightarrow \infty$ (a straight focusing channel), we have $\rho/\gamma \gg \beta_{x,y}$ or $\varsigma_{x,y} \gg 1$, both Eqs. (4.187) and (4.188) reduce to

$$\left\langle \frac{dJ_x}{dt} \right\rangle = -\Gamma_b \varsigma_x^2 \left(J_x - \frac{\hbar}{2} \right) = -\Gamma_c^x \left(J_x - \frac{\hbar}{2} \right), \quad (4.191)$$

$$\left\langle \frac{dJ_y}{dt} \right\rangle = -\Gamma_b \varsigma_y^2 \left(J_y - \frac{\hbar}{2} \right) = -\Gamma_c^y \left(J_y - \frac{\hbar}{2} \right), \quad (4.192)$$

where $\Gamma_c^{x,y} = \Gamma_b \varsigma_{x,y}^2 = 2r_e K_{x,y} / (3m_e c)$ is the damping constant due to the focusing field defined in Eq. (4.84). No quantum excitation is induced in the straight system because $\underline{(m, n)} = 0$ in Eq. (4.180), and the selection rules becomes $\delta n_x = -1$ and $\delta n_y = 0$ or vice versa. As discussed in Section 4.2.4, the fundamental emittance $\lambda_c/2$ can in principle be reached in the ideal focusing channel in both transverse dimensions.

In the intermediate regime where the radiation formation length is on the order of the reduced betatron wavelength ($\rho/\gamma \sim \beta_{x,y}$ or $\varsigma_{x,y} \sim 1$), the horizontal action turns to damping instead of antidamping in this combined function system, while the damping of the vertical action is enhanced by a factor of two than that from the bending alone. What's more, the rates of quantum excitation in both transverse dimensions are exponentially suppressed according to Eqs. (4.187) and (4.188) and start to depart from the results based on the quasiclassical approach (see Fig. 4.6). Thus, the fundamental emittance can be approached very closely in such a focusing-dominated system. A physical interpretation can be given as follows: The transverse energy levels of the electron are well separated as a result of the strong focusing forces. Radiative transition to higher transverse levels becomes impossible for the electron with almost all photon emissions, and hence the quantum excitation is suppressed by the focusing environment.

4.4.3 Longitudinal Considerations

We are mostly interested in the regime when the radiation formation length is on the order of the transverse betatron wavelength ($\varsigma_{x,y} \sim 1$) and when the transverse oscillation amplitudes are small ($\gamma \theta_p^{x,y} \ll 1$). In this regime, the average radiated

Figure 4.6: Horizontal and vertical quantum excitation rate in units of $\Gamma_b \hbar$, predicted by (a) the quasi-classical model, i.e., the second terms of Eqs. (4.189) and (4.190), and (b) the quantum mechanical perturbation approach, i.e., the second terms of Eqs. (4.187) and (4.188).

energy loss comes predominately from the bending field rather than from the focusing field because

$$\frac{(dE/dt)_b}{(dE/dt)_f} = \frac{\frac{cC_r}{2\pi} \frac{E_0^4}{\rho^2}}{\frac{2r_e}{3mc} \gamma^2 K_x E_x} \sim \frac{1}{\zeta_x^2 \gamma^2 \theta_p^2} \gg 1. \quad (4.193)$$

We assume the average radiated energy loss is replenished by RF acceleration. The damping of the energy spread is achieved through the fact that the higher energy electrons lose more energy than the lower energy electrons. The energy spread may be due to the initial beam preparation, or may as well arise from the amplitude dependence of the radiated power in the focusing field (see Eq. (4.93)). The equilibrium energy spread is reached when the damping effect balances the average effect of quantum radiation. Since the synchrotron oscillation frequency is always much less than the transverse betatron oscillation frequencies (*i.e.*, $\omega_s \ll \omega_{x,y}$), the radiation formation length is always much smaller than the reduced synchrotron wavelength. Thus, the instantaneous picture of quantum emission is still valid in the longitudinal phase space and the results on the longitudinal damping and excitation derived in Section 4.1.3 follow. For example, the longitudinal damping rate and the equilibrium RMS energy spread are still given by Eq (4.48) and (4.51) respectively.

We note that all of the above results can be extended to alternating-gradient focusing systems when longitudinal variations of both bending and focusing fields are short compared with the radiation formation length. The generalization of the individual damping rate is straightforward. Combining the above analysis in this section and that of Section 4.3, we expect that the damping partition numbers for all three degrees of freedom are given by

$$\mathcal{J}_x = 1 - \mathcal{D} + \frac{\langle 1/\beta_x^2 \rangle_s}{\gamma^2 \langle 1/\rho^2 \rangle_s}, \quad \mathcal{J}_y = 1 + \frac{\langle 1/\beta_y^2 \rangle_s}{\gamma^2 \langle 1/\rho^2 \rangle_s}, \quad \mathcal{J}_s = 2 + \mathcal{D}, \quad (4.194)$$

Obviously, the Robinson damping criterion is modified because of the enhancement of radiation damping due to the transverse focusing forces. The rate of quantum excitation is slightly more complicated in an alternating-gradient system. However, we expect the exponential suppression factor $\exp(-2\sqrt{3}\zeta_{x,y})$ remain the same as in

the smooth system. Thus, the equilibrium transverse emittances may be substantially reduced because of the enhancement of radiation damping and the exponential suppression of quantum excitation due to very strong focusing.

4.4.4 A Focusing-dominated Damping Ring

In this section, we provide preliminary lattice considerations on a focusing-dominated damping ring based on the results obtained in the previous sections. Suppose that the ring is composed of many repetitive FODO cells. Each cell of length $4L$ consists of four basic elements of equal length L : focusing quad, bend, defocusing quad, and another identical bend. Both quads have the same field gradient g . Furthermore, we assume that the phase advance per cell is 60 degrees. If we treat the bending as gradual and the cell as a basic FODO cell with drift space $2L$, we obtain [29]

$$L[\text{cm}] = \left(\frac{E_0[\text{MeV}]}{6g[\text{Tesla/cm}]} \right)^{1/2}. \quad (4.195)$$

The average beta function (or the reduced betatron wavelength) for the 60 degrees cell is

$$\bar{\beta} = \frac{24L}{2\pi} = \frac{12L}{\pi} \quad (4.196)$$

By choosing the average bending radius $\bar{\rho} \simeq \gamma\bar{\beta}$, quantum excitation is kept at the very low level because of Eq. (4.187) and Eq. (4.188). Thus, the equilibrium emittance can be on the order of the Compton wavelength.

These simple lattice scaling formulas suggest that in order to design a compact ring, it is favorable to use high-gradient focusing quads and low-energy electron beams. As an example, if we assume that permanent-magnet quads have a field gradient $g = 4$ Tesla/cm, and we take the electron energy to be $E_0 = 25$ MeV, we then arrive at

$$L \simeq 1.0 \text{ cm}, \quad \bar{\beta} \simeq 3.9 \text{ cm}, \quad \bar{\rho} \simeq 1.9 \text{ m}. \quad (4.197)$$

The transverse damping rate is about the same for both the focusing effect and the bending effect since $\bar{\rho}/\gamma \simeq \bar{\beta}$. The two damping constants are

$$\Gamma_b = \Gamma_c = 0.11 \text{ sec}^{-1}. \quad (4.198)$$

This is very slow damping even in a storage ring because the energy of the electron beam is low.

The transverse size that corresponds to the Compton wavelength is

$$\sigma_{x,y} = \sqrt{\frac{\lambda_c \bar{\beta}}{\gamma}} = 18 \text{ nm}. \quad (4.199)$$

The energy loss per turn is mainly due to the bends, as long as the betatron amplitude is not too large. Thus, we have

$$(\Delta E) = \frac{2\pi\bar{\rho}}{c} \Gamma_b E_0 = 0.11 \text{ eV}. \quad (4.200)$$

It can be replenished by either RF or betatron-type acceleration. The equilibrium energy spread is determined by Eq. (4.51) with $\mathcal{J}_s = 2$:

$$\sigma_\delta = \sqrt{\frac{55\sqrt{3} \lambda_c \gamma^2}{96 \bar{\rho}}} = 1.6 \times 10^{-5}. \quad (4.201)$$

However, at such low energy, the space charge effects are significant. It might be conceivable to operate the ring below the transition energy $\gamma_t m_e c^2$ when

$$\frac{\bar{\rho}}{\beta} \simeq \gamma_t > \gamma \quad (4.202)$$

is satisfied, then the Coulomb interaction between electrons, together with the external focusing environment, tend to stabilize the beam by the crystallization effect [76]. Other collective effects such as wakefields and beam-gas scattering can also influence the stability of the system and may determine the final beam emittance. These effects have yet to be studied in this new regime of operation.

Chapter 5

Laser-Electron Storage Ring

In the preceding chapter we investigated different characteristics of radiation damping and quantum excitation in bending systems and focusing systems. We point out that the focusing environment can lead to a very quiet damped system with the potential of reaching the fundamental emittance. However, as we see from Section 4.4.4, the damping rate in a focusing-dominated ring is very slow unless we go to very high electron energy with correspondingly increased number of focusing elements. Thus, the intensity of such a cold electron beam is often limited by the collective growth effects such as space charge and wakefields.

Traditionally, the increase of the damping rate in a storage ring is achieved through the insertion wigglers [78]. The effect of these damping wigglers is to generate a lot more (undulator) radiation while keeping quantum excitation in check. This can be done by placing the wigglers in the dispersion free region of the storage ring. Recently, Telnov pointed out [75] that with a sufficiently intense laser pulse, a high energy electron beam can be cooled significantly during a single collision with the laser pulse. When the maximum energy of the scattered photons is small compared with the electron energy, the process of laser-electron interaction can be viewed either as Thomson scattering [35] or as undulator radiation, and hence the term “Radiative Laser cooling” [40] is invoked to distinguish from laser cooling that utilizes an atomic transition [66]. Later, Huang and Ruth proposed [30, 32] a compact laser-electron storage ring (LESR) where radiative laser cooling is used to overcome the space charge

effects encountered in a medium energy circular machine for electron beam cooling or x-ray generation.

In this chapter we introduce the concept of radiative laser cooling in analogy to wiggler damping and investigate the basic principle of a laser-electron storage ring. The beam dynamics in such a storage ring are somewhat different than a normal storage ring because of the existence of radiative laser cooling and the significant space charge effects in the energy range we consider. We then discuss some basic configurations and illustrate the potential applications of the laser-electron storage ring as a compact electron damping ring and an intense x-ray lithography source.

5.1 Radiative Laser Cooling

Many schemes of laser-electron interaction have been proposed for various applications such as compact x-ray sources [74, 17, 41, 80], γ - γ colliders [65], and electron-beam diagnostics [67]. The basic principle is Compton (or Thomson) scattering off a high-energy electron beam with an intense laser pulse to produce the desired photon spectrum. Recent experiments at SLAC [9] and LBNL [60] have shown the practicality of such schemes. More recently, Telnov pointed out [75] that the process of laser-electron interaction is also a radiation damping process for the phase space of the electron beam and can be used to “cool” multi-GeV electrons for linear collider applications.

The motion of the electron in a laser field is equivalent to that in an undulator. Suppose the laser propagates in the $-z$ direction, then the laser field satisfying the wave equation is

$$\mathbf{E} = -\mathcal{E}_0 \hat{\mathbf{x}} e^{-ik_L z - i\omega_L t}, \quad \mathbf{B} = \frac{1}{c}(-\hat{\mathbf{z}} \times \mathbf{E}), \quad (5.1)$$

where $k_L = \omega_L/c = 2\pi/\lambda_L$, and λ_L is the laser wavelength. An electron traveling along $z' = \beta ct$ direction makes an angle θ_e with the z axis prior to the interaction (Fig. 5.1), the electron “sees” the electric and magnetic fields as

$$\mathbf{E} = -\mathcal{E}_0 \hat{\mathbf{x}} e^{-ik_L z' \cos \theta_e - ik_L z' / \beta}, \quad \mathbf{B} = \frac{\mathcal{E}_0}{c} \hat{\mathbf{y}} e^{-ik_L z' \cos \theta_e - ik_L z' / \beta}, \quad (5.2)$$

Figure 5.1: The coordinates for laser-electron interaction.

The motion of the electron is governed by the Lorentz force

$$e(\mathbf{E} + \mathbf{v} \times \mathbf{B}) = -e\mathcal{E}_0(1 + \beta \cos \theta_e) \hat{\mathbf{x}} \exp \left[-i \left(\cos \theta_e + \frac{1}{\beta} \right) k_L z' \right]. \quad (5.3)$$

This force can be also produced by a magnetic field of the form $B_u \sin(k_u z') \hat{\mathbf{y}}'$ with

$$B_u = \frac{\mathcal{E}_0}{c}(1 + \beta \cos \theta_e), \quad k_u = k_L \left(\cos \theta_e + \frac{1}{\beta} \right). \quad (5.4)$$

Thus, the laser field acts like a static wiggler or undulator prescribed by Eq. (5.4). The scattered photon spectrum from the laser-electron interaction can be viewed as undulator radiation which has been discussed in Section 3.1.5.

Radiative laser cooling of electron beams is then very similar to wiggler damping [78]. When an electron counter-propagates through an intense laser pulse, it radiates energy in the form of scattered photons. Taking $\beta \simeq 1$ and $\theta_e = 0$ in Eq. (5.4), we have

$$B_u = \frac{2}{c}\mathcal{E}_0 = \frac{2}{c}\sqrt{2Z_0 I}, \quad (5.5)$$

$$k_u = 2k_L \quad \text{or} \quad \lambda_u = \frac{\lambda_L}{2}, \quad (5.6)$$

where I is the laser intensity, and $Z_0 = (c\epsilon_0)^{-1} = 377 \, \Omega$ is the free space impedance. The radiated power is given by Eq. (3.107):

$$P_\gamma = \frac{4\pi\epsilon_0}{3} r_e^2 c^3 \gamma^2 B_u^2 = \frac{32\pi}{3} r_e^2 \gamma^2 I, \quad (5.7)$$

On average, the electron loses momenta in all three degrees of freedom to the scattered photons, so that both the transverse position and the direction does not change. Thus, the transverse normalized emittances damp proportionally to the energy decrement. If the initial energy and the initial transverse normalized emittance are E_0 and ε_{n0} , then we have

$$\varepsilon_n = \frac{E}{E_0} \varepsilon_{n0} < \varepsilon_{n0} \quad \text{for } E < E_0. \quad (5.8)$$

In Ref. [75], Telnov estimated that a 5 GeV electron can lose 90% of its initial energy in one single passage of a laser pulse with a flash energy of a few Joules. Thus, the normalized transverse emittances (in both x and y directions) of the electron beam would be reduced by a factor of 10. However, the energy spread induced in the process is quite large (more than 10%), and long sections of linac with a large energy gain are required to re-accelerate the beam back to its initial high energy. To significantly reduce the emittance, multiple cooling stages with special focusing systems would be necessary. Thus, this scheme does not seem very practical.

5.2 Beam Dynamics in a LESR

In this section we study a laser-electron storage ring (LESR) [32] where radiative laser cooling (RLC) is used to overcome the intrabeam scattering (IBS) effect [53] encountered in a circular machine when the beam energy is only a few MeV up to a few hundred MeV. The LESR makes use of both electron beam storage ring technology as well as laser developments. The basic idea is shown in Fig. 5.2. An electron beam is injected into a storage ring and at the same time an intense laser pulse is built up inside a high-finesse optical resonator. The laser light path is chosen to match exactly the time it takes for the electron to circulate once around the ring so that a focused electron beam repeatedly encounters the light pulse at the focus of the resonator each turn. Normally, in the absence of the laser the electron beam would damp at the rate determined by the time it takes to radiate its complete energy in the bending magnets in the ring. In the LESR, the laser pulse acts like an extremely strong damping wiggler or undulator, and the fast radiative laser cooling leads to a very low

Figure 5.2: The schematic diagram of a laser-electron storage ring.

emittance beam for very moderate electron energy (around 100 MeV). As the beam circulates around the ring, the lost energy is restored by an RF accelerating system, as in a normal storage ring. This cooling effect can be also utilized as a stabilization mechanism to maintain a highly intense bunch of electrons for Compton scattering, even when the energy range of these electrons is less than 10 MeV. Therefore, such a compact LESR can be configured either for the production of low emittance electron beams or as a high intensity x-ray source.

5.2.1 Damping and Excitation in a Laser Field

For electrons in the energy range of a few MeV to a few hundred MeV, the normal radiation damping and quantum excitation from the bending magnets is negligible compared with those from the laser field. Thus, the central part of this device is the interaction between the electron and the laser beams. To illustrate the underlying physical effects, let us consider a diffraction limited laser beam that has a Gaussian

profile:

$$I(x, y, z, t) = I_0 \exp \left[-\frac{(z + ct)^2}{2\sigma_L^2} - \frac{x^2 + y^2}{2\sigma_w^2} \right], \quad (5.9)$$

where I_0 is the peak intensity, σ_L is the RMS laser pulse length, and σ_w is the RMS transverse size (one half of the waist in the laser terminology [68]). Suppose that the laser pulse length is short compared with the Rayleigh range of the optical resonator Z_R . We can then neglect the longitudinal variation of σ_w at the focus of the resonator when interacting with the electron beam (see Fig. 5.3). Thus, we have [68]

$$\sigma_w = \sigma_{w0} \sqrt{1 + \frac{z^2}{Z_R^2}} \simeq \sigma_{w0} = \sqrt{\frac{Z_R \lambda_L}{4\pi}}. \quad (5.10)$$

Similarly, we assume that the electron pulse length is much smaller than the beta function at the interaction region. Electron trajectories can then be assumed to be parallel to the z -axis. The trajectory of a particular electron is

$$x = x_i, \quad y = y_i, \quad z = z_i + ct. \quad (5.11)$$

The intensity “felt” by this electron as a function of time is then

$$I_i(t) = I_0 \exp \left[-\frac{(z_i + 2ct)^2}{2\sigma_L^2} - \frac{x_i^2 + y_i^2}{2\sigma_{w0}^2} \right]. \quad (5.12)$$

Insert this into Eq. (5.7) and integrate the radiated power over time, we obtain the energy loss of this electron after passing through the laser pulse

$$\begin{aligned} (\Delta E)_i &= \int P_\gamma^i dt = \frac{32\pi}{3} r_e^2 \gamma^2 \int I_i(t) dt \\ &= \frac{32\pi}{3} r_e^2 \gamma^2 \frac{I_0}{2c} \exp \left[-\frac{x_i^2 + y_i^2}{2\sigma_{w0}^2} \right] \int \exp \left[-\frac{(z_i + 2ct)^2}{2\sigma_L^2} \right] d(2ct) \\ &= (\Delta E)_0 \exp \left[-\frac{x_i^2 + y_i^2}{2\sigma_{w0}^2} \right]. \end{aligned} \quad (5.13)$$

We have assumed that the energy loss is small compared with the energy of the electron itself so that γ is approximately constant during the interaction, and that the maximum energy loss is

$$(\Delta E)_0 = \frac{32\pi}{3} r_e^2 \gamma^2 \frac{\sqrt{2\pi}\sigma_L}{2c} I_0. \quad (5.14)$$

Figure 5.3: The laser-electron interaction region.

We can also define a laser flash energy as

$$E_L = \int \int \int I(x, y, z, t) dx dy dt = I_0 2\pi \sigma_{w0}^2 \frac{\sqrt{2\pi} \sigma_L}{c}, \quad (5.15)$$

from which we can write Eq. (5.14) as

$$(\Delta E)_0 = \frac{32\pi}{3} r_e^2 \gamma^2 \frac{E_L}{4\pi \sigma_{w0}^2} = \frac{32\pi}{3} r_e^2 \gamma^2 \frac{E_L}{Z_R \lambda_L}. \quad (5.16)$$

Let n_d be the minimum number of turns needed to damp away the electron's initial energy E_0 . In practical units, we can write

$$n_d \equiv \frac{E}{(\Delta E)_0} \simeq \frac{1.6 \times 10^5 \lambda_L [\mu\text{m}] Z_R [\text{mm}]}{E_L [\text{J}] E_0 [\text{MeV}]}. \quad (5.17)$$

As an example, with the laser energy $E_L \simeq 1$ J and wavelength $\lambda_L \simeq 1$ μm , the Rayleigh range $Z_R \simeq 1$ mm, and the electron energy 100 MeV, it takes at least $n_d = 1600$ turns for the electron to damp one e-folding, which is still much faster than that in the SLC damping ring.

If T_0 is the revolution time of the electron beam around the ring, the average damping rate to the transverse action is then given by

$$\Gamma_{x,y}^i \equiv -\frac{1}{J_{x,y}^i} \left\langle \frac{dJ_{x,y}^i}{dt} \right\rangle = \frac{\langle \Delta E \rangle_i}{E_0 T_0} = \Gamma_L \exp \left[-\frac{x_i^2 + y_i^2}{2\sigma_{w0}^2} \right], \quad (5.18)$$

where $\Gamma_L = (\Delta E)_0 / E_0 T_0$ is the characteristic laser damping rate. Thus, the individual transverse damping rates are slightly different for electrons with different betatron amplitudes.

The laser-electron interaction also gives rise to quantum excitation of the transverse emittances. The quantum statistical nature of photon scattering can in principle have two effects on the transverse dynamics of the electron, a random displacement of the reference orbit that depends on the energy of the electron (the dispersion effect), and a sudden change of direction if the scattered photon does not exactly follow the electron motion (the opening-angle effect). Since the interaction region is designed to be free of dispersion, the only dispersion comes from the laser wiggler. The differential equation for the dispersion function in the laser wiggler is

$$\eta'' = \frac{1}{\rho} = \frac{1}{\rho_u} \sin(k_u z), \quad (5.19)$$

where $\rho_u = \gamma m_e c / e B_u = 1 / (k_u \theta_d)$, and θ_d is the deflection angle. Thus, we obtain

$$\begin{aligned} \eta' &= -\frac{1}{k_u \rho_u} \cos(k_u z) = -\theta_d \cos(k_u z), \\ \eta &= \frac{1}{k_u^2 \rho_u} [1 - \sin(k_u z)] = \frac{\theta_d}{k_u} [1 - \sin(k_u z)]. \end{aligned} \quad (5.20)$$

The dispersion effect is characterized by the $\mathcal{H}$ function defined in Section 4.1.2. For the laser wiggler, we have $\beta_x \simeq \beta_x^* \gg \lambda_u = \lambda_L / 2$, $\beta'_x \simeq 0$ at the interaction region, so that

$$\mathcal{H} = \frac{1}{\beta_x} [\eta^2 + (\beta_x \eta' - \frac{\beta'_x}{2} \eta)^2] \simeq \beta_x^* \eta'^2 = \beta_x^* \theta_d^2 \cos^2(k_u z). \quad (5.21)$$

Thus, the growth of the horizontal action due to the dispersion effect is

$$\delta J_x = \frac{p_0 \beta_x^*}{2} \theta_d^2 \left(\frac{\hbar \omega}{E_0} \right)^2. \quad (5.22)$$

When the scattered photon does not exactly follow the direction of the electron, the electron receives a transverse recoil from the scattered photon and changes its direction by $\delta \theta_e = -\hbar \omega \sin \theta / E_0 \simeq -\hbar \omega \theta / E_0$, with $\theta \sim 1/\gamma$ being the opening angle of the scattered photon (Fig. 5.3). Project this change onto the x and y planes, the resulting growths of the transverse actions due to this opening angle effect are

$$\delta J_x = \frac{p_0 \beta_x^*}{2} \theta^2 \cos^2 \phi \left(\frac{\hbar \omega}{E_0} \right)^2, \quad \delta J_y = \frac{p_0 \beta_y^*}{2} \theta^2 \sin^2 \phi \left(\frac{\hbar \omega}{E_0} \right)^2, \quad (5.23)$$

where $\beta_{x,y}^*$ is the electron beta function in the x or y direction at the laser-electron interaction region (IP), and ϕ is the azimuthal angle of the scattered photon.

The total growth of the horizontal action is the sum of two effects. However, since the undulator parameter (or the equivalent laser parameter)

$$K_u = \gamma\theta_d = eB_u/k_um_ec \simeq 8.55 \times 10^{-10} \sqrt{I[\text{W}/\text{cm}^2]} \lambda_L [\mu\text{m}] \quad (5.24)$$

is much less than 1 unless $I \sim 10^{18} \text{ W}/\text{cm}^2$, the deflection angle θ_d under consideration is always much smaller than the opening angle of the scattered photons $1/\gamma$. We can then treat the laser pulse as a weak undulator and neglect quantum excitation due to the dispersion effect compared to the opening angle effect. The power radiated by electrons in a weak undulator is given by Eq. (3.106). Combining with Eq. (3.107) and integrating over the time of interaction, we have the total number of scattered photons by the i^{th} electron into a given bandwidth $d\omega$:

$$n_\gamma^i(\omega) \equiv \frac{1}{\hbar\omega} \left| \frac{dE}{d\omega} \right| = \frac{3\langle\Delta E\rangle_i}{\hbar\omega_1^2} \left[1 - 2\left(\frac{\omega}{\omega_{10}}\right) + 2\left(\frac{\omega}{\omega_{10}}\right)^2 \right]. \quad (5.25)$$

where $\langle\Delta E\rangle_i$ is calculated in Eq. (5.13), and $\omega_{10} = 2\gamma^2\omega_u = 8\pi\gamma^2c/\lambda_L$ is the maximum frequency at the forward direction determined by Eq. (3.84). The scattered photon frequency ω and the scattering angle θ of the photon with respect to the direction of the electron trajectory are related through

$$\omega = \frac{\omega_{10}}{(1 + \gamma^2\theta^2)}. \quad \text{or} \quad \theta^2 = \frac{1}{\gamma^2} \left(\frac{\omega_{10}}{\omega} - 1 \right). \quad (5.26)$$

Following Section 4.1.1 and with the help of Eq. (5.26), we can integrate the photon distribution over the frequency range to obtain the expected quantum excitation of the transverse actions per turn

$$\langle\Delta J_{x,y}^i\rangle = \frac{p_0\beta_{x,y}^*}{2} \int_0^{\omega_{10}} d\omega \left(\frac{\hbar\omega}{E_0} \right)^2 \frac{\theta^2}{2} n_\gamma^i(\omega) = \frac{3\pi}{5} \frac{\hbar}{\lambda_L} \frac{\langle\Delta E\rangle_i}{E_0} \beta_{x,y}^*. \quad (5.27)$$

Since quantum excitation from the rest of the storage ring is negligible at the energy range we consider, the average quantum excitation rate for the i^{th} electron becomes

$$\left\langle \frac{dJ_{x,y}^i}{dt} \right\rangle_{\text{QE}} = \frac{\langle\Delta J_{x,y}^i\rangle}{T_0} = \frac{3\pi}{5} \frac{\hbar}{\lambda_L} \frac{\langle\Delta E\rangle_i}{E} \frac{\beta_{x,y}^*}{T_0}. \quad (5.28)$$

We see that both the damping rate Eq. (5.18) and the excitation rate Eq. (5.28) are proportional to $\langle \Delta E \rangle_i$, which depends on $J_{x,y}^i$ nonlinearly. The balance between these two rates cancels out the nonlinearity and leads to a minimum normalized transverse emittances for the electron beam

$$(\varepsilon_{x,y}^n)_{\min} = \frac{3\pi}{5} \frac{\lambda_c}{\lambda_L} \beta_{x,y}^*, \quad (5.29)$$

where $\lambda_c = \hbar/m_e c$ is again the Compton wavelength of the electron. These minimum normalized transverse emittances are independent of the energy and only depend on the laser wavelength and the beta function at IP. From Eq. (5.29), we conclude that in order to generate very low emittance electron beams, a reasonably small $\beta_{x,y}^*$ is necessary. For example, $\lambda_L \simeq 1 \mu\text{m}$ and $\beta_{x,y}^* \simeq 1 \text{ cm}$ set a lower limit on the normalized transverse emittances at about $7.3 \times 10^{-9} \text{ m}$, far below any known sources. In addition, a small $\beta_{x,y}^*$ is also necessary to focus the electron beam at the interaction region in order to match the small focal spot size of the laser beam.

In the longitudinal dimension, the energy spread can be increased by the energy fluctuation of the scattered photons. Following Section 4.1.3, the expected rate of quantum excitation to the peak energy spread A_δ

$$\left\langle \frac{d(A_\delta^2)}{dt} \right\rangle_{\text{QE}} = \frac{1}{T_0} \int_0^{\omega_{10}} d\omega \left(\frac{\hbar\omega}{E_0} \right)^2 n_\gamma(\omega) = \frac{7}{10} \frac{\hbar\omega_{10} \langle \Delta E \rangle_i}{T_0 E_0^2}. \quad (5.30)$$

However, the energy spread is also damped as in a normal storage ring (see Eq. (4.48)):

$$\frac{1}{A_\delta^2} \left\langle \frac{d(A_\delta^2)}{dt} \right\rangle = -\frac{2}{T_0} \frac{\langle \Delta E \rangle_i}{E_0} \equiv -\Gamma_s^i. \quad (5.31)$$

The RMS energy spread is equal to $1/\sqrt{2}$ of the peak energy spread, which reaches the minimum when the damping is balanced by the quantum excitation:

$$(\sigma_\delta)_{\min} = \frac{1}{\sqrt{2}} A_\delta = \sqrt{\frac{7\pi}{5} \frac{\lambda_c}{\lambda_L} \gamma_0}. \quad (5.32)$$

Thus, the minimum RMS energy spread obtainable in a LESR depends weakly on the laser wavelength and the energy of the electrons. For example, when 100 MeV electrons interact with $1 \mu\text{m}$ wavelength lasers, a minimum RMS energy spread is

about 1.8%. In spite of the fact that the energy spread is relatively large due to the hard photons scattered, it can actually help spread out the beam in the dispersive regions around the storage ring to reduce the Coulomb interaction between electrons. Nevertheless, the chromaticity in this storage ring must be well corrected for beam stability [78]. In addition, since the RMS bunch length σ_s is related to the energy spread σ_δ by Eq. (4.52), we conclude that a high frequency RF cavity is needed to control the electron bunch length σ_s and the normalized longitudinal emittance $\varepsilon_s^n = \gamma\sigma_\delta\sigma_s$. Moreover, if we want to store the electron beam in the storage ring for a long period of time, the RF voltage must also be high enough to obtain a sufficient RF momentum acceptance [78]. We postpone the numerical examples to Section 5.3.

5.2.2 Space Charge Effects

In addition to quantum excitation, intrabeam scattering provides additional diffusion in the 6-dimensional phase space of the electron beam. Intrabeam scattering is the result of multiple small-angle Coulomb collisions between particles in the beams leading to a continuous increase of beam dimensions and to a reduction of the beam lifetime when the particles hit the aperture [52]. For a bunched Gaussian beam with N_e number of electrons, the intrabeam scattering growth rate to the oscillation amplitude, averaged over the whole storage ring, can be cast into the following forms [53]:

$$\begin{aligned} \frac{1}{\tau_s} &= \left\langle A \frac{\sigma_h^2}{\sigma_\delta^2} f(a_1, a_2, a_3) \right\rangle_s \\ \frac{1}{\tau_x} &= \left\langle A \left[f\left(\frac{1}{a_1}, \frac{a_2}{a_1}, \frac{a_3}{a_1}\right) + \frac{\eta^2 \sigma_\delta^2}{\sigma_x^2} f(a_1, a_2, a_3) \right] \right\rangle_s \\ \frac{1}{\tau_y} &= \left\langle A f\left(\frac{1}{a_2}, \frac{a_1}{a_2}, \frac{a_3}{a_2}\right) \right\rangle_s \end{aligned} \quad (5.33)$$

with

$$A = \frac{r_e^2 c N_e}{64\pi^2 \sigma_s \sigma_p \varepsilon_x^n \varepsilon_y^n \gamma^2}, \quad (5.34)$$

$$\frac{1}{\sigma_h^2} = \frac{1}{\sigma_\delta^2} + \frac{\eta^2}{\sigma_x^2}. \quad (5.35)$$

The function f is given by

$$f(a_1, a_2, a_3) = 8\pi \int_0^1 \left[\ln \left(\frac{c^2}{2} \left(\frac{1}{\sqrt{P}} + \frac{1}{\sqrt{Q}} \right) \right) - 0.577... \right] \frac{1-3x^2}{\sqrt{PQ}} dx, \quad (5.36)$$

where

$$P = a_1^2 + (1 - a_1^2)x^2, \quad Q = a_2^2 + (1 - a_2^2)x^2, \quad (5.37)$$

and

$$a_1 = \frac{\sigma_h}{\gamma\sigma'_x}, \quad a_2 = \frac{\sigma_h}{\gamma\sigma'_y}, \quad a_3 = \sigma_h \sqrt{\frac{\sqrt{2\pi}\sigma_y}{r_e}}. \quad (5.38)$$

Since the intrabeam scattering growth times are complicated functions of the phase space properties of the electron beam, in general, the equilibrium emittances are determined by the following three coupled equations:

$$\left[\frac{2}{\tau_j} - \Gamma_j \right] \varepsilon_j^n + \left\langle \frac{d\varepsilon_j^n}{dt} \right\rangle_{QE} = 0, \quad (5.39)$$

where $j = x, y, s$ stands for the horizontal, vertical and longitudinal direction respectively. The second and the third term in Eq. (5.39) represent the rates of radiative laser cooling and quantum excitation calculated in Section 5.2.1. Because each term in Eq. (5.39) can become nonlinear for large oscillation amplitudes, the equilibrium distribution of the electron beam can be very complicated and will in general have a nearly Gaussian core with long tails [56]. Nevertheless, if we restrict ourselves to consider only small oscillation amplitudes, we can then apply the above linear theories of laser-electron interaction and intrabeam scattering to calculate the core equilibrium emittance in order to illustrate the parameter ranges and some potential applications in the next section.

While intrabeam scattering depends upon the 6-dimensional phase space density parameter A defined in Eq. (5.34) and can be always counterbalanced by radiative laser cooling at a certain phase space density, the space charge induced tune shift must be kept small (usually less than a quarter) in order not to have beam loss [77]. Suppose that the ring is basically two half circles with two small straight sections

for the RF cavity and the laser-electron interaction region (see Fig. 5.2). Using the smooth approximation, we have for the maximum space charge incoherent tune shift around the ring [55]

$$\Delta\nu_{x,y} = -\frac{N_e r_e \bar{\beta}_{x,y} R}{\sqrt{2\pi} \gamma^3 \sigma_s} \frac{1}{\bar{\sigma}_{x,y}(\bar{\sigma}_x + \bar{\sigma}_y)}, \quad (5.40)$$

where N_e is the number of electrons in the bunch, R is the average radius, $\bar{\beta}_{x,y}$ and $\bar{\sigma}_{x,y}$ are the average beta function and the average beam size in the x or y direction. Suppose the dispersion exists only in the x direction (with the average value being $\bar{\eta}$), then we have

$$\bar{\sigma}_x = \sqrt{\frac{\varepsilon_x^n}{\gamma} \bar{\beta}_x + \bar{\eta}^2 \sigma_\delta^2}, \quad \bar{\sigma}_y = \sqrt{\frac{\varepsilon_y^n}{\gamma} \bar{\beta}_y}. \quad (5.41)$$

Because of the relatively large energy spread, the beam size in the x direction is increased in the dispersive region of the ring; thus, the space charge incoherent tune shift can be controlled (see the numerical examples in Section 5.3).

5.2.3 X-ray Generation

Recent progress in high peak and high average power laser development has attracted a growing number of interests in generating x-rays by Compton (or Thomson) backscattering an intense laser pulse off a high energy electron beam [74, 17]. From Eq. (5.26), the backscattered x-ray wavelengths are given by

$$\lambda = (1 + \gamma^2 \theta^2) \frac{\lambda_L}{4\gamma^2}. \quad (5.42)$$

These x-rays are tunable, collimated within an opening angle of $1/\gamma$, and nearly monochromatic.

However, these Compton sources are somewhat limited by the relatively low x-ray yields. It is well known that the cross section of Compton scattering is quite small, and is approximately given by the Thomson cross section when the energy of the scattered photon is much less than the electron energy [35]:

$$\sigma_T = \frac{8\pi}{3} r_e^2 = 6.66 \times 10^{-29} \text{m}^2. \quad (5.43)$$

If we let N_e electrons encounter N_L photon with a common Gaussian RMS transverse size σ_w at an interaction rate f_I , then the total number of scattered x-ray photons per unit time (or the average x-ray flux) is given by [78]

$$\dot{N}_\gamma = \frac{\sigma_T}{4\pi\sigma_w^2} N_e N_L f_I \quad (5.44)$$

Even with the state-of-art laser technology [74] and the development of photon storage systems [17], the x-ray flux has been limited because of either low electron intensity or low repetition rate of existing electron accelerators.

Nevertheless, in a laser-electron storage ring configuration we discussed here, the interaction rate is naturally high due to the circulating nature and the compactness of storage ring. More importantly, the laser-electron interaction also provides a very fast cooling mechanism for the normalized emittances of the electrons, and can be used to counterbalance the strong intrabeam scattering effect when a dense electron beam is stored. Following Eq. (5.44), we can determine the x-ray flux as a function of laser and resonator parameters. Assume that the average power of the laser is P_L , and the total mirror reflectivity of the optical resonator is R_F , so that the average power inside the resonator can be as high as $P_L/(1 - R_F)$. We can use Eq. (5.10) for the transverse beam size and the relation

$$N_L f_I = \frac{P_L}{\hbar\omega(1 - R_F)}, \quad (5.45)$$

then Eq. (5.44) for the total number of x-ray photons produced per unit time can be written as

$$\dot{N}_\gamma = \frac{4}{3} N_e \frac{r_e^2}{Z_R \hbar c} \frac{P_L}{(1 - R_F)}, \quad (5.46)$$

with $\hbar c = 1.97 \times 10^{-7}$ eVm. As we will see from the explicit example in Section 5.3.2, the LESR provides both an intense electron beam and a high interaction rate, the resulting x-ray flux is significantly enhanced over previous proposals [74, 17].

5.3 LESR Configurations and Applications

Two configurations will be discussed to demonstrate some LESR design considerations for various applications. One is a transient mode device that is capable of producing

very low emittance electron beams. The other is a steady state operation for the generation of intense soft x-rays. Table 5.1 lists some typical parameters. In both configurations, we assume that the two half circles of storage rings consist of identical FODO cells, and that the Fabry-Perot resonators are made of mirrors with total reflectivity $R_F = 99.99\%$ (finesse $F \simeq \pi/(1 - R_F) \simeq 3.14 \times 10^4$). To simplify the intrabeam scattering calculations, we consider a round beam in the transverse dimensions induced by the $x - y$ coupling for both cases.

5.3.1 A Compact Damping Ring

In the transient mode, a high peak power (200 GW), pulsed (10 psec) laser pulse is built up inside the resonator. Suppose that the electron beam (100 MeV) is injected into this ring with both normalized transverse emittances initially at 1×10^{-5} m. The laser pulse scatters off the electron bunch each round trip with little change of intensity because of negligible laser depletion and internal loss. From Table 5.1, the electron beam damps rapidly (within 5 damping times) to the equilibrium transverse normalized emittances 1×10^{-7} m determined by Eq. (5.39). At the same time, very bright, energetic x-rays are also produced. The electron beam is then extracted from this ring. A new laser pulse can be built up, and a new electron beam can be injected to repeat the process. The normalized transverse emittances achieved in the LESR are much smaller than those of SLC damping ring [20], and are also well below present RF gun technology [51]. Since the relative energy spread can be made much smaller by adiabatic acceleration, such a low emittance beam might be suitable for x-ray free electron lasers, linear colliders, and other advanced accelerator experiments.

Table 5.1: Laser-Electron Storage Ring Parameters

LESR mode	transient	steady state
Laser and resonator parameters		
Wavelength [μm]	1	1
Flash energy in the resonator	2 J (initial)	20 mJ (steady)
Laser pulse length [mm]	3	1
Rayleigh range [mm]	5	8
Focal transverse RMS size [μm]	20	25
Electron storage ring parameters		
Energy [MeV]	100	8
Number of electrons	1.3×10^{10}	1.1×10^{10}
Average ring radius [m]	1	0.5
Horizontal/vertical tune	~ 10	~ 10
Energy loss per turn	25 KeV	1 eV
Trans. damping time	80 μsec	80 msec
Equil. energy spread	1.8% ¹	2.3% ²
RF frequency [MHz]	2856	1428
RF peak voltage	1 MV	60 KV
RF momentum acceptance	10%	23%
RMS bunch length [mm]	4.2	6.6
Beta function at IP	1 cm	2 mm
Equil. norm. long. emit. [mm]	16	2.4
Equil. norm. trans. emit. [m]	1×10^{-7}	6×10^{-6}
Max. space charge tune shift	0.012	0.19
X-ray parameters		
Wavelength	6.25 pm	1 nm
Photon energy [keV]	200	1.24
Photon flux [sec^{-1}]	2.6×10^{20} (peak)	9.1×10^{14} (average)

¹Dominated by quantum excitation²Dominated by intrabeam scattering

5.3.2 An Intense X-ray Source

For the steady state configuration, in order to sustain the energy level of the laser pulse in the Fabry-Perot resonator, a 200 W average power, mode-locked Nd:YAG laser (96 MHz pulse train) is resonantly coupled to the resonator. As we can see from Table 5.1, when the accumulated laser pulse scatters off an 8 MeV electron bunch in the resonator, the interaction not only gives rise to soft x-rays with wavelength around 1 nm, but also provides a cooling and stabilization mechanism to maintain the intense compact bunch (1.1×10^{10} electrons) so that all electrons participate in each laser pulse collision. As a result of radiative laser cooling, an average flux of 9.1×10^{14} x-ray photons per second is generated over an opening angle ± 64 mrad. The intensity of this x-ray source is orders of magnitude higher than other schemes based on Compton scattering [74, 17]. If the laser beam is slightly tilted with respect to the electron beam direction at the interaction region (Fig. 5.4), one can collect the scattered x-rays in the forward direction from 0 to -25 mrad through a thin Beryllium window that is transparent to x-rays. From Eq. (5.42), the bandwidth of the collected x-rays is

$$\frac{\Delta\lambda}{\lambda} = (\gamma\Delta\theta)^2 = 16\%, \quad (5.47)$$

and the wavelengths of these x-rays are between 1.2 nm and 1 nm. Thus, at a distance 1 m away from the interaction point, a field size of 25 mm in diameter can be uniformly ($< 5\%$ variation) illuminated. The power density is estimated to be on the order of 10 mW/cm², which is adequate for high throughput x-ray lithography [2].

Compared with synchrotron based x-ray lithography [2], the x-ray source based on the LESR is naturally concentrated around the desired x-ray lithography wavelength (1 nm) instead of a broad band spectrum. The necessary electron energy is about two orders of magnitude lower than that of synchrotrons. Thus, the device can be made extremely compact, and both the electron injector and the radiation shielding are much easier. It is also conceivable to orient the whole system in the vertical

Figure 5.4: The geometry for x-ray generation.

direction so that traditional wafer production facilities could be adapted to XRL manufacturing.

The x-ray source we propose here is completely tunable and can be extended to cover both soft x-ray and hard x-ray ranges. We choose to use solid-state lasers in the example because of both high peak and high average power developments. Nevertheless, recent progress in terawatt picosecond CO₂ laser technology [54] opens up the possibility that the LESR could be built with a CO₂ laser (available for an average power level greater than 1 KW). Having an order of magnitude longer laser wavelength means that the accessible wavelength of the scattered photons may be extended to softer x-rays (between 1 nm to 10 nm), and even into the extreme ultraviolet (EUV) range (above 10 nm). On the other hand, by raising the electron energy in the storage ring, bright and energetic x-rays with energies up to a few hundred KeV can be generated [3]. With the flexibility in wavelength, the high-intensity x-ray source described here may have many industrial and medical applications such as lithography, radiography, and angiography.

Chapter 6

Conclusions and Future Work

Beam physics is a very diverse field, but the underlying motivation for most research in this field can be summarized to be the optimization of three important parameters that globally characterizes a particle beam: energy, intensity and emittance. The emphasis on each of these three parameters may be different depending upon the potential applications of such a beam. However, none of them can be ignored in the design of particle accelerators.

In this dissertation, we have attempted to address some fundamental aspects of generating very low emittance electrons or positron beams. In chapter 4, we have systematically examined radiation damping and quantum excitation in various accelerator systems. We have showed that radiation damping in focusing systems is fundamental different from that in conventional storage rings. In a straight, continuous focusing channel, the damping rate of the transverse normalized emittance is independent of an electron's energy, and no quantum excitation is induced during the radiative process. In principle, this absolute damping effect leads to the existence of a transverse ground state to which the electron inevitably decays and yields the fundamental emittance, the Compton wavelength of the electron. In a smooth, periodic focusing channel, quantum excitation can exist because of the periodicity of the lattice. However, the dominate effect is radiation damping due to the average focusing field, and the equilibrium transverse normalized emittance is no more than a few Compton wavelength. In a bent focusing system when the radiation formation

length is comparable to the transverse betatron wavelength, quantum excitation is exponentially suppressed by the focusing environment, and hence the Compton wavelength can be arbitrarily approached for the transverse normalized emittance of the beam.

Nevertheless, radiation damping due to the focusing field is a very slow process except in certain extreme situations such as in crystal channels. Since quantum excitation is suppressed in a focusing environment, any other source of excitation must also be taken into account to determine the actual equilibrium beam emittance. Generally speaking, there are two categories of such excitation mechanism. The first category is thermal excitation that “heats up” the beam. In fact, we have already studied the “quantum heating” due to the quantum nature of radiation. A true thermal heating effect is due to blackbody radiation [47] of the lattice temperature. Here the effect can be described by Compton (or Thomson) scattering of the electron with the blackbody photons, which can be treated similarly to the laser-electron interaction in Chapter 5. Other thermal-like effects including lattice imperfection, machine errors and jitters must also be investigated in order to set tolerances for a focusing-dominated damping ring. These effects have yet to be studied and depend upon the details of the design considered.

Another category of excitation mechanism is intensity-related collective growth such as space charge, intrabeam scattering, ion trapping, and wakefields. Together, they will set a practical limit on the intensity of an ultra-low emittance electron beam if such a focusing device were realized. A very important and challenging question is the issue of beam crystallization [76]. When conditions are right, Coulomb force between the particles can cause an ultra-low emittance particle beam to crystallize. Therefore, particles within a beam are essentially screened from the interaction of each other electromagnetically, and the intensity limitation due to space charge forces and intrabeam scattering can virtually be removed.

One attempt to reach the intensity frontier has been illustrated in Chapter 5, where we have proposed to use fast radiative laser cooling to counterbalance intrabeam scattering in a relatively low energy electron storage ring. The laser-electron storage ring (LESR) seems to be a very promising idea to generate a low emittance electron

beam with a practically interesting intensity. In addition, the x-rays scattered by the repetitive laser-electron interaction tend to be very intense, and very flexible in wavelength. The compactness of such an intense x-ray source makes it attractive for many industrial and medical applications.

Although we have studied the basic beam dynamics in a laser-electron storage ring, the parameters of such a storage ring enter an entirely new regime, hence many nonlinear and collective effects associated with storage rings have to be re-visited. The LESR configuration and parameters have yet to be optimized through detailed design simulation. Many technological problems, especially those associated with the laser and the optical resonator, must be resolved before such a device can be realized.

In summary, we have found two new approaches to generate very low emittance electron beams. One is the suppression of quantum excitation through focusing environment. This approach can in principle reach the fundamental beam emittance with probably a rather limited intensity. The other is the radiative laser cooling in a laser-electron storage ring, which provides rapid damping for a dense electron beam. Generation of low emittance electron beams is an interesting subject in its own right, and the two approaches discussed here may have potential applications in linear colliders, novel accelerators or light sources.

Appendix A

Transverse Dynamics in a Storage Ring

In this appendix, we review the linear theory of single particle transverse dynamics in a storage ring. Detailed derivations of the equations and discussions of the particle motion can be found in any textbook on particle accelerator physics. Here, we will describe the basic physics and provide the necessary definitions so that one can follow the body of this dissertation. In particular, we discuss the dispersion function and the betatron motions using the Hamiltonian approach. All materials presented in this appendix can be found in Ref. [57] and Ref. [46].

A.1 Coordinate System

We use the Frenet-Serret curvilinear coordinate system (x, s, y) based on a closed planar reference curve (Fig. A.1). This reference curve is taken to be the closed trajectory of a particle with some reference momentum p_0 in the guiding magnetic field. $\rho(s)$ is the local radius of curvature. Let s measure the arc length along the curve from a fixed origin somewhere on the curve, x and y measures the horizontal and vertical deviations from the reference orbit.

Figure A.1: The Frenet-Serret curvilinear coordinate system (x, s, y) .

A.2 Transverse Hamiltonian

The motion of a charged particle in an accelerator is governed by the Lorentz force equation

$$\frac{d\mathbf{P}}{dt} = e(\mathbf{E} + \mathbf{v} \times \mathbf{B}), \quad (\text{A.1})$$

where $\mathbf{P}$ is the relativistic kinetic momentum and $\mathbf{v}$ is the velocity. Expressing the electric and magnetic fields in terms of the vector and scalar potentials with

$$\mathbf{E} = -\nabla\Phi - \frac{\partial\mathbf{A}}{\partial t}, \quad \mathbf{B} = \nabla \times \mathbf{A}, \quad (\text{A.2})$$

the Hamiltonian that governs the motion of charged particle is given by

$$H = e\Phi + c[m_e^2 c^2 + (\mathbf{p} - e\mathbf{A})^2]^{1/2}, \quad (\text{A.3})$$

where $\mathbf{p} = \mathbf{P} + e\mathbf{A}$ is the canonical momentum.

In the absence of radiation and RF acceleration fields, the motion of the particle can be described by the following Hamiltonian:

$$H = c \left[m_e^2 c^2 + (p_x - eA_x)^2 + (p_y - eA_y)^2 + \frac{(p_s - eA_s)^2}{(1 + x/\rho)^2} \right]^{1/2}, \quad (\text{A.4})$$

$p_s = \mathbf{p} \cdot \hat{\mathbf{s}}(1 + x/\rho)$ is the canonical momentum conjugate to s , and $A_s = \mathbf{A} \cdot \hat{\mathbf{s}}(1 + x/\rho)$ is the canonical vector potential.

We consider a storage ring mainly consists of dipoles and quadrupoles to study the linear dynamics. The magnetic field in such a system is given by

$$\begin{aligned} B_y &= -B_0(s) + B_1(s)x + \dots, \\ B_x &= B_1(s)y. \end{aligned} \quad (\text{A.5})$$

The main bending field $B_0(s)$ is chosen so that a particle at the reference momentum p_0 will bend with a local radius of curvature $\rho(s)$, i. e.,

$$B_0 = \frac{p_0}{e\rho(s)}. \quad (\text{A.6})$$

The gradient of the magnetic field $B_1(s)$ can be scaled to obtain a focusing function

$$k_q(s) = \frac{eB_1(s)}{p_0} = \frac{B_1}{B_0\rho}. \quad (\text{A.7})$$

The vector potential that corresponds to the magnetic field is

$$\begin{aligned} A_x &= A_y = 0, \\ A_s &= -\frac{p_0}{e} \left[\frac{x}{\rho} + \left(\frac{1}{\rho^2} - k_q \right) \frac{x^2}{2} + k_q \frac{y^2}{2} \right]. \end{aligned} \quad (\text{A.8})$$

It is convenient to change the independent variable from t to s . This can be done by a canonical transformation which defines $(-p_s)$ as the new Hamiltonian, with $(t, -H)$ playing the role of the third coordinate and conjugate momentum:

$$\begin{aligned} \tilde{H} &= -p_s(x, p_x, y, p_y, t, -H) \\ &= -eA_s - \left(1 + \frac{x}{\rho}\right) \left[\frac{H^2}{c^2} - m_e^2 c^2 - p_x^2 - p_y^2 \right]^{1/2} \\ &\simeq -p + (p_0 - p) \frac{x}{\rho} + p_0 \left(\frac{1}{\rho^2} - k_q \right) \frac{x^2}{2} + \frac{p_x^2}{2p} + p_0 k_q \frac{y^2}{2} + \frac{p_y^2}{2p}. \end{aligned} \quad (\text{A.9})$$

Note that $p = (H^2/c^2 - m_e^2 c^2)^{1/2}$ is the total kinetic momentum of the particle, and that we keep terms up to the order of $(x/\rho)^2$ and $(p_{x,y}/p)^2$.

Since there is no time dependence in the Hamiltonian (no longitudinal acceleration), the total kinetic momentum p (or the energy H) is a constant of motion. In most situations, p is very close to the reference momentum p_0 . Thus, we can replace

p by p_0 in both $p_x^2/2p$ and $p_y^2/2p$ because the difference will be in higher order. This corresponds to neglecting the chromatic effect in the ring. We also neglect the vertical y dimensional terms since its treatment is similar to and simpler than the horizontal x dimension. After all these simplifications, our Hamiltonian is now taking the form

$$\hat{H}(x, p_x, t, -H) = -p + (p_0 - p)\frac{x}{\rho} + p_0 k_x \frac{x^2}{2} + \frac{p_x^2}{2p_0}, \quad (\text{A.10})$$

where $k_x(s) = 1/\rho(s)^2 - k(s)$ is periodic in s with the period equal to the circumference of the ring. The equation of motion can be found with the Hamilton's equation

$$x' = \frac{\partial \hat{H}}{\partial p_x} = \frac{p_x}{p_0}, \quad (\text{A.11})$$

$$p'_x = -\frac{\partial \hat{H}}{\partial x} = -p_0 k_x x + \frac{(p - p_0)}{\rho}, \quad (\text{A.12})$$

where prime denotes differentiation with respect to s . Equation (A.11) can be regarded as the definition of x' , sometimes called the angular divergence of the particle. Combining Eq. (A.11) and Eq. (A.12), we obtain

$$x'' + \frac{p_0}{p} k_x x = \frac{(p - p_0)}{p} \frac{1}{\rho}, \quad (\text{A.13})$$

This equation is called Hill's equation due to the periodicity of both $K_x(s)$ and $\rho(s)$. The particle trajectory is completely determined by this equation with proper initial conditions.

A.3 Dispersion Function

To remove the coupling term $(p_0 - p)x/\rho$ in H_2 , we perform a canonical transformation using the generating function

$$F_2(x, p_\beta, t, -H_1, s) = (x - x_\epsilon)(p_\beta + p_\epsilon) + \frac{x_\epsilon p_\epsilon}{2} + t(-H_1), \quad (\text{A.14})$$

and the transformation between $(x, p_x, t, -H)$ and $(x_\beta, p_\beta, t_1, -H_1)$ is

$$\begin{aligned}
x_\beta &= \frac{\partial F_2}{\partial p_\beta} = x - x_\epsilon, \\
p_x &= \frac{\partial F_2}{\partial x} = p_\beta + p_\epsilon, \\
t_1 &= \frac{\partial F_2}{\partial(-H_1)} = t + \frac{\partial(-x_\epsilon)}{\partial(-H_1)}(p_\beta + p_\epsilon) + x_\beta \frac{\partial(p_\epsilon)}{\partial(-H_1)} + \frac{\partial(x_\epsilon p_\epsilon/2)}{\partial(-H_1)}, \\
-H &= \frac{\partial F_2}{\partial t} = -H_1.
\end{aligned} \tag{A.15}$$

x_ϵ represents the off-momentum equilibrium orbit displacement and x_β represents the betatron motion around the equilibrium. The Hamiltonian is also transformed to

$$\begin{aligned}
\tilde{H} &= \hat{H} + \frac{\partial F_2}{\partial s} \\
&= -p + (p_0 - p) \frac{x}{\rho} + p_0 k_x \frac{(x_\beta + x_\epsilon)^2}{2} + \frac{(p_\beta + p_\epsilon)^2}{2p_0} \\
&\quad - \frac{\partial x_\epsilon}{\partial s} (p_\beta + p_\epsilon) + x_\beta \frac{\partial p_\epsilon}{\partial s} + \frac{\partial(x_\epsilon p_\epsilon/2)}{\partial s} \\
&= -p + (p_0 - p) \frac{x_\epsilon}{\rho} + p_0 k_x \frac{x_\epsilon^2}{2} + \frac{p_\epsilon^2}{2p_0} - \frac{\partial x_\epsilon}{\partial s} \frac{p_\epsilon}{2} + \frac{x_\epsilon}{2} \frac{\partial p_\epsilon}{\partial s} \\
&\quad + (p_0 - p) \frac{x_\beta}{\rho} + p_0 k_x x_\epsilon x_\beta + \frac{\partial p_\epsilon}{\partial s} x_\beta + \frac{p_\epsilon}{p_0} p_\beta - \frac{\partial x_\epsilon}{\partial s} p_\beta \\
&\quad + p_0 k_x \frac{x_\beta^2}{2} + \frac{p_\beta^2}{2p_0},
\end{aligned} \tag{A.16}$$

where $p = (H^2/c^2 - m_e^2 c^2)^{1/2} = (H_1^2/c^2 - m_e^2 c^2)^{1/2}$. By requiring the linear order term in x_β and p_β to vanish, we have

$$\begin{aligned}
\frac{\partial x_\epsilon}{\partial s} &= \frac{p_\epsilon}{p_0}, \\
\frac{\partial^2 x_\epsilon}{\partial s^2} + k_x x_\epsilon &= \frac{p - p_0}{p_0} \frac{1}{\rho}.
\end{aligned} \tag{A.17}$$

Let us define the fractional momentum difference $\delta = (p - p_0)/p_0$, and the dispersion function $\eta(s)$ such that $x_\epsilon = \delta \eta$, where η satisfies

$$\eta'' + k_x \eta = \frac{1}{\rho}. \tag{A.18}$$

With the help of Eqs. (A.17) and (A.18), the Hamiltonian can be written as

$$\tilde{H} = -p - p_0 \delta^2 \frac{\eta}{2\rho} + p_0 k_x \frac{x_\beta^2}{2} + \frac{p_\beta^2}{2p_0} \quad (\text{A.19})$$

From the transformation equations Eq. (A.15), the horizontal displacement is the sum of two parts: the horizontal betatron displacement x_β and the equilibrium orbit displacement x_ϵ that is proportional to the fractional momentum (energy) change δ (the dispersion effect). Similarly, the angular divergence x' is the sum of betatron divergence $x'_\beta = p_\beta/p_0$ and the equilibrium orbit divergence $x'_\epsilon = p_\epsilon/p_0$, i. e., we have

$$\begin{aligned} x &= x_\beta + x_\epsilon = x_\beta + \eta\delta \\ x' &= x'_\beta + x'_\epsilon = x'_\beta + \eta'\delta \end{aligned} \quad (\text{A.20})$$

A.4 Betatron Oscillation

Since we have decoupled the transverse betatron oscillation from the energy variation by introducing the equilibrium orbit and the dispersion function, we can construct action-angle variables (J, ϕ) to describe the transverse Hamiltonian

$$H_x = p_0 k_x \frac{x_\beta^2}{2} + \frac{p_\beta^2}{2p_0} = p_0 \left(k_x \frac{x_\beta^2}{2} + \frac{x_\beta'^2}{2} \right). \quad (\text{A.21})$$

A generating function that accomplishes this is [57]

$$F_1(x_\beta, \phi, s) = -p_0 \frac{x_\beta^2}{2\beta_x(s)} \left(\tan \phi - \frac{1}{2} \beta_x' \right), \quad (\text{A.22})$$

with the Courant-Snyder amplitude function $\beta_x(s)$ (beta function) satisfying the differential equation

$$\frac{1}{2} \beta_x'' - \frac{1}{4\beta_x} (\beta_x')^2 + k_x \beta_x - \frac{1}{\beta_x} = 0. \quad (\text{A.23})$$

The complete set of transformation equations becomes

$$\begin{aligned} x_\beta &= \sqrt{\frac{2J\beta_x}{p_0}} \cos \phi, \\ x'_\beta &= -\sqrt{\frac{2J}{\beta_x p_0}} \left(\sin \phi - \frac{1}{2} \beta_x' \cos \phi \right), \end{aligned} \quad (\text{A.24})$$

and the transformed Hamiltonian is

$$\tilde{H}_x = H_x + \frac{\partial F_1}{\partial s} = \frac{J}{\beta(s)}. \quad (\text{A.25})$$

Because the new transverse Hamiltonian is independent of the angle variable ϕ , the transverse action J is an invariant and is related to the old coordinates by

$$\begin{aligned} J &= \frac{p_0}{2\beta_x} \left[x_\beta^2 + \left(\beta_x x'_\beta + \alpha_x x_\beta \right)^2 \right], \\ &= \frac{p_0}{2} [\gamma_x x_\beta^2 + 2\alpha_x x_\beta x'_\beta + \beta_x x'^2_\beta] \end{aligned} \quad (\text{A.26})$$

where $\alpha_x = -\beta'_x/2$ and $\gamma_x = (1 + \alpha_x^2)/\beta_x$ according to Courant-Snyder parameterization [18]. The transverse action is related to the Courant-Snyder invariant W [18] through

$$W = \frac{2}{p_0} J = [\gamma_x x_\beta^2 + 2\alpha_x x_\beta x'_\beta + \beta_x x'^2_\beta] \quad (\text{A.27})$$

The particle motion governed by Eq. (A.26) or Eq. (A.27) is called betatron motion after it was first described in a betatron [39]. The trajectory of particle motion with initial condition $(x_{\beta 0}, x'_{\beta 0})$, follows an ellipse described by $W(x_\beta, x'_\beta) = W_0$ in the phase space (x_β, x'_β) (see Fig. A.2). Although the shape and the orientation of the ellipse changes with s all the time, the area of the phase space enclosed by the ellipse is always equal to πW_0 . The maximum orbit displacement is $x_{\max} = \sqrt{\beta_x W_0}$, and the maximum divergence is $x'_{\max} = \sqrt{W_0 \gamma_x} = \sqrt{W_0 (1 + \alpha_x^2)/\beta_x}$.

From Eq. (A.24), the beta function can be seen as the amplitude of the betatron oscillation. It also determines the phase advance by

$$\phi' = \frac{\partial \tilde{H}_x}{\partial J} = \frac{1}{\beta_x(s)}, \quad \text{or} \quad \phi(s) = \int_0^s \frac{ds^*}{\beta_x(s^*)}. \quad (\text{A.28})$$

Thus, the instantaneous wavelength of this pseudo-harmonic oscillation is $2\pi\beta_x(s)$.

It is possible to transform away the explicit s -dependence of $\tilde{H}_x$. Let us first introduce the betatron tune as

$$\nu_x = \frac{1}{2\pi} \int_0^{L_0} \frac{ds}{\beta_x}, \quad (\text{A.29})$$

Figure A.2: The Courant-Snyder invariant ellipse.

where L_0 is the circumference of the ring or the periodicity of the lattice. A canonical transformation that maps (ϕ, J) to (ϕ_1, J_1) is

$$F_2(\phi, J_1, s) = J_1 \left[\frac{2\pi\nu}{L_0} s - \int_0^s \frac{ds^*}{\beta_x(s^*)} \right] + \phi J_1, \quad (\text{A.30})$$

Since

$$\begin{aligned} \phi_1 &= \frac{\partial F_2}{\partial J_1} = \phi + \frac{2\pi\nu}{L_0} s - \int_0^s \frac{ds^*}{\beta_x(ds^*)}, \\ J &= \frac{\partial F_2}{\partial \phi} = J_1, \end{aligned} \quad (\text{A.31})$$

the transformed transverse Hamiltonian now becomes

$$\hat{H}_x = \tilde{H}_x + \frac{\partial F_2}{\partial s} = \frac{2\pi\nu}{L_0} J_1 = \frac{J_1}{\bar{\beta}}, \quad (\text{A.32})$$

where $\bar{\beta} = L_0/2\pi\nu$. In these new coordinates the oscillating part of the phase advance has been extracted leaving only the average phase advance. The transverse energy and the transverse action are related by the average beta function.

Appendix B

Index of Symbols

Symbol	Description	Page defined
$\alpha_{x,y}$	Horizontal/vertical Twiss parameter α	125
α_c	Momentum compaction factor	50
β	Velocity divided by c	8
$\boldsymbol{\beta}$	Velocity vector divided by c	15
β^*	Average velocity divided by c	30
$\boldsymbol{\beta}_{1,2}$	Velocity vector at t_1 and t_2	25
$\bar{\beta}$	Average beta function	53
$\beta_{x,y}$	Horizontal/vertical beta function	1
$\beta_{x,y}^*$	Horizontal/vertical beta at IP	106
χ	Ratio of radiation frequency to the critical frequency	28
χ_q	Quantum correspondence to χ	42
ΔE	Energy difference or loss	54
δ	Fractional energy or momentum difference	54
$\delta()$	Dirac delta function	16
$\delta_p()$	Periodic delta function	87
$\delta_{n,m}$	Kronecker delta function	77
δJ	Change of J after a photon emission	46
ϵ	Arbitrarily small positive quantity	35

Symbol	Description	Page defined
ϵ_0	Free space permittivity	16
ε_{rms}	RMS emittance	10
$\varepsilon_{\text{rms}}^n$	Normalized RMS emittance	10
$\varepsilon_{x,y}$	Horizontal/vertical emittance	1
$\varepsilon_{x,y}^n$	Horizontal/vertical normalized emittance	8
η	Dispersion function	123
η_c	Momentum compaction	54
Γ_b	Damping constant for bending fields	45
Γ_c	Damping constant for focusing fields	64
Γ_L	Damping constant for laser fields	104
γ	Ratio of kinetic energy to rest energy	8
γ_t	Ratio of transition energy to rest energy	97
$\gamma_{x,y}$	Horizontal/vertical Twiss parameter γ	125
κ	FODO parameter	16
λ	X-ray wavelength	110
λ_0	Oscillation wavelength	23
λ_L	Laser wavelength	99
λ_{rf}	RF wavelength	56
$\tilde{\lambda}_0$	Reduced oscillation wavelength	34
$\tilde{\lambda}_c$	Compton wavelength of the electron	51
$\tilde{\lambda}_u$	Reduced undulator oscillation wavelength	34
$\tilde{\lambda}_x$	Reduced transverse oscillation wavelength	34
μ	Space-time index	16
μ_x	Betatron phase advance per FODO cell	79
μ_0	Free space permeability	18
ν	Index for Bessel functions	27
$\nu_{x,y}$	Horizontal/vertical betatron tune	89
ω	Radiation frequency	23
ω_c	Synchrotron radiation critical frequency	22
ω_u	Undulator oscillation frequency	30

Symbol	Description	Page defined
ω_1	Undulator or channeling fundamental frequency	31
ω_{10}	Forward dipole frequency	23
$\omega_{x,y}$	Transverse oscillation frequency	32
Φ	Scalar Potential	16
ϕ	General angle variable	
φ	Angle between $\mathbf{n}$ to the horizontal plane	26
Π	Transition probability	38
Ψ	Electron's wavefunction	37
ψ	Stationary wavefunction	37
ρ	Radius of curvature, bending radius	21
ρ_u	Peak bending radius in the undulator	105
ρ_0	Isomagnetic bending radius	50
$\bar{\rho}$	Average bending radius	34
$\sigma_{x,y}$	Horizontal/vertical beam size	1
$\bar{\sigma}_{x,y}$	Average horizontal/vertical beam size	110
$\sigma'_{x,y}$	Horizontal/vertical beam divergence	1
σ_δ	RMS energy spread	55
σ_s	RMS bunch length	56
σ_L	RMS laser pulse length	103
σ_w	RMS laser transverse size	103
σ_{w0}	RMS laser transverse size at the waist	103
σ_T	Thomson cross section	110
$\varsigma_{x,y}$	Ratio of radiation formation length to $\beta_{x,y}$	91
τ	Dimensionless time variable	
Θ	Angle between $\mathbf{n}$ and $\dot{\boldsymbol{\beta}}$ or $\mathbf{z}$	18
$\Theta()$	Heavyside step function	35
θ	Angle between $\mathbf{n}$ and $\mathbf{s}$ or $\mathbf{z}$	19
θ_d	Deflection angle in the undulator	30
θ_e	Electron angle with the z direction	99
θ_p	Pitch angle in the channel	31

Symbol	Description	Page defined
ϑ	Angle between $\mathbf{n}$ and the horizontal plane	26
Υ	Strong field parameter	36
v	Ratio of photon energy to electron's kinetic energy	42
ξ	Argument in Eq. (3.64)	27
$\mathbf{A}$	Vector potential	16
A	Phase space density parameter	108
A_s	Canonical vector potential conjugate to s	120
A_δ	Peak energy spread	54
A_μ	4-Potential	16
$\mathbf{B}$	Magnetic field vector	16
B	Magnetic field strength	45
B_0	Main bending field	121
B_1	Gradient of the magnetic field	121
B_u	Undulator peak field	30
C_γ	Sands' radiation constant	21
c	Speed of light in vacuum	21
$\mathcal{D}$	Damping partition constant	49
$\mathbf{E}$	Electric field vector	16
E	Electron energy	19
e	Electron charge	
E_γ	Radiated energy	23
E_0	Initial energy or synchronous energy	45
E_L	Laser flash energy	104
E_x	Transverse energy	58
E_z	Longitudinal energy	31
$\mathcal{E}_0$	Electric field amplitude	99
f	Quadrupole focal length	79
$f()$	Distribution function	5
$f(a_1, a_2, a_3)$	Intrabeam scattering function	109
G	Green's function	85

Symbol	Description	Page defined
H	Hamiltonian	4
$\mathcal{H}$	$\mathcal{H}$ function for quantum excitation	50
h	RF harmonic number	54
$\hbar$	Planck constant	13
I	Laser intensity	100
I_0	Laser peak intensity	103
i	General index	
J	Invariant action	9
$J_{x,y}$	Horizontal/vertical action	125
$\mathcal{J}_{x,y,s}$	Damping partition numbers	55
K_u	Undulator parameter	31
$K_{x,y}$	Horizontal/vertical Focusing strength	31
k	Radiated photon momentum magnitude	84
$\mathbf{k}$	Radiated photon momentum vector	37
k_q	Focusing function	121
$k_{x,y}$	Horizontal/vertical focusing function	122
k_L	Laser photon momentum magnitude	99
L	Magnet length	79
L_c	Channel length	58
L_{mc}	Multiple Coulomb scattering length scale	70
L_0	Lattice periodicity	125
l	General index	
m	General index	
m_e	Electron mass	18
m_p	Particle mass	8
N	Number of particles	4
$\mathbf{n}$	Radiation direction	16
n	General index	
N_e	Number of electrons	108
N_L	Number of laser photons	111

Symbol	Description	Page defined
n_d	Minimum turns to damping one e-folding	104
$n_{x,y}$	Horizontal/vertical quantum level	58
$\dot{n}_\gamma$	Differential photon rate	46
n_γ	Differential photon number	106
$\dot{N}_\gamma$	Total x-ray photon flux	111
P_γ	Radiated Power	18
$\mathbf{P}$	Kinetic momentum vector	120
$\mathbf{p}$	Canonical momentum vector	
$p_{x,y,z}$	Momentum in the x , y or z direction	
p_s	Canonical momentum conjugate to s	120
$p_\perp$	Perpendicular component momentum	19
$p_\parallel$	Parallel component of the momentum	19
$\mathbf{q}$	Canonical coordinate vector	
R	average radius of a storage ring	45
R_F	Total reflectivity in an optical resonator	111
$\mathbf{r}$	Position vector	15
r_e	Classical electron radius	18
$\mathbf{S}$	Poynting Vector	18
s	Longitudinal coordinates in a curved system	119
T_0	Revolution or oscillation period	45
t	General time variable	
t_0	Relative time in radiation integrals	25
U_0	Energy radiated per turn	45
$\mathbf{v}$	Velocity vector	120
W	Courant-Snyder invariant	125
W_0	Courant-Snyder invariant of the envelope ellipse	125
W_{fi}	Total transition rate	85
dW_{fi}	Differential transition rate	39
x	Horizontal coordinate	119
y	Vertical coordinate	119

Symbol	Description	Page defined
z	Longitudinal coordinate in a straight system	30
Z_0	Free space impedance	100
Z_R	Rayleigh range	103

Bibliography

- [1] *Advanced Accelerator Concepts, AIP Conference Proceedings 91, 130, 156, 193, 279, 335, 398.* American Institute of Physics.
- [2] *Electron Beam, X-ray, and Ion-Beam Submicrometer Lithographies for Manufacturing.* SPIE, 1990-1996.
- [3] G. Arfken. *Mathematical Methods for Physicists.* Academic Press, Inc, San Diego, third edition, 1985.
- [4] V. M. Baier and V. M. Katkov. On radiation damping at planar channeling in presence of a multiple scattering. Technical Report Budker INP 97-13, The Budker Institute of Nuclear Physics, 1997.
- [5] V. N. Baier and V. M. Katkov. Processes involved in the motion of high energy particles in a magnetic field. *Zh. Eksp. Teor. Fiz.*, 53:1478, 1967. transl., Sov. Phys. JETP 26, 854 (1968).
- [6] V. N. Baier and V. M. Katkov. Quantum effects in magnetic bremsstrahlung. *Phys. Lett.*, 25A:492, 1967.
- [7] V. N. Baier and V. M. Katkov. Quasiclassical theory of bremsstrahlung by relativistic particles. *Zh. Eksp. Teor. Fiz.*, 55:1542, 1968. transl., Sov. Phys. JETP 28, 807 (1969).
- [8] V. N. Baier, V. M. Katkov, and V. M. Strakhovenko. Radiation of relativistic particles moving quasiperiodically. *Zh. Eksp. Teor. Fiz.*, 80:1348–1360, 1981. transl., Sov. Phys. JETP 53(4), 688 (1981).

- [9] V. Balakin *et al.* Focusing of submicro beams for TeV-scale e^+e^- linear colliders. *Phys. Rev. Lett.*, 74:2479–2482, 1995.
- [10] A. Baurichter *et al.* Radiation emission and its influence on the motion of multi-gev electrons and positrons in strong crystalline fields. *Phys. Rev. Lett.*, 79:3415–3418, 1997.
- [11] J. D. Bjorken and S. D. Drell. *Relativistic Quantum Mechanics*. McGraw-Hill, New York, 1964.
- [12] J. Buon. Beam phase space and emittance. In S. Turner, editor, *CERN accelerator school fifty general accelerator physics course*, volume 1, pages 89–116, January 1994.
- [13] A. W. Chao. *Physics of Collective Beam Instabilities in High Energy Accelerators*. John Wiley & Sons, 1995.
- [14] P. Chen, Z. Huang, and R. D. Ruth. Channeling acceleration: A path to ultrahigh energy colliders. In T. Tajima, editor, *Fourth Tamura Symposium on Accelerator Physics*, number 356 in AIP Conference Proceedings, pages 331–343, Austin, TX, November 1995. American Institute of Physics.
- [15] P. Chen and R. J. Noble. Channeled particle acceleration by plasma waves in metals. In R. A. Carrigan and J. A. Ellison, editors, *Relativistic Channeling*, page 517, New York, 1987. Plenum.
- [16] P. Chen and R. J. Noble. Crystal channel collider: Ultra-high energy and luminosity in the next century. In Swapan Chattopadhyay, editor, *Seventh Workshop on Advanced Accelerator Concepts*, number 398 in AIP Conference Proceedings, pages 273–285, Lake Tahoe, CA, October 1997. American Institute of Physics.
- [17] J. Chen *et al.* Development of a compact high brightness x-ray source. *Nucl. Instrum. Meth. in Phys. Res. A*, 341:346–350, 1994.
- [18] E. D. Courant and H. S. Snyder. Theory of the alternating-gradient synchrotron. *Annals of Physics*, 3:1–48, 1958.

- [19] F. R. Elder *et al.* Radiation from electrons in a synchrotron. *Phys. Rev.*, 71:829–830, 1947. more see SY76.
- [20] P. Emma. The Stanford Linear Collider. In Robert Siemann, editor, *Proceedings of the 1995 Particle Accelerator Conference and International Conference on High-Energy Accelerators*, volume 5, pages 606–610, Dallas, TX, May 1995.
- [21] H. Goldstein. *Classical Mechanics*. Addison-Wesley, Reading, Massachusetts, second edition, 1981.
- [22] I. S. Gradshteyn and I. M. Ryzhik. *Table of Integrals, series, and products*. Academic Press, New York, 4 edition, 1980.
- [23] W. Heitler. *Quantum Theory of Radiation*. Dover Publications, Inc, New York, third edition, 1984.
- [24] A. Hofmann. Theory of synchrotron radiation. Technical Report ACD-Note 38, SSRL, 1986.
- [25] Z. Huang, P. Chen, and R. D. Ruth. Radiation and radiation reaction in continuous focusing channels. In Paul Schoessow, editor, *Sixth Workshop on Advanced Accelerator Concepts*, number 335 in AIP Conference Proceedings, pages 646–658, Fontana, WI, June 1994. American Institute of Physics.
- [26] Z. Huang, P. Chen, and R. D. Ruth. Radiation damping in focusing-dominated systems. In Robert Siemann, editor, *Proceedings of the 1995 Particle Accelerator Conference and International Conference on High-Energy Accelerators*, volume 5, pages 3326–3328, Dallas, TX, May 1995.
- [27] Z. Huang, P. Chen, and R. D. Ruth. Radiation reaction in a continuous focusing channel. *Phys. Rev. Lett.*, 74:1759–1762, 1995.
- [28] Z. Huang, P. Chen, and R. D. Ruth. A semi-classical treatment of channeling radiation reaction. *Nucl. Instrum. Meth. in Phys. Res. B*, 119:192–198, 1996.

- [29] Z. Huang and R. D. Ruth. Suppression of radiation excitation in focusing environment. In Swapam Chattopadhyay, editor, *Seventh Workshop on Advanced Accelerator Concepts*, number 398 in AIP Conference Proceedings, pages 254–262, Lake Tahoe, CA, October 1996. American Institute of Physics.
- [30] Z. Huang and R. D. Ruth. Laser-electron storage ring as a compact source of high-intensity x-rays. In *Nineteenth International Free Electron Laser Conference*, Beijing, China, 1997.
- [31] Z. Huang and R. D. Ruth. Effects of focusing on radiation damping and quantum excitation in electron storage rings. *Phys. Rev. Lett.*, 80:2318–2321, 1998.
- [32] Z. Huang and R. D. Ruth. Laser-electron storage ring. *Phys. Rev. Lett.*, 80:976–979, 1998.
- [33] Z. Huang and R. D. Ruth. Radiation damping and quantum excitation in a focusing-dominated storage ring. In P. Chen, editor, *Fifteenth ICFA Advanced Beam Dynamics on Quantum Aspects of Beam Physics*, Monterey, CA, 1998.
- [34] D. D. Ivanenko and A. A. Sokolov. *Dokl. Akad. Nauk SSSR*, 59:1551, 1948.
- [35] J. D. Jackson. *Classical Electrodynamics*. John Wiley & Sons, Inc, 2 edition, 1975.
- [36] J. D. Jackson. On understanding spin-flip synchrotron radiation and the transverse polarization of electron in storage rings. *Review of Modern Physics*, 48(3):417–433, 1976.
- [37] J. M. Jowett. Introductory statistical mechanics for electron storage rings. In Melvin Month and Margaret Dienes, editors, *Physics of Particle Accelerators*, number 153 in AIP Conference Proceedings, pages 864–970. American Institute of Physics, 1987.
- [38] Robinson K. Radiation effects in circular electron accelerators. *Phys. Rev.*, 111:373–380, 1958.

- [39] D. Kerst and R. Serber. Electronic orbits in the induction accelerator. *Phys. Rev.*, 60:5358, 1941.
- [40] K.-J. Kim. Emittance in particle and radiation beam techniques. In Swapan Chattopadhyay, editor, *Seventh Workshop on Advanced Accelerator Concepts*, number 398 in AIP Conference Proceedings, pages 243–253, Lake Tahoe, CA, October 1996. American Institute of Physics.
- [41] K.-J. Kim, S. Chattopadhyay, and C. V. Shank. Generation of femtosecond x-rays by 90° Thomson scattering. *Nucl. Instrum. Meth. in Phys. Res. A*, 341:351–354, 1994.
- [42] N. P. Klepikov. Radiation of photons and electron-positron pairs in a magnetic field. *Zh. Eksp. Teor. Fiz.*, 26:19, 1954.
- [43] A. Kolomenski and A. Lebedev. The effect of radiation on the motion of relativistic electrons in synchrotrons. In *CERN Symposium*, volume 447, 1956.
- [44] M. A. Kumakhov and F. F. Komarov. *Radiation From Charged Particles in Solids*. American Institute of Physics, New York, 1989.
- [45] M. A. Kumakhov and R. Wedell. Theory of channelling of relativistic particles. *phys. stat. sol. (b)*, 92:65–71, 1979.
- [46] S. Y. Lee. Introduction to accelerator physics. Technical report, Indiana University, Bloomington, IN 47405, 1997.
- [47] R. L. Liboff. *Introductory Quantum Mechanics*. Addison-Wesley, Reading, Massachusetts, 1980.
- [48] A. Liénard. *L'Eclairage elect.*, 55(53):106, 1898.
- [49] J. Lindhard. Influence of crystal lattice on motion of energetic charged particles. *Mat. Fys. Medd. Dan. Vid. Selsk.*, 34(14), 1965.
- [50] J. Liouville. *Journ. de Math.*, 3:349, 1838.

- [51] D. T. Palmer *et al.* Emittance studies of the BNL/SLAC/UCLA 1.6 cell photocathode rf gun. In *Seventeenth IEEE Particle Accelerator Conference*, Vancouver, Canada, May 1997. SLAC-PUB-7422.
- [52] A. Piwinski. Intra-beam-scattering. In *Proceedings of the Ninth International Conference on High Energy Accelerators*, pages 405–409, Stanford, 1974.
- [53] A. Piwinski. In *Fourth Advanced Accelerator Physics Course, CERN Accelerator School*, pages 226–242, 1991.
- [54] I. V. Pogorelsky and I. Ben-Zvi. Emerging terawatt picosecond co2 laser technology and possible applications in accelerator physics. In *Seventeenth IEEE Particle Accelerator Conference*, Vancouver, Canada, May 1997.
- [55] T. O. Raubenheimer. *The Generation and Acceleration of Low Emittance Flat Beam For Future Linear Colliders*. PhD thesis, Stanford University, Stanford, CA, November 1991. SLAC-Report-387.
- [56] T. O. Raubenheimer. The core emittance with intrabeam scattering in e^+e^- rings. *Particle Accelerators*, 45:111–118, 1994.
- [57] R. D. Ruth. Single-particle dynamics in circular accelerators. In Melvin Month and Margaret Dienes, editors, *Physics of Particle Accelerators*, number 153 in AIP Conference Proceedings, pages 150–235. American Institute of Physics, 1987.
- [58] M. Sands. Synchrotron oscillation induced by radiation fluctuations. *Phys. Rev.*, 97:470–473, 1955.
- [59] M. Sands. The physics of electron storage rings: an introduction. Technical Report 121, SLAC, 1970.
- [60] R. W. Schoenlein *et al.* Femtosecond x-ray pulses at $0.4 \text{ \AA}$ generated by 90° Thomson scattering: a tool for probing the structural dynamics of materials. *Science*, 274:236–238.

- [61] G.A. Schott. *Electromagnetic Radiation*. Cambridge University Press, 1912.
- [62] J. Schwinger. On radiation by electrons in a betatron. unpublished but circulated manuscript, reissued as LBNL Report - 39088 (1996) [transcribed by M. A. Furman, 1945.
- [63] J. Schwinger. On the classical radiation of accelerated electrons. *Phys. Rev.*, 75(12):1912–1925, 1949.
- [64] J. Schwinger. The quantum correction in the radiation by energetic accelerated electrons. *Proc. Nat. Acad. Sci.*, 40:132–136, 1954.
- [65] A. Sessler, editor. *Workshop on Gamma-Gamma Colliders*, Berkeley, CA, 1994.
- [66] A. Sessler. Methods of beam cooling. In *INFN Eloisatron Project: 31st Workshop: Crystalline Beams and Related Issues*, Erice, Italy, November 1995.
- [67] T. Shintake. Proposal of a nanometer beam size monitor for e^+e^- linear colliders. *Nucl. Instrum. Meth. in Phys. Res. A*, 311:453–464, 1992.
- [68] A. E. Siegman. *Lasers*. University Science Books, Mill Valley, California, 1986.
- [69] A. A. Sokolov, N. P. Klepikov, and I. M. Ternov. *Dokl. Akad. Nauk SSSR*, 89:665, 1953.
- [70] A. A. Sokolov and A. N. Matveev. The problem of the radiation of ultra high velocity electrons moving in a constant magnetic field. *Zh. Eksp. Teor. Fiz.*, 30:126, 1956. transl., Sov. Phys. JETP 3, 105 (1956).
- [71] A. A. Sokolov and I. M. Ternov. *Zh. Eksp. Teor. Fiz.*, 25:698, 1953.
- [72] A. A. Sokolov and I. M. Ternov. *Synchrotron Radiation*. Pergamon Press, Oxford, 1968, 1971.
- [73] A. A. Sokolov and I. M. Ternov. *Radiation from Relativistic Electrons*. American Institute of Physics, New York, 1986.

- [74] P. Sprangle, A. Ting, E. Esarey, and A. Fisher. Tunable, short pulse hard x-rays from a compact laser synchrotron source. *J. Appl. Phys.*, 72:5032–5038, 1992.
- [75] V. Telnov. Laser cooling of electron beams for linear colliders. *Phys. Rev. Lett.*, 78:4757–4760, 1997.
- [76] J. Wei, X. Li, and A. Sessler. Low-energy state of circulating stored ion beams: crystalline beams. *Phys. Rev. Lett.*, 73:3089–3092, 1994.
- [77] W. T. Weng. Space charge effects—tune shifts and resonances. In Melvin Month and Margaret Dienes, editors, *Physics of Particle Accelerators*, number 153 in AIP Conference Proceedings, pages 348–389. American Institute of Physics, 1987.
- [78] H. Wiedemann. *Particle Accelerator Physics*. Springer-Verlag, New York, 1993.
- [79] K. Yokoya and P. Chen. Beam-beam phenomena in linear colliders. In M. Dienes, M. Month, and S. Turner, editors, *Frontiers of Particle Beams, Intensity Limitations*, volume 400, pages 415–445, Hilton Head Island, South Carolina, USA, 1990. Springer-Verlag.
- [80] A. A. Zholents and M. S. Zolotarev. A proposal for the generation of ultra-short x-ray pulses. *Nucl. Instrum. Meth. in Phys. Res. A*, 358:455–458, 1995.