Linear Collider Collaboration Tech Notes

Design Studies of Positron Collection for the NLC

Yuri K. Batygin, Ninod K. Bharadwaj, David C. Schultz, John C. Sheppard

Stanford Linear Accelerator Center
Stanford, CA

Abstract: The positron source for the NLC project utilizes a 6.2 GeV electron beam interacting in a high-Z positron production target. The electromagnetic shower in the target results in large energy deposition which can cause damage to the target. Optimization of the collection system is required to insure long-term operation of the target with needed high positron yield into the 6-dimensional acceptance of the subsequent pre-damping ring. Positron tracking through the accelerating system indicates a dilution of the initial positron phase space density. Results of simulations indicate that a positron yield of 0.76 can be obtained at the injection into pre-damping ring if the beam is limited by the normalized emittances of $\epsilon_x, \epsilon_y = 0.03 \text{ nm rad}$, bunch length $\sigma_z = 6.97 \text{ mm}$ and energy spread $\Delta E/E = 2\%$. The value of positron yield can be increased by 1.15 if longitudinal focusing is utilized in 1.9 GeV booster linac. In the regime of polarized positrons injection, the polarization of 0.65 can be obtained for 6.5 % of initial polarized positrons emerged from the target. The number of captured polarized positrons is increased by 9.6 % keeping the value of polarization as 0.63 if longitudinal focusing in the booster linac is used.

9 August 2001

LCC-0070

DESIGN STUDIES OF POSITRON COLLECTION FOR THE NLC

Yuri K. Batygin, Vinod K. Bharadwaj, David C. Schultz, John C. Sheppard

Stanford Linear Accelerator Center, Stanford University, Stanford, CA 94309

Abstract

The positron source for the NLC project utilizes a 6.2 GeV electron beam interacting in a high-Z positron production target. The electromagnetic shower in the target results in large energy deposition which can cause damage to the target. Optimization of the collection system is required to insure long-term operation of the target with needed high positron yield into the 6-dimensional acceptance of the subsequent pre-damping ring. Positron tracking through the accelerating system indicates a dilution of the initial positron phase space density. Results of simulations indicate that a positron yield of 0.76 can be obtained at the injection into pre-damping ring if the beam is limited by the normalized emittances of $\epsilon_x, \epsilon_y \leq 0.03 \pi \text{ m rad}$, bunch length $\sigma_z = 6.97 \text{ mm}$ and energy spread $\Delta E/E = 2\%$. The value of positron yield can be increased by 1.15 if longitudinal focusing is utilized in 1.9 GeV booster linac. In the regime of polarized positrons injection, the polarization of 0.65 can be obtained for 6.5 % of initial polarized positrons emerged from the target. The number of captured polarized positrons is increased by 9.6 % keeping the value of polarization as 0.63 if longitudinal focusing in the booster linac is used.

1 INTRODUCTION

The positron injector includes a production target followed by a short solenoid with a strong magnetic field (flux concentrator), a 250 MeV linac with 0.5 Tesla focusing solenoids, a 1.73 GeV booster linac with quadrupole focusing, and an energy compressor system before injection into the positron pre-damping ring (PPDR), see Table 1. The preliminary design of injector is presented in Ref. [1], [2], [3]. The new set of parameters is listed in Tables 2, 3. The main changes in the requirements to the injector are imposed by a new value of PPDR normalized transverse acceptance of 0.045π m rad instead of the previous value of 0.09π m rad. The ultimate goal of the collector system is to provide the highest number of positrons within the 6-dimensional acceptance of the pre-damping ring.

2 POSITRON YIELD

As positron capture is restricted by the acceptance of the pre-dumping ring, it is convenient to select an energy-invariant 6-dimensional phase space volume and observe the dilution of positron phase space density inside this volume. The 6-dimensional volume is defined in canonical conjugate variables (x, P_x) , (y, P_y) , $(z - z_s, p - p_s)$, where P_x and P_y are the canonical momentum

$$P_x = p_x - \frac{e B_z}{2} y, \quad P_y = p_y + \frac{e B_z}{2} x, \quad (2.1)$$

p_x , p_y are the mechanical momentum, B_z is a longitudinal magnetic field, and z_s , p_s define the dynamics of synchronous particles. To insure proper capture of positrons into PPDR, the edge normalized emittance of the positron beam is selected to be ϵ_x , $\epsilon_y \leq 0.03 \pi$ m rad, bunch length $\sigma_z = 6.97$ mm and energy spread $\Delta E/E = 2\%$ at the PPDR injection energy of $E = 1.98$ GeV. The value of energy spread corresponds to momentum spread of the beam $\Delta(\beta\gamma) = 80$. The positron yield is defined as a ratio of positrons in a volume of phase space per incident electron at the target:

$$Y_{e^+} = \frac{N_{e^+}}{N_{e^-}}. \quad (2.2)$$

3 BEAM DYNAMICS IN INJECTOR

3.1 Initial distribution

The initial positron distribution was obtained via Monte-Carlo simulation of electron-positron pair production utilizing the code EGS [4]. Generation of positron distribution was performed as 3 steps.

1. Generation of distribution $x_o, y_o, p_{x, o}, p_{y, o}, p_{z, o}$ by the program EGS using point-size incidence electron beam (FILE=nlce15rays, SOLID TARGET W75RE25 5RL R=3 MM IN THE CU CAST R=3 CM E=6.22 GeV, 02/20/1995)

2. Generation of 3D Gaussian distribution $x_G, y_G, z_G, p_{x, G}, p_{y, G}, p_{z, G}$ with $\sigma_x = \sigma_y = 0.. 3$ mm, $\sigma_z = 0.1275$ cm

3. Combination of both distributions using the following relationships:

$$x = x_o + x_G, \quad y = y_o + y_G, \quad z = z_G \quad (3.1)$$

$$p_x = p_{x, o}, \quad p_y = p_{y, o}, \quad p_z = p_{z, o} \quad (3.2)$$

Initial distribution of positrons in 6-dimensional phase space is presented in Fig. 1.

The positron beam created by an electromagnetic shower in solid target possesses large momentum spread. The typical value of transverse positron emittance after the interaction of the incident 6.2 GeV electron beam of $\sigma_{x,y} = 1.6$ mm with a W-Re target of 4 radiation lengths (RL) is $\epsilon_o = 0.135 \pi$ m rad. The production target is in the field of a tapered solenoid with a maximum field of $B_t = 1.2$ Tesla (see Fig. 2). The presence of a magnetic field at the target does not significantly increase the normalized beam emittance:

$$\epsilon = \sqrt{\epsilon_o^2 + \left(\frac{e B_t R_t^2}{2 m c}\right)^2} \approx \epsilon_o. \quad (3.3)$$

Positron yield at 250 MeV as a function of radius of an incident electron beam is presented in Fig. 3.

3.2 Dynamics in flux concentrator and linacs

The created beam enters the strong longitudinal magnetic field of a flux concentrator. The flux concentrator is a solenoid with sharp increase of magnetic field up to peak value of 5.8 Tesla at a distance of 5 mm from the target and an adiabatic decrease of the field over a distance of 15 cm [5]. The strong magnetic field at the target is required to confine the emitted positron beam with its large momentum spread.

The flux concentrator is followed by a 250 MeV linac with an effective accelerating gradient of 25 MeV/m and transverse focusing by a 0.5 Tesla solenoid field. The transverse acceptance of the linac with solenoid focusing is energy independent:

$$\alpha = \frac{e B_z}{2 m c} a^2 = 0.06 \pi \text{ m rad} . \quad (3.4)$$

After acceleration to 250 MeV positrons are accelerated in a linac with quadrupole focusing and an accelerating gradient of 15 MeV/m.

Tables 4, 5 and Figs. 4 - 7 show the results of the positron beam dynamics simulation in the injector. The positron yield within the 6D phase space volume drops from the value of 4.7 at the target to 0.76 at the end of the linac.

3.3 Chromaticity induced beam emittance growth

One of the reasons for the dilution of the beam phase space density in the linac is the beam energy spread, which results in chromaticity-induced beam emittance growth. In Figs. 8 -10 results of the test problem illustrating this phenomenon is presented. Three groups of particles with different energies initially occupy the same transverse phase space (Fig. 8). Due to energy spread, every ellipse is tilted in transverse phase space at different angle after each quadrupole. As a result, an effective area occupied by the beam is increased due to overlapping of different ellipses (see Figs. 9, 10). It is a source of reduction of number of positrons in the specified 6D phase space box.

An alternative scheme utilizes longitudinal focusing in 1.98 GeV linac instead of quadrupole structure. Calculations were done for two cases, using longitudinal focusing: for a linac with solenoid focusing with $B = 0.5$ Tesla, and a linac with focusing by periodic permanent magnets (PPM). The field of the PPM was approximated by function

$$B_z = B_0 \sin\left(\frac{2\pi z}{L}\right), \quad (3.5)$$

where $B_0 = 0.5$ Tesla is the maximum field and $L = 50$ cm was chosen to be the period of the PPM structure. Particle tracking indicates that in the case of longitudinal focusing, the positron yield at the end of the linac is increased to $Y_{e^+} = 1.15$ (see Tables 6, 7). Because acceptance of longitudinal magnetic field is energy-independent, transverse distribution of particles in booster linac remains the same (see Fig. 11).

4 DYNAMICS OF POLARIZED POSITRONS

One option for the positron injector being considered is the collection and acceleration of polarized positrons. Polarized positrons may be produced by targeting helically polarized gammas, which could be made by Compton backscattering [6] or with a helical undulator [7], on a thin target. To study the effects of positron depolarization, the particle tracking code was modified to include Thomas-BMT equation [8], describing the precession of the spin vector $\vec{S}$:

$$\frac{d\vec{S}}{dt} = \frac{e\vec{S}}{m\gamma} \times \left[(1+G\gamma)\vec{B}_\perp + (1+G)\vec{B}_\parallel + \left(G\gamma + \frac{\gamma}{1+\gamma}\right) \frac{\vec{E} \times \vec{\beta}}{c} \right], \quad (4.1)$$

where G is the anomalous magnetic moment of the positron, $\vec{E}$ is the electrical field, and $\vec{B}_\perp$ and $\vec{B}_\parallel$ are components of the magnetic field perpendicular and parallel to the particle velocity. The spin advance at a small distance dz is described as a matrix [9] :

$$\begin{pmatrix} S_x \\ S_y \\ S_z \end{pmatrix} = \begin{pmatrix} 1 - a(B^2 + C^2) & ABa + Cb & ACa - Bb \\ ABa - Cb & 1 - a(A^2 + C^2) & BCa + Ab \\ ACa + Bb & BCa - Ab & 1 - a(A^2 + B^2) \end{pmatrix} \begin{pmatrix} S_{x,o} \\ S_{y,o} \\ S_{z,o} \end{pmatrix}, \quad (4.2)$$

$$A = \frac{D_x}{D_o}, \quad B = \frac{D_y}{D_o}, \quad C = \frac{D_z}{D_o}, \quad D_o = \sqrt{D_x^2 + D_y^2 + D_z^2}, \quad (4.3)$$

$$a = 1 - \cos(D_o \delta z), \quad b = \sin(D_o \delta z), \quad (4.4)$$

where components D_x , D_y , D_z are defined by the equations:

$$D_x = \frac{e}{m\gamma v} \left[(1+G\gamma)(B_x - x'B_z) + (1+G)x'B_z + \frac{v}{c^2} \left(\frac{\gamma}{1+\gamma} + G\gamma \right) (E_y - y'E_z) \right], \quad (4.5)$$

$$D_y = \frac{e}{m\gamma v} \left[(1+G\gamma)(B_y - y'B_z) + (1+G)y'B_z + \frac{v}{c^2} \left(\frac{\gamma}{1+\gamma} + G\gamma \right) (x'E_z - E_x) \right], \quad (4.6)$$

$$D_z = \frac{e}{m\gamma v} \left[(1+G\gamma)(-x'B_x - y'B_y) + (1+G)(x'B_x + B_z + y'B_y) + \frac{v}{c^2} \left(\frac{\gamma}{1+\gamma} + G\gamma \right) (y'E_x - E_y x') \right]. \quad (4.7)$$

Fig. 12 illustrates the polarization of positrons emerging from 0.2 RL W-Re target as a function of their energy. Polarization of positrons emerged from the target was calculated by the EGS code extended to study polarization propagation in the target [10]. Polarization is defined as the probability to find the spin of the positron along the direction of the positron momentum.

During beam transport and acceleration, the spin vector precesses, resulting in the depolarization of the beam. We define the longitudinal polarization as an average of the product of the longitudinal component S_z and the value of polarization, P , over all positrons:

$$\langle P_z \rangle = \frac{1}{N} \sum_{i=1}^N S_z^{(i)} P^{(i)}. \quad (4.8)$$

Figs. 12 - 17 and Tables 8 - 11 illustrates the dynamics of polarized positrons. Simulation shows that 6.5 % of the produced positrons have an average value of polarization of 65 % (see Fig. 13 a). The value of captured polarized positrons can be increased by 9.6 % keeping the polarization of positrons as 63% if longitudinal focusing in the booster linac is used (see Fig. 13 b). Additional study is required to increase the number of captured positrons keeping the value of polarization high, and determine the needed γ - flux.

REFERENCES

- [1] Zeroth-Order Design Report for the Next Linear Collider , SLAC-Report 474, (1996).
- [2] T.Kotseroglou et. al., Proc. of the 1999 Particle Accelerator Conference, 3450 (1999).
- [3] J.C. Sheppard et. al., "Update to the NLC Injector System Design", PAC 2001, June 2001.
- [4] W.Nelson, H.Hirayama and D.Rogers, "The EGS4 Code System", SLAC-Report-265 (1985).
- [5] A.V.Kulikov, S.D.Ecklund and E.M.Reuter, Proc. of the 1991 Particle Accelerator Conference, 2005 (1991).
- [6] T.Omori, Proc. of the Workshop on New Kind of Positron Sources, Stanford, (1997), SLAC-R-502, p.285.
- [7] A.Mikhailichenko, Proc. of the Workshop on New Kind of Positron Sources, Stanford, (1997), SLAC-R-502, p.229.
- [8] V.Bargmann, L.Michel, V.L.Telegdi, Phys. Rev. Lett. 2 (1959) 435.
- [9] Y.Batygin and T.Katayama, Physical Review E, Vol. 58, (1998), 1019.
- [10] K.Flottmann, Ph.D. Thesis, DESY-93-161A (1993).

Table 1. Positron injector parameters.

<i>Tapered field</i>	
Max field	1.2 Tesla
<i>Flux concentrator</i>	
Max field	5.8 Tesla
Aperture	0.45.....2.6 cm
Field length	15 cm
<i>RF linac (250 MeV)</i>	
Accelerating field	25 MV/m
Frequency	1428 MHz
Length	10 m
Radius of aperture	2 cm
Focusing field	0.5 Tesla
<i>RF linac (1.9 GeV)</i>	
Accelerating field	9.16 MV/m
Frequency	1428 MHz
Length	180 m
Radius of aperture	3 cm
<i>Energy compressor</i>	
Bend	Arc $8 \times 7.5^\circ = 60^\circ$
Focusing field	Quadrupole structure
RF voltage	24 MV/m $\times$ 5 m = 120 MV

Table 2. Parameters of the electron beam drive for the positron target.

Parameter	Value
Energy	6.2 GeV
Bunch spacing	1.4 / 2.8 ns
Bunch energy variation	1% FW
Single bunch energy spread	1 % FW
Normalized emittance	$10^{-4} \pi$ m rad
Transverse size, σ_x	1.6 mm
Bunch length, σ_z	5 mm
Particles/Bunch	$1.2 / 2.4 \cdot 10^{10}$
Train population uniformity	1 % FW
Bunch-to-Bunch Pop. Unif.	2 % rms
Number of Bunches	190 / 95
Repetition Rate	120 Hz
Beam Power	271 kW

Table 3. Positron beam parameters.

Parameter	Value
Energy	1.98 GeV
Bunch spacing	1.4/2.8 ns
Bunch energy variation	1% FW
Single bunch energy spread	2 % FW
Normalized emittance	0.03π m rad
Bunch length, σ_z	10 mm
Particles/Bunch	$0.9/1.8 \cdot 10^{10}$
Train population uniformity	1 % FW
Bunch-to-Bunch Pop. Unif.	2 % rms
Number of Bunches	190/95
Repetition Rate	120 Hz
Beam Power	58 kW

Fig. 1. Initial positron distribution in phase space.

Fig. 2. Magnetic field at the injection.

Fig. 3. Positron yield at 250 MeV as a function of incident 6 GeV electron beam size:

Upper curve: positron yield at 250 MeV within 6-dimensional phase space $\epsilon_x = 0.06 \pi$ m rad, $\epsilon_y = 0.06 \pi$ m rad, $\Delta p_z = 80$ as a function of incident 6 GeV electron beam size, $2\sigma_e$.

Lower curve: positron yield at 250 MeV within 6-dimensional phase space $\epsilon_x = 0.03 \pi$ m rad, $\epsilon_y = 0.03 \pi$ m rad, $\Delta p_z = 80$ as a function of incident 6 GeV electron beam size, $2\sigma_e$.

Table 4. Results of positron tracking (1.98 GeV booster linac with quadrupole focusing).

	Initial data (after target)	After flux concentrator	End of 250 MeV RF linac	End of 1.9 GeV RF linac	End of 1.9 GeV energy compressor
Number of particles in channel	5128 (100%)	2024 (39.5%)	929 (18.1%)	811 (15.8%)	801 (15.6%)
Fraction of particles within x_px phase space $\epsilon_x < 0.03 \pi$ mrad	0.596	0.54	0.92	0.70	0.56
Fraction of particles within y_py phase space $\epsilon_y < 0.03 \pi$ m rad	0.596	0.54	0.92	0.79	0.69
Fraction of particles within z_pz phase space $\Delta p_z < 80$	0.778	0.58	0.86	0.69	0.78
Fraction of particles within 6-D phase space $\epsilon_x < 0.03 \pi$ mrad $\epsilon_y < 0.03 \pi$ m rad $\Delta p_z < 80$	0.39	0.37	0.7351	0.40	0.357
Positron yield, N_{e^+} / N_{e^-} , within 6-D phase space	4.7 (39%)	1.76 (14.6%)	1.598 (13.3%)	0.759 (6.3%)	0.67 (5.5%)

Table 5. Results of positron tracking (1.98 GeV booster linac with quadrupole focusing).

	Initial data (after target)	After flux concentrator	End of 250 MeV RF linac	End of 1.9 GeV RF linac	End of 1.9 GeV energy compressor
Number of particles in channel	5128 (100%)	2024 (39.4%)	929 (18.1%)	811 (15.8%)	801 (15.6%)
Fraction of particles within x_px phase space $\epsilon_x < 0.06 \pi$ mrad	0.77	0.69	0.99	0.86	0.70
Fraction of particles within y_py phase space $\epsilon_y < 0.06 \pi$ m rad	0.77	0.69	0.99	0.93	0.85
Fraction of particles within z_pz phase space $\Delta p_z < 80$	0.778	0.58	0.86	0.69	0.78
Fraction of particles within 6-D phase space $\epsilon_x < 0.06 \pi$ mrad $\epsilon_y < 0.06 \pi$ m rad $\Delta p_z < 80$	0.51	0.51235	0.8643	0.5856	0.553
Positron yield, N_{e^+} / N_{e^-} , within 6-D phase space	6.1 (51%)	2.42 (20.21%)	1.878 (15.65%)	1.111 (9.26%)	1.036 (8.637%)

Fig. 4. Positron distribution after flux concentrator.

Fig. 5. Positron distribution at 250 MeV.

Fig. 6. Positron distribution after booster linac at 1.98 GeV.

P_x vs x (cm)

Fig. 7. Positron distribution after 1.9 GeV energy compressor.

P_x vs x (cm)

P_y vs y (cm)

P_z vs z (cm)

Fig. 8. Initial positron distribution at 250 MeV.

P_x vs x (cm)

P_y vs y (cm)

P_z vs z (cm)

Fig. 9. Positron distribution at 675 MeV.

P_x vs x (cm)

P_y vs y (cm)

P_z vs z (cm)

Fig. 10. Positron distribution at 1.9 GeV.

Table 6. Results of positron tracking (1.98 GeV booster linac with 0.5 Tesla longitudinal focusing).

	Initial data (after target)	After flux concentrator	End of 250 MeV RF linac	End of 1.9 GeV RF linac
Number of particles in channel	5128 (100%)	2024 (39.46%)	929 (18.11%)	921 (17.96%)
Fraction of particles within x_{px} phase space $\epsilon_x < 0.03 \pi$ mrad	0.596	0.54	0.92	0.92
Fraction of particles within y_{py} phase space $\epsilon_y < 0.03 \pi$ m rad	0.596	0.54	0.92	0.92
Fraction of particles within z_{pz} phase space $\Delta p_z < 80$	0.778	0.58	0.86	0.62
Fraction of particles within 6-D phase space $\epsilon_x < 0.03 \pi$ mrad $\epsilon_y < 0.03 \pi$ m rad $\Delta p_z < 80$	0.39	0.37	0.7351	0.536
Positron yield, N_{e^+} / N_{e^-} , within 6-D phase space	4.7 (39%)	1.76 (14.7%)	1.598 (13.31%)	1.15 (9.62%)

Table 7. Results of positron tracking (1.98 GeV booster linac with 0.5 Tesla longitudinal focusing).

	Initial data (after target)	After flux concentrator	End of 250 MeV RF linac	End of 1.9 GeV RF linac
Number of particles in channel	5128 (100%)	2024 (39.46%)	929 (18.11%)	921 (17.96%)
Fraction of particles within x_px phase space $\epsilon_x < 0.06 \pi$ mrad	0.77	0.69	0.99	0.99
Fraction of particles within y_py phase space $\epsilon_y < 0.06 \pi$ m rad	0.77	0.69	0.99	0.99
Fraction of particles within z_pz phase space $\Delta p_z < 80$	0.778	0.58	0.86	0.62
Fraction of particles within 6-D phase space $\epsilon_x < 0.06 \pi$ mrad $\epsilon_y < 0.06 \pi$ m rad $\Delta p_z < 80$	0.51	0.51235	0.8643	0.62649
Positron yield, N_{e^+} / N_{e^-} , within 6-D phase space	6.1 (51%)	2.42 (20.21%)	1.878 (15.65%)	1.35 (11.26%)

P_x vs x (cm)

P_y vs y (cm)

P_z vs z (cm)

Fig. 11. Positron distribution in 1.9 GeV linac with 0.5 Tesla solenoid focusing.

Energy range, MeV	Fraction of positrons within 6D phase space	$\langle P_z \rangle$
50-60	4.8E-02	0.98
40-60	0.19	0.94
30-60	0.37	0.86
0-60	0.94	0.49

Energy range, MeV	Positron capture within 6D phase space	$\langle P_z \rangle$
50-60	0.0052	0.98
40-60	0.019	0.93
20-60	0.20	0.60
0-60	0.49	0.32

Energy range, MeV	Positron capture within 6D phase space	$\langle P_z \rangle$
260-280	0.028	0.92
255-280	0.038	0.86
245-280	0.084	0.68
242-280	0.11	0.60
240-280	0.14	0.53

Polarization vs Energy, MeV

Fig. 12. Positron polarization: a) after target, b) after flux concentrator, c) at 250 MeV.

a)

Polarization vs Energy (MeV)

Energy range, MeV	Positron capture within 6D phase space	$\langle P_z \rangle$
2013-2023	0.0043	0.98
1992-2023	0.037	0.8339
1982-2023	0.0655	0.65
1961-2023	0.14	0.40

b)

Polarization vs Energy, MeV

Energy range, MeV	Positron capture within 6D phase space	$\langle P_z \rangle$
2013-2023	0.0065	0.98
1992-2023	0.045	0.82
1982-2023	0.096	0.63
1961-2023	0.20	0.41

Fig. 13. Polarization at 1.9 GeV: a) 1.98 GeV booster linac with quadrupole focusing, b) 1.98 GeV booster linac with 0.5 Tesla longitudinal focusing).

P_x vs x (cm)

P_y vs y (cm)

dN/dE vs $Energy$ (MeV)

Fig. 14. Initial distribution of polarized positrons in phase space.

P_z vs $z(cm)$

Fig. 15. Distribution of polarized positrons in phase space at 250 MeV.

Fig. 16. Distribution of polarized positrons at 1.9 GeV (1.9 GeV booster linac with quadrupole focusing).

Fig. 17. Polarized positron distribution in phase space at 1.98 GeV (1.9 GeV booster linac with 0.5 Tesla focusing).

Table 8. Results of polarized positron tracking (1.9 GeV booster linac with quadrupole focusing).

	Initial data (after target)	After flux concentrator	End of 250 MeV RF linac	End of 1.9 GeV RF linac
Number of particles in channel	16027 (100%)	8339 (52%)	4665 (29%)	4339 (27%)
Fraction of particles within x_{px} phase space $\epsilon_x < 0.03 \pi$ mrad	0.85	0.65	0.95	0.76
Fraction of particles within y_{py} phase space $\epsilon_y < 0.03 \pi$ m rad	0.85	0.65	0.95	0.86
Fraction of particles within z_{pz} phase space $\Delta p_z < 80$	0.80	0.74	0.55	0.39
Fraction of particles within 6-D phase space $\epsilon_x < 0.03 \pi$ mrad $\epsilon_y < 0.03 \pi$ m rad $\Delta p_z < 80$	0.59	0.46	0.49	0.26
Positron capture, $\frac{N_{e^+}(\text{accepted})}{N_{e^+}(\text{produced})}$, within 6-D phase space	0.59	0.23	0.14	0.07

Table 9. Results of polarized positron tracking (1.9 GeV booster linac with quadrupole focusing).

	Initial data (after target)	After flux concentrator	End of 250 MeV RF linac	End of 1.9 GeV RF linac
Number of particles in channel	16027 (100%)	8339 (52%)	4665 (29%)	4339 (27%)
Fraction of particles within x_{px} phase space $\epsilon_x < 0.06 \pi$ mrad	0.92	0.78	1	0.90
Fraction of particles within y_{py} phase space $\epsilon_y < 0.06 \pi$ m rad	0.92	0.78	1	0.96
Fraction of particles within z_{pz} phase space $\Delta p_z < 80$	0.80	0.74	0.92	0.39
Fraction of particles within 6-D phase space $\epsilon_x < 0.06 \pi$ mrad $\epsilon_y < 0.06 \pi$ m rad $\Delta p_z < 80$	0.68	0.59	0.55	0.34
Positron capture, $\frac{N_{e^+}(\text{accepted})}{N_{e^+}(\text{produced})}$, within 6-D phase space	0.68	0.3069	0.16	0.098

Table 10. Results of polarized positron tracking (1.9 GeV booster linac with 0.5 Tesla longitudinal focusing).

	Initial data (after target)	After flux concentrator	End of 250 MeV RF linac	End of 1.9 GeV RF linac
Number of particles in channel	16027 (100%)	8339 (52%)	4665 (29%)	4657 (29%)
Fraction of particles within x_{px} phase space $\epsilon_x < 0.03 \pi$ mrad	0.85	0.65	0.95	0.94
Fraction of particles within y_{py} phase space $\epsilon_y < 0.03 \pi$ mrad	0.85	0.65	0.95	0.94
Fraction of particles within z_{pz} phase space $\Delta p_z < 80$	0.80	0.74	0.55	0.39
Fraction of particles within 6-D phase space $\epsilon_x < 0.03 \pi$ mrad $\epsilon_y < 0.03 \pi$ mrad $\Delta p_z < 80$	0.59	0.46	0.49	0.33
Positron capture, $\frac{N_{e^+}(\text{accepted})}{N_{e^+}(\text{produced})}$, within 6-D phase space	0.59	0.23	0.14	0.096

Table 11. Results of polarized positron tracking (1.9 GeV booster linac with 0.5 Tesla longitudinal focusing).

	Initial data (after target)	After flux concentrator	End of 250 MeV RF linac	End of 1.9 GeV RF linac
Number of particles in channel	16027 (100%)	8339 (52%)	4665 (29%)	4657 (29%)
Fraction of particles within x_{px} phase space $\epsilon_x < 0.06 \pi$ mrad	0.92	0.78	1	1
Fraction of particles within y_{py} phase space $\epsilon_y < 0.06 \pi$ mrad	0.92	0.78	1	1
Fraction of particles within z_{pz} phase space $\Delta p_z < 80$	0.80	0.74	0.92	0.39
Fraction of particles within 6-D phase space $\epsilon_x < 0.06 \pi$ mrad $\epsilon_y < 0.06 \pi$ mrad $\Delta p_z < 80$	0.68	0.59	0.55	0.39
Positron capture, $\frac{N_{e^+}(\text{accepted})}{N_{e^+}(\text{produced})}$, within 6-D phase space	0.68	0.3069	0.16	0.11