SLAC-74 UC-28, Particle Accelerators and High Voltage Machines TID-4500

STREAMER CHAMBER DEVELOPMENT

by

F. Bulos, A. Odian, F. Villa, and D. Yount

June 1967

Technical Report Prepared Under Contract AT (04-3)-515

Printed in USA. Available from CFSTI, National Bureau of Standards, U.S. Department of Commerce, Springfield, Virginia 22151 Price: Printed Copy \$3.00; Microfiche \$0.65

TABLE OF CONTENTS

		age
Ι.	Introduction \ldots	1
п.	Streamer Theory and Experiment	4
	A. Single Avalanche (Townsend Equations)	5
	B. Streamer Formation (Meek Equations)	10
	C. Experimental Studies of Streamer Prightness	13
	D. Experimental Studies of Streamer Diffusion and Memory	16
	E. Ionization Measurements in Streamer Chambers	21
ш.	Optics	27
	A. Image Intensifiers Versus Direct Fhotography	28
	B. Selecting the Demagnification and f-Number	33
	C. Film, Lenses, and Measuring Machines	36
	D. Data Analysis: Streamer Chambers versus Bubble Chambers	41
IV.	Chamber Technology	46
	A. Single versus Double Gap	46
	B. Small versus Large Chambers	47
	C. Electrodes	50
	D. Cells and Targets	51
	E. Purifier	55
v.	High Voltage Technology	63
	A. Introduction	63
	B. High Voltage Generators	58
	C. Pulse Shaping Networks	77
	D. Pulse Monitoring	35

h.

-

	Page
VI. Development of the Two-Meter Streamer Chamber	89
A. A Brief History	89
B. Summary of the Final System	96 -
C. Initial Performance of the Two-Meter Streamer Chamber	104
D. Speculation	108
References	113
Appendix A	117
Appendix B	127
Appendix C	134

Ĩ.__

~ ~

LIST OF ILLUSTRATIONS

1 The set of the part of the

-

.

-

		Page
1.	Streamer tracks with 0.15- μ sec delay in the high voltage pulse, photographed with f/2.8 lens aperture	2
2.	Q versus E/p in kV/(cm · torr). Q, which is roughly proportional to $1/E$, is the ratio of the rates for producing protons and free electrons during avalanche formation	8
3.	α /p versus E/p in κ V/(cm · torr). α is the first Townsend coefficient and is roughly proportional to the electric field E	9
4.	Streamer track with 20- μ sec delay in the high voltage pulse. Diffusion of the primary electrons is seen clearly in the view parallel to \vec{E} (left side of picture).	18
5.	Projected scatter of the diffused streamer track plotted as a function of the pulse delay τ in μ sec. Essentially this figure indicates the accuracy with which the axis of a streamer track can be found with various pulse delays	19
6.	The effects of an admixture of Freon 12 on the memory of the chamber and on the track quality. In (a) the streamer density is plotted as a function of the pulse delay for 14 PPM Freon 12. The time at which the streamer density has dropped to half the $T = 0$ value is shown in (b) for various concentrations f of Freon 12 in PPM. In (c) the minimum streamer length visible in the side view (f/1.5, RAR 2475 film) is plotted as a function of the memory time	20
7.	Streamer gap length distribution for 0.15- μ sec delayed high voltage pulse. The expected distribution is exponential, and the cut-off at about 2.0 mm indicates that approximately 50% of the streamers are prevented from developing by a robbing action between closely spaced streamers. The mean streamer density corrected for robbing is 4.0/cm and the mean gap about 2.8 mm	23
8.	Average number of streamers per cm of track length versus the pulse delay in μ sec. Delta rays and bright clusters are excluded in analyzing the streamer data.	24
9.	Average number of streamers per cm of track length versus the chamber pressure in atm. Robbing by adjacent streamers is apparently not important below about 0.2 atm	26
10.	Layout for a three-stage image intensifier. The streamer chamber, with maximum depth of field Δu , is on the left and the film plane on the right	31
11.	Comparison of Kodak SO 340 film on the left with Kodak RAR 2475 on the right. The exposure was 1/100 sec in each case, and the development was in Nikor Reel D-19 developer at 83°F. The grain density versus time for 3 min, 6 min, 8 min, and 10 min of hand development is given for each film	37

		Page
12.	Comparison of hand development on the right with spray machine development on the left. The exposure in each case was $1/100$ sec with a W-21 filter, and the development was in modified Dupont x-ray developer at 83° F. The high speed spray developing machine was run at 50 ft/min	38
13.	Comparison of effect of forced developing (left) versus standard developing (right)	39
14.	Resolution chart photographed with RAR 2475 film on the right and SO 343 film on the left. For RAR 2475 film the large box has fuzzy edges, while for the SO 340 film the edges are quite sharp	40
15.	An early single-gap streamer chamber developed at SLAC. The dimensions of the sensitive volume are length 50 cm, width 50 cm, and gap 10 cm.	48
16.	An early double-gap chamber developed at SLAC. The dimensions of the sensitive volume are length 150 cm width 45 cm, and double gap 30 cm; the view is from the input end. The outer, ground elec- trodes have been joined to enclose completely the central high voltage electrode	49
17.	Purifier for the 90% neon-10% helium streamer chamber gas. As described in the text, the pump and control unit can be used either with Ca-Na reactors indicated or with a molecular sieve cooled to LN_2 temperature	56
18.	Nitrogen contamination as a function of time. In (a) the flow rate was 2400 liters/hour through a single 900-liter foam cell with the Ca-Na reactors providing the active unit. In (b) the 50-kg molecular sieve at LN_2 temperature was used to purify a cell containing initially about 50% air(40% nitrogen). The flow rate was 250 liters/hour into one 900-liter cell	60
19.	Gas impurities versus the equilibrium flow rate, versus the neon volume flowed per day, and versus the neon cost. A leak rate of 0.01% per hour into two 900-liter foam cells is assumed here and is similar to the actual leak rates observed during tests, including a preliminary run in the photon beam	61
20.	Block diagram illustrating the principal elements of the streamer chamber system (a) and a chamber layout to be considered either as a capacitor or as a transmission line (b)	65
21.	Streamer track photograph with the 2-meter chamber terminated by an impedance 35% lower than the characteristic value. The ionizing particle was incident from the input end of the chamber	<u>^</u> -
	where the track is brightest	67

-

-

_

~.__

22.	A four-stage, single-polarity Marx generator. The spark gap capacity C_G , the stray capacity to ground C_S , and the interelectrode capacity C_I are shown with dashed lines and should satisfy the condition $C_G \ll C_S$, C_I for reliable triggering. The trigger capacitor C_T is added to the trigger gap to increase the energy discharged by this gap and thus to increase the light output	69
23.	Circuit diagram for the 17-gap, 34-stage Marx generator used to drive the 2-meter streamer chamber. A photograph of this gener- ator is shown in Fig. 38	71
24.	Marx generator equivalent circuit. The procedures by which one can determine the capacitance and the internal inductance and resistance of a Marx generator are described in the text	72
25.	Circuit for measuring the capacity at a given high voltage (a) and the results of such a measurement (b) made with a barium- titanate capacitor similar to those used in the 17-gap, 34-stage Marx generator	74
26.	Schematic drawings of a stacked stripline generator (a) and a spiral generator (b). These and several other generators are discussed in detail in the article by R. A. Fitch and V. T. S. Howell, Ref. 48	76
27.	Three pulse shaping networks driven by Marx generators. These are the capacitor with series (S) and shorting gaps (S') shown in (a), the dielectrically loaded line shown in (b), and the Blumlein line shown in (c). Also sketched are the characteristic output pulses for each type of pulse shaping network	79
28.	Two views of a system in which the parasitic capacitance C_p has been enhanced and in which series and shorting gaps have been added to a Marx generator to form a pulse shaping network. A photograph of this system is shown in Fig. 32	80
29.	Analysis of the operation of a Blumlein line. The five-electrode Blumlein (a) is equivalent to two three-electrode Blumleins (b) each of which can be considered as a constant impedance line interrupted at the center by the load NZ. The first Blumlein pulse begins at time τ after the spark gap fires and continues until time 3τ where τ is the time required for a wave to travel from the spark gap to the end of the charged electrode. When the impedances of the Blumlein and load are properly matched (N=2), the amplitude of the first pulse is equal to the charging voltage, and all succeeding pulses are zero	83
30.	Charging the Blumlein with a bridge circuit to control the Blumlein prepulse which appears across the chamber. By ad- justing the prepulse properly, one can cancel the displacement of the streamer origins which normally occur when a driving pulse of only one polarity is used	86

Page

Page

, - - -

~.

31.	A resistive probe (a), a capacitive probe (b), and the pulses (c and d) obtained on the 2-meter streamer chamber with each. The pulses are similar for the two probes except for the small amplitude, high frequency ringing in the capacitive case. The pulse amplitude for streamers is nearly 600 kV across the 30-cm chamber gaps. The rise time is 4 nsec and the pulse duration about 12 nsec at half the peak voltage. The characteristic rise time for each probe is about
	$1 \text{ nsec.} \dots \dots$
32.	Photograph of a double-gap streamer channer driven by a Marx generator with an intermediate capacitor and with series and shorting spark gaps used as a pulse shaping network. The chamber, with electrodes in the vertical plane, has a sensitive volume 50 cm wide and 150 cm long with two gaps of 15 cm each. Drawings of this system are shown in Figs. 28 a and b
33.	Side view of the experimental arrangement for the photoproduction program. A highly collimated, hardened bremsstrahlung beam is incident from the left and passes through a 1/2-inch-diameter hydrogen gas target in the upper of two foam cells
34.	Top view of the experimental arrangement for the photoproduction experiment. Events which occur in the chamber are photographed stereoscopically by three cameras through the hole left by the absent upper pole piece. The magnet windings, three below and seven above, are unbalanced to compensate for the missing pole piece and to improve the field uniformity
35.	A three-dimensional, x-ray vision drawing of the experimental arrangement for the photoproduction program
36.	A photograph of the experimental arrangement for the photopro- duction program. The view is similar to that shown in Fig. 35, but the vacuum pipe for the photon beam is not in place
37.	Photograph of the experimental arrangement for the photopro- duction program. In this figure, the beam is incident from the right. The "elbow" can be seen on the right arching from the Marx generator - Blumlein oil tank to the streamer chamber, which passes through the magnet between the visible upper and lower magnet coils. The vertical trigger-counter array, con- sisting in this case of 16 counters, is supported on the downstream side of the magnet. The trigger electronics is visible on the magnet column nearest the counters. The magnet, including the entire streamer chamber and drive system and the trigger counters, can be driven in and out of the photon beam along the tracks visible in the floor

-

38. Photograph of the 17-gap, 34-stage Marx generator used to drive the 2-meter streamer chamber. A circuit diagram of this generator appears in Fig. 23. The carbon rod resistors used in charging the capacitor stages are not shown in the photograph, but supporting fixtures can be clearly seen. The modular construction permits the rapid removal of any stage in case of capacitor failure, and the spark gap manifold can also be replaced in a matter of minutes. The arrangement of the capacitor stages is designed to enhance the interstage capacity $C_{\rm I}$ and the stray capacity $\tilde{C}_{\rm C}$ to ground, while the capacity of each spark gap C_G is ninimal. Thus the design satisfies the condition $C_G \ll C_I$, C_S as discussed in the text. In addition, light emitted from any one gap has an excellent chance to induce photoionization in the succeeding gaps and thus to insure the reliable triggering of all gaps. 10339. The Blumlein and "elbow" used in shaping the 10-nsec, 600-kV pulse which drives the streamer chamber. The sheet metal which normally encloses the Blumlein and elbow has been largely removed for viewing. The vertical elements of the Blumlein taper outward and upward from the spark gap in such a way that the 23-ohm chamber impedance is everywhere matched and that the electrical paths leading from the gap to the chamber are as nearly equal in length as possible. When mounted in the oil tank with the Marx generator, the Blumlein is emersed in oil up to the point where the Blumlein and elbow are joined. At this point there is a large bulge in the center electrode of the elbow to compensate 105for the impedance change at the air-oil interface 40. Photograph of the streamer chamber installed in the magnet. The sheet metal rf enclosure at the downstream end of the chamber has been removed for viewing. The lucite supports for the central electrode as well as the carbon-rod terminating resistors are clearly visible. A corona guard encircles the central electrode to prevent breakdown at the edges. The electrode itself consists of 0.25-mm wires spaced 1 cm apart and supported on a 1/4-inch-106 thick aluminum window frame . . . 41. Photograph of a foam cell used in the 2-meter streamer chamber. Each cell is 30 cm deep, 150 cm wide and about 230 cm long at the location of the target. Nylon fishline is used here to space the mylar windows away from individual electrode wires so that breakdown does not occur. In later models, 1/8-inch-diameter lucite rods are used in place of the nylon, and the spacing between the rods is increased to 6 inches. The hydrogen gas target is supported under tension by the lucite fixtures at each end. The target can be pressurized to about 60 psig to enhance the signal-to-background ratio for backgrounds not originating in the target . . 107 42. A K^o decay which occurred in the 2-meter streamer chamber during the first preliminary run in the photon beam 109

Page

- x -

Page

43.	A nuclear interaction event which occurred in the streamer	· .	
	chamber during the first preliminary run in the photon beam	• • •	110

- -

_

Appendix A

A. 1.	DC electric field for breakdown in several gases versus the gas pressure. This figure was obtained originally by A. Kusko and has been recopied from Fig. 2 of the article by J. G. Trump, Ref. 1
A.2.	Breakdown electric field versus pulse duration for several gases. This figure was recopied from the article by P. Felsenthal and J. M. Proud
A.3.	Electric field for pulse breakdown in transformer oil versus the electrode area. These are unpublished data communicated to us by J. C. Martin and I. Smith of AWRE
A.4.	Electric field for pulse breakdown in deionized water versus the electrode area. These are unpublished data communicated to us by J. C. Martin and I. Smith of AWRE
A.5.	Electric field for pulse breakdown in thin sheets of mylar, lucite, and polyethylene versus the sample volume in cm ³ . These are unpublished data communicated to us by J. C. Martin and I. Smith of AWRE
	Appendix B
B.1.	Switch equivalent circuit (a) and the time dependence of the voltage across a triggered gap (b)
в2	Schematic drawing of a triggered spark gap. The trigger needle

B. Z.	Schematic drawing of a triggered spark gap. The trigger needle	
	is located at the center of the lower electrode, and its penetration	
	into the gap can be adjusted by turning the larger threaded shaft	
	to which the needle is attached. A cylindrical ceramic insulator	
	is imbedded in the lucite which surrounds the threaded shaft, and	
	it is used to isolate the trigger needle as it passes through the	
	lower electrode.	131

Appendix C

C.1.	Layout and construction details for the autotransformer developed by J. C. Martin and I. Smith of AWRE	135
C.2.	Three different circuit configurations for the autotransformer developed by J. C. Martin and I. Smith of AWRE	136

C.3.	Equivalent circuit for the autotransformer developed by J. C. Martin and I. Smith of AWRE	138
C.4.	Calculated rise time in nsec for $V_{out}/V_{in} = 800 \text{ kV}/50 \text{ kV}$ versus b_{max} , the maximum width of the tapered autotrans- former winding. Calculations were made for the three circuit configurations indicated and for the transformer radii shown with each curve. Additional parameter values are included in the text	140
C.5.	Calculated output voltage maximized with respect to the number of turns in a center-tap autotransformer versus the output rise time in μ sec. The maximum width b_{max} of the tapered winding, and the radius r identify the different curves. Additional param- eter values are included in the text	141

- - - -

Page

,---

~._
